



## E-DRIV<sup>®</sup> LF-Series

### Brushless Electric Torque Screwdrivers

- Various models that range from 0.8 - 15.6 lbf.in
- High performance Swiss Maxon brushless motor design provides durability and reduces the standard maintenance costs for electric screwdrivers.
- Designed for high production environments. Minimal heat build-up even when tool is operated continuously.
- Over Heat Protection (OHP) and Over Current Protection (OCP) protect driver from damage or malfunction. Features a LED display that signals the tool status for the operator to view.
- Can be connected with the Scout Screw Counter.
- External torque adjustment scale.
- Requires STC 40 transformer (power supply).
- All models are ESD designed and prevent the occurrence of electro static discharge, which improves production yields, manufacturing costs, product quality, product reliability, reputation and profitability.



#### Torque Cover: Item # 145823

Protects the LF-Series tools from incidental or operator tampering of torque setting.

| Model        | Driver Type   | Item # | Torque Ranges |              | RPM  | Grip Dia. | Length | Drive Size | Wt.     | Applicable Screw Size |
|--------------|---------------|--------|---------------|--------------|------|-----------|--------|------------|---------|-----------------------|
|              |               |        | lbf.in        | cN.m         |      |           |        |            |         |                       |
| LF060-A ESD  | Lever Start   | 145897 | 0.8 - 5.2     | 3 - 58.8     | 1550 | 1 1/2"    | 9"     | 1/4 F/Hex  | 15.5 oz | M1.3-M2.8             |
| LF060P-A ESD | Push-to-Start | 145898 | 0.8 - 5.2     | 3 - 58.8     | 1550 | 1 1/2"    | 9"     | 1/4 F/Hex  | 15.5 oz | M1.3-M2.8             |
| LF080-A ESD  | Lever Start   | 145891 | 1.7 - 6.9     | 19.6 - 78.4  | 1250 | 1 1/2"    | 9"     | 1/4 F/Hex  | 15.5 oz | M1.7-M3               |
| LF080P-A ESD | Push-to-Start | 145892 | 1.7 - 6.9     | 19.6 - 78.4  | 1250 | 1 1/2"    | 9"     | 1/4 F/Hex  | 15.5 oz | M1.7-M3               |
| LF120-A ESD  | Lever Start   | 145893 | 2.6 - 10.4    | 29.4 - 117.6 | 1000 | 1 1/2"    | 9"     | 1/4 F/Hex  | 15.5 oz | M2.0-M4               |
| LF120P-A ESD | Push-to-Start | 145894 | 2.6 - 10.4    | 29.4 - 117.6 | 1000 | 1 1/2"    | 9"     | 1/4 F/Hex  | 15.5 oz | M2.0-M4               |
| LF180-A ESD  | Lever Start   | 145895 | 3.5 - 15.6    | 39.3 - 176.6 | 700  | 1 1/2"    | 9"     | 1/4 F/Hex  | 15.5 oz | M2.6-M4               |
| LF180P-A ESD | Push-to-Start | 145896 | 3.5 - 15.6    | 39.3 - 176.6 | 700  | 1 1/2"    | 9"     | 1/4 F/Hex  | 15.5 oz | M2.6-M4               |

## **X-ON Electronics**

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [mountz manufacturer](#):*

Other Similar products are found below :

[280041](#) [145866](#) [280034](#) [EPT250I-A](#) [068106](#) [280035](#)