

# Palm Size Digital Multimeter



## Description

The model multimeter is a 3-3/4 digits with steady operations, fashionable design and highly reliable hand-held measuring instrument. The meter can measure AC/DC current, resistance, transistor hFE, Diode and Continuity. It is an ideal tool for maintenance.



## Features

- Display Count : 4,000
- Auto Range
- Diode Test
- Transistor Test
- Continuity Buzzer
- Low Battery Indication
- Input Impedance for DCV : Around 10MΩ

## Specifications

	Range	Best Accuracy
DC Voltage (V)	400mV/4V/40V/400V/500V	±(0.8%+1)
AC Voltage (V)	4V/40V/400V/500V	±(1.2%+3)
DC Current (A)	400μA/4000μA/40mA/400mA/4A/10A	±(1%+2)
AC Current (A)	400μA/4000μA/40mA/400mA/4A/10A	±(1.5%+5)
Resistance (Ω)	400Ω/4kΩ/40kΩ/400kΩ/4MΩ/40MΩ	±(1%+2)

## General Characteristic

Power	1.5V Cell (R03) × 2
LCD Size	48mm × 16mm
Product Colour	Orange and Grey
Product Net Weight	179g (Including Holster)
Product Size	130mm × 73.5mm × 35mm
Standard Accessories	1.5V Cells, Test Lead, Holster
Safety Rating	CAT II 250V

## Part Number Table

Description	Part Number
Palm Size Digital Multimeter	72-7765

**Important Notice :** This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Tenma is the registered trademark of the Group. © Premier Farnell plc 2012.



# X-ON Electronics

Authorized Distributor

*Click to view similar products for [Tenma manufacturer](#).*

Other Similar products are found below :

[BEBKQRT](#) [7210160727770A](#) [722630](#) [76090](#) [76097](#) [76300](#) [76350](#) [761444](#) [76020](#) [21685](#)  
[7213300](#) [7213768](#) [7214058](#) [7214316](#) [7214320](#) [7214322](#) [ST5C](#) [76270](#) [BECKKRT](#)  
[BECKMRT](#) [7210179727770A](#) [727635](#) [76082](#) [761662](#) [76021](#)