

Bench Type Digital Multimeter



Description

The model is a manual range digital bench-type multimeter with average value display, full function and full range overload protection and a unique design. It can be powered by AC 220V/50Hz or 1.5V cell (R14) × 6. It's your ideal testing meter with superior performance. It is widely used in industrial production and service, technological research and design, college education (laboratory, courses), and automotive industry.

Features

- Display Count : 2,000
- Manual Range
- Diode Test
- Transistor Test
- Continuity Buzzer
- Low Battery Indication
- Data Hold
- LCD Backlight
- Input Impedance for DCV : Around 10MΩ
- Misuse Alarm

Specifications

	Range	Best Accuracy
DC Voltage (V)	200mV/2V/20V/200V/1000V	±(0.5%+2)
AC Voltage (V)	2V/20V/200V/750V	±(0.8%+3)
DC Current (A)	200μA/2mA/20mA/200mA/10A	±(0.8%+2)
AC Current (A)	2mA/20mA/200mA/10A	±(1.0%+3)
Resistance (Ω)	200Ω/2kΩ/20kΩ/200kΩ/2MΩ/20MΩ	±(0.8%+3)
Capacitance (F)	20nF/2μF/200μF	±(4%+3)
Frequency (Hz)	2kHz/200kHz	±(1.5%+5)
Temperature (°C)	-40°C to 1000°C	±(1.2%+3)

General Characteristic

Power	AC 220V/50Hz or 1.5V Cell (R14) × 6
LCD Size	108mm × 34.5mm
Product Colour	Orange and Grey
Product Net Weight	1650g
Product Size	300mm × 245mm × 105mm
Standard Accessories	1.5V Cell, Test Lead, Alligator Clip, Point Contact Temperature Probe, Multi-Purpose Socket, AC 220V Power Cord, Power Adapter
Safety Rating	CAT II 1000V

Part Number Table

Description	Part Number
Bench Type Digital Multimeter	72-8715

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Tenma is the registered trademark of the Group. © Premier Farnell plc 2012.



X-ON Electronics

Authorized Distributor

Click to view similar products for [Tenma manufacturer](#).

Other Similar products are found below :

[BEBKQRT](#) [7210160727770A](#) [722630](#) [76090](#) [76097](#) [76300](#) [76350](#) [761444](#) [76020](#) [21685](#)
[7213300](#) [7213768](#) [7214058](#) [7214316](#) [7214320](#) [7214322](#) [ST5C](#) [76270](#) [BECKKRT](#)
[BECKMRT](#) [7210179727770A](#) [727635](#) [76082](#) [761662](#) [76021](#)