


Rx Series Diagonal cutters Oval head, RX 8130-RX 8162

These cutters are made from high performance ball bearing steel, black oxidised. Numerically controlled machine grinding guarantees edge angle accuracy and contact which increases the tools reliability and consistency.

Precision induction hardened edges 63-65 HRC. Handles in two component synthetic material and come with return spring. The cutting capacity that is given is for copper wire!

These Oval Head cutters are ideal for wire harness work and standard printed circuit board assembly.



| | | | | A mm | B mm | C mm | D mm | F mm | | | |
|---------|--|---------|----|----------------|----------------|----------------|----------------|----------------|----------|-------|----|
| RX 8130 | | 0103003 | 1 | 133.5 | 8.5 | 8.0 | 5 | 0.8 | 0.2-1.0 | Micro | 68 |
| RX 8131 | | 0103010 | 1 | 133.5 | 8.5 | 8.0 | 5 | 0.8 | 0.1-1.0 | Flush | 68 |
| RX 8132 | | 0103027 | 1 | 133.5 | 8.5 | 8.0 | 5 | 0.8 | 0.1-0.8 | Ultra | 68 |
| RX 8140 | | 0103034 | 1 | 135.5 | 10.5 | 10.0 | 6 | 0.8 | 0.2-1.25 | Micro | 70 |
| RX 8141 | | 0103041 | 1 | 135.5 | 10.5 | 10.0 | 6 | 0.8 | 0.1-1.25 | Flush | 70 |
| RX 8142 | | 0103058 | 1 | 135.5 | 10.5 | 10.0 | 6 | 0.8 | 0.1-1.0 | Ultra | 70 |
| RX 8150 | | 0103133 | 1 | 138.0 | 13.0 | 12.5 | 6 | 1.2 | 0.3-1.6 | Micro | 73 |
| RX 8151 | | 0103140 | 1 | 138.0 | 13.0 | 12.5 | 6 | 1.2 | 0.2-1.6 | Flush | 73 |
| RX 8152 | | 0103157 | 1 | 138.0 | 13.0 | 12.5 | 6 | 1.2 | 0.2-1.25 | Ultra | 73 |
| RX 8160 | | 0111534 | 10 | 147.0 | 16.0 | 16.0 | 8 | 1.6 | 0.4-2.0 | Micro | 97 |
| RX 8161 | | 0111541 | 10 | 147.0 | 16.0 | 16.0 | 8 | 1.6 | 0.3-2.0 | Flush | 97 |
| RX 8162 | | 0111558 | 10 | 147.0 | 16.0 | 16.0 | 8 | 1.6 | 0.3-1.6 | Ultra | 97 |

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [erg manufacturer](#):

Other Similar products are found below :

[BE-8610](#) [BE-8705](#) [SDC-4-023](#) [4239](#) [BE-7806](#) [BE-8702](#) [BE-8706](#) [BE-8160](#) [BE-8801](#) [BE-8910](#) [BE-7808](#) [BE-8620](#) [BE-8350](#) [BE-8602](#) [BE-7804](#) [BE-8907](#) [RX8141](#) [4131](#) [2101G-160](#) [2427G160](#) [BE-8802](#) [BE-8601](#) [BE-8908](#) [BE-8040](#) [BE-7807](#) [9070](#) [020741E](#) [DS16C1-8](#) [DS16C4-2](#) [ERG16-412/2](#) [SDS-4-023](#) [SDS-10-014](#) [ERG10-412/6](#) [SDD-2-023](#) [ERG10-412/2](#) [JSA4-1-G0](#)