

Data Sheet

Tag_types.pdf

1 Page

Last Revised 06-01-06

Summary of supported passive transponders (smart cards, tags etc)

Transponder type	Frequency	Memory size (bytes) Total/user	Communication rate (baud)	Security	Key features and typical application
Hitag 1	125 kHz	256/192	up to 4k	Yes, data encryption	Read/Write (General purpose)
Hitag S256/2048*	125 kHz	256/256	up to 4k	Yes, data encryption and password	Read/Write (General purpose)
Hitag 2	125 kHz	32/16	up to 4k	Yes, password exchange	Read/Write (Secure access, asset tracking)
EM4001/4102 (UNIQUE tag)	125 kHz	8/5	up to 4k	No	Read-only (Access control)
MCRF200/123	125 kHz	16/14	up to 4k	No	Read-only (Access control)
Mifare 1k	13.56 MHz	1024/768 (16 individual segments)	up to 106k	Yes, multiple keycodes and Crypto	Read/Write (secure multi-application card, payment, access)
Mifare 4k	13.56 MHz	4096/3456 (40 individual segments)	up to 106k	Yes, multiple keycodes and Crypto	Read/Write (secure multi-application card, payment, access)
Ultralight	13.56 MHz	64/48	up to 106k	No	Read/Write (low-cost payment)
ICODE SLI (ISO15693)	13.56 MHz	128/112	Up to 53k	No	Read/Write (low-cost asset tracking, smart labels)

*Hitag S supported in plain memory mode at present (Philips default)

<http://www.ibtechnology.co.uk>

sales@ibtechnology.co.uk

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [rf solutions manufacturer](#):

Other Similar products are found below :

[FOBBER-8T2](#) [ZULU-868](#) [ANT-PCB4520-FL](#) [GAMMA-868-SO](#) [DB5XA](#) [ZULUEVAL-M](#) [DELTA-TRX8C1](#) [LAMBDA62C-9D](#)
[LAMBDA80-24D](#) [ADP-SMAFRP-SMAF](#) [GAMMA-868R-SO](#) [GAMMA-868R](#) [KAPPAM-ARD](#) [ICEPIC](#) [FLEXI-SMA-868](#) [FM-RTFQ2-433P](#) [DB756](#) [KAPPA-R868-SO](#) [ZETA-ARD-868](#) [ZULUEVAL-DONGLE](#) [ZETAPLUS-915-D](#) [TRAP-T1](#) [ANT-GROD8-NSMA](#) [ZPT-4RS](#)
[ADP-SMAM-NF](#) [HORNET200-TX1](#) [EZTEXT](#) [ICEPIC3-US](#) [I3-TRACER1](#) [ZULU-M-ARDUINO](#) [GAMMA-915R](#) [RFM68W-433-S2](#)
[KAPPAT-ARD](#) [I3DBF77](#) [ALPHA-TRX433S](#) [ZETAPLUS-915-SO](#) [ZETAPLUS-433-D](#) [ANT-24G-DPL-SMA](#) [FOBLOQF-4S2](#) [ADP-SMAM-2SMAF](#) [CBA-SMAF-OP](#) [ANT-MCLING3-N](#) [RF600E](#) [HORNETPRO-8S3](#) [ADP-SMAF-SMAF](#) [ZETA-868-SO](#) [CF-WU710NV2](#) [BRAVO-ARD](#) [LAMBDA62-8D](#) [110C2-433A](#)