



Panasonic
ideas for life

Panasonic PLC Starter Kit (KITGT05FPXC30R)

Contents:	- PLC FPXC30R and the programming software Control FPCWIN Pro
	- 3.5" touch panel GT05 and programming software GTWIN
	- TB-SYMKEYS: User library with flow diagram symbols and switch elements for GT touch terminals
	- USB programming cable for PLC and HMI, cable to connect the FP-X and GT05, power supply cable

GT05 Touch panel (AIG05GQ02D)

Power supply	24V DC
Display	3,5" (71 x 53,3mm)
Display colour	2 colors (black/white)
Resolution	320 x 240 Pixel
Backlight	3-color LED (green/orange/red)
Display characters	Up to 53 x 30 characters. Depends on character size.
Memory capacity	2048kB
Clock	Realtime clock with calendar (Battery "AFPXBATTJ" not included)
USB port for programming	Yes
Port for PLC	RS232C
SD/SDHC memory card slot	Yes (for datalogging, recipes, program up/download ...)

FP-X PLC (FPXC30R)

Number of inputs	16 (24V DC)
Number of outputs	14 relays
Output capacity	2A
Digital I/Os (max.)	352
Processing speed	0.32µs/step (basic instruction)
Program capacity	32000 steps
Data register (DT)	32765 words
Memory type	Built-in Flash-ROM
High-speed counter	Input of main unit: 1-phase: 8 channel, 10kHz each; 2-phase: 4 channel, 5kHz each
Ports	1 x RS232 port 1 x Mini USB port
Other functions	Password (4 digits, 8 digits), upload protection, comment storage (328kByte)
Operating voltage	100 to 240V DC (± 10%)
Service power output	24V DC, 400mA

Panasonic Electric Works Europe AG

Rudolf-Diesel-Ring 2
83607 Holzkirchen
Tel: +49-(0)8024-648-0
Fax: +49-(0)8024-648-111
e-mail: info-eu@eu.pewg.panasonic.com
www.panasonic-electric-works.com

Panasonic®

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [panasonic](#) manufacturer:

Other Similar products are found below :

[ECE-A1HKAR47](#) [ELK-EA102FA](#) [ELC-09D151F](#) [EEC-S0HD224H](#) [ELL-5PS3R3N](#) [HC2-H-DC48V-F](#) [HL2-HP-AC120V-F](#) [HL2-H-DC12V-F](#) [HL2-HP-DC12V-F](#) [HL2-HP-DC6V-F](#) [HL2-HP-DC24V-F](#) [HC4-H-DC24V](#) [HL2-HTM-DC24V-F](#) [HL2-HTM-AC24V-F](#) [HC4-H-AC24V](#) [HC4-H-AC120V](#) [EEC-RG0V155H](#) [AZH2031](#) [RP-SDMF64DA1](#) [EEF-UD0K101R](#) [EVM-F6SA00B55](#) [RP-SMLE08DA1](#) [ELC-12D101E](#) [ERA-3YEB272V](#) [EEC-RF0V684](#) [ERA-3YEB153V](#) [ELC-3FN2R2N](#) [ERA-3YEB512V](#) [ERJ-1GEJ564C](#) [ERZ-V20R391](#) [ETQ-P3W3R3WFN](#) [ELL-ATV681M](#) [ELK-EA100FA](#) [EEF-UD0J101R](#) [LC-R121R3P](#) [ERA-3YEB303V](#) [ERZ-V05V680CB](#) [EEF-UE0K101R](#) [ELK-E101FA](#) [EEC-S0HD224V](#) [EVQ-PAC05R](#) [ELK-EA222FA](#) [LT4H-DC24V](#) [LT4HL8-AC24V](#) [LT4HW-AC24V](#) [LT4HWT8-AC240V](#) [LT4HWT-AC240VS](#) [CX-444-P-Z](#) [CY-122A-P](#) [ETQ-P5M470YFM](#)