


Central
Semiconductor Corp.

Central
Semiconductor Corp.

Central
Semiconductor Corp.

Central
Semiconductor Corp.

145 Adams Avenue
Hauppauge, New York 11788



2N5172 NPN TO-92 (ECB)
2N6076 PNP TO-92 (ECB)
MPS5172 NPN TO-92 (EBC)
MPS6076 PNP TO-92 (EBC)
COMPLEMENTARY SILICON TRANSISTOR

JEDEC TO-92 CASE

DESCRIPTION

The CENTRAL SEMICONDUCTOR 2N/MPS5172, 2N/MPS6076 types are Silicon Complementary Small Signal Transistors designed for general purpose applications.

MAXIMUM RATINGS ($T_A=25^\circ\text{C}$)

	SYMBOL		UNIT
Collector-Base Voltage	V_{CB0}	25	V
Collector-Emitter Voltage	V_{CE0}	25	V
Emitter-Base Voltage	V_{EB0}	5.0	V
Collector Current	I_C	100	mA
Power Dissipation	P_D	625	mW
Operating and Storage Junction Temperature	T_J, T_{STG}	-65 TO +150	$^\circ\text{C}$

ELECTRICAL CHARACTERISTICS ($T_A=25^\circ\text{C}$ unless otherwise noted)

SYMBOL	TEST CONDITIONS	MIN	MAX	UNIT
I_{CBO}	$V_{CB}=25\text{V}$		100	nA
I_{CBO}	$V_{CB}=25\text{V}, T_A=100^\circ\text{C}$		10	μA
I_{CES}	$V_{CB}=25\text{V}$		100	nA
I_{EBO}	$V_{EB}=5.0\text{V}$ (2N5172)		100	nA
I_{EBO}	$V_{EB}=3.0\text{V}$ (2N6076)		100	nA
BV_{CEO}	$I_C=10\text{mA}$	25		V
$V_{CE(SAT)}$	$I_C=10\text{mA}, I_B=1.0\text{mA}$		0.25	V
$V_{BE(SAT)}$	$I_C=10\text{mA}, I_B=1.0\text{mA}$		0.80	V
$V_{BE(ON)}$	$V_{CE}=10\text{V}, I_C=10\text{mA}$	0.5	1.2	V
h_{FE}	$V_{CE}=10\text{V}, I_C=10\text{mA}$	100	500	
h_{fe}	$V_{CE}=10\text{V}, I_C=10\text{mA}, f=1.0\text{kHz}$	100	750	
f_T	$V_{CB}=5.0\text{V}, I_C=2.0\text{mA}$		200TYP	MHz
C_{ob}	$V_{CB}=10\text{V}, I_E=0, f=1.0\text{MHz}$	1.0	13	pF

CentralTM
Semiconductor Corp.

145 Adams Avenue
Hauppauge, NY 11788 USA
Tel: (631) 435-1110 • Fax: (631) 435-1824
www.centralsemi.com

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Bipolar Transistors - BJT category](#):

Click to view products by [Central Semiconductor manufacturer](#):

Other Similar products are found below :

[619691C](#) [MCH4017-TL-H](#) [MJ15024/WS](#) [MJ15025/WS](#) [BC546/116](#) [BC556/FSC](#) [BC557/116](#) [BSW67A](#) [HN7G01FU-A\(T5L,F,T](#)
[NJVMJD148T4G](#) [NSVMMBT6520LT1G](#) [NTE187A](#) [NTE195A](#) [NTE2302](#) [NTE2330](#) [NTE2353](#) [NTE316](#) [IMX9T110](#) [NTE63](#) [NTE65](#)
[C4460](#) [SBC846BLT3G](#) [2SA1419T-TD-H](#) [2SA1721-O\(TE85L,F\)](#) [2SA1727TLP](#) [2SA2126-E](#) [2SB1202T-TL-E](#) [2SB1204S-TL-E](#) [2SC5488A-](#)
[TL-H](#) [2SD2150T100R](#) [SP000011176](#) [FMC5AT148](#) [2N2369ADCSM](#) [2SB1202S-TL-E](#) [2SC2412KT146S](#) [2SC4618TLN](#) [2SC5490A-TL-H](#)
[2SD1816S-TL-E](#) [2SD1816T-TL-E](#) [CMXT2207 TR](#) [CPH6501-TL-E](#) [MCH4021-TL-E](#) [BC557B](#) [TTC012\(Q\)](#) [BULD128DT4](#) [JANTX2N3810](#)
[Jantx2N5416](#) [US6T6TR](#) [KSF350](#) [068071B](#)