


Central  
Semiconductor Corp.  
Central  
Semiconductor Corp.  
Central  
Semiconductor Corp.  
**Central™  
Semiconductor Corp.**

145 Adams Avenue  
Hauppauge, New York 11788



MJ2500 MJ2501 PNP  
MJ3000 MJ3001 NPN

SILICON COMPLEMENTARY TRANSISTORS  
POWER DARLINGTON  
10 AMPERES, 60-80 VOLTS

JEDEC TO-3 CASE

## DESCRIPTION

The CENTRAL SEMICONDUCTOR MJ2500, MJ3000 Series are medium-power Complementary Silicon Darlington Transistors designed for general purpose amplifier applications as complementary output devices.

## MAXIMUM RATINGS ( $T_C=25^{\circ}\text{C}$ )

	SYMBOL	MJ2500 MJ3000	MJ2501 MJ3001	UNIT
Collector-Base Voltage	$V_{CB0}$	60	80	V
Collector-Emitter Voltage	$V_{CE0}$	60	80	V
Emitter-Base Voltage	$V_{EB0}$	5.0	5.0	V
Collector Current	$I_C$	10	10	A
Base Current	$I_B$	0.2	0.2	A
Power Dissipation	$P_D$	150	150	W
Operating and Storage Junction Temperature	$T_J, T_{stg}$	-55 TO +200		$^{\circ}\text{C}$
Thermal Resistance, Junction TO Case	$\theta_{JC}$	1.17		$^{\circ}\text{C}/\text{W}$

## ELECTRICAL CHARACTERISTICS ( $T_C=25^{\circ}\text{C}$ unless otherwise noted)

SYMBOL	TEST CONDITIONS	MJ2500 MJ3000		MJ2501 MJ3001		UNIT
		MIN	MAX	MIN	MAX	
$I_{CER}$	$V_{CE}=\text{Rated}, R_{BE}=1,000\Omega$		1.0		1.0	mA
$I_{CER}$	$V_{CE}=\text{Rated}, R_{BE}=1,000\Omega, T_C=150^{\circ}\text{C}$		5.0		5.0	mA
$I_{CEO}$	$V_{CE}=\frac{1}{2} \times \text{Rated } V_{CE}$		1.0		1.0	mA
$I_{EBO}$	$V_{EB}=5.0\text{V}$		2.0		2.0	mA
$BV_{CEO}$	$I_C=100\text{mA}$	60		80		V
$V_{CE}(\text{SAT})$	$I_C=5.0\text{A}, I_B=20\text{mA}$		2.0		2.0	V
$V_{CE}(\text{SAT})$	$I_C=10\text{A}, I_B=50\text{mA}$		4.0		4.0	V
$V_{BE}(\text{on})$	$V_{CE}=3.0\text{V}, I_C=5.0\text{A}$		3.0		3.0	V
$h_{fe}$	$V_{CE}=3.0\text{V}, I_C=5.0\text{A}$	1000		1000		-



## OUTSTANDING SUPPORT AND SUPERIOR SERVICES

---

### PRODUCT SUPPORT

Central's operations team provides the highest level of support to insure product is delivered on-time.

- Supply management (Customer portals)
- Inventory bonding
- Consolidated shipping options
- Custom bar coding for shipments
- Custom product packing

---

### DESIGNER SUPPORT/SERVICES

Central's applications engineering team is ready to discuss your design challenges. Just ask.

- Free quick ship samples (2<sup>nd</sup> day air)
- Online technical data and parametric search
- SPICE models
- Custom electrical curves
- Environmental regulation compliance
- Customer specific screening
- Up-screening capabilities
- Special wafer diffusions
- PbSn plating options
- Package details
- Application notes
- Application and design sample kits
- Custom product and package development

---

### REQUESTING PRODUCT PLATING

1. If requesting Tin/Lead plated devices, add the suffix " TIN/LEAD" to the part number when ordering (example: 2N2222A TIN/LEAD).
2. If requesting Lead (Pb) Free plated devices, add the suffix " PBFREE" to the part number when ordering (example: 2N2222A PBFREE).

---

### CONTACT US

#### Corporate Headquarters & Customer Support Team

Central Semiconductor Corp.  
145 Adams Avenue  
Hauppauge, NY 11788 USA  
Main Tel: (631) 435-1110  
Main Fax: (631) 435-1824  
Support Team Fax: (631) 435-3388  
[www.centrasemi.com](http://www.centrasemi.com)

**Worldwide Field Representatives:**  
[www.centrasemi.com/wwreps](http://www.centrasemi.com/wwreps)

**Worldwide Distributors:**  
[www.centrasemi.com/wwdistributors](http://www.centrasemi.com/wwdistributors)

---

For the latest version of Central Semiconductor's **LIMITATIONS AND DAMAGES DISCLAIMER**, which is part of Central's Standard Terms and Conditions of sale, visit: [www.centrasemi.com/terms](http://www.centrasemi.com/terms)

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Bipolar Transistors - BJT category](#):*

*Click to view products by [Central Semiconductor manufacturer](#):*

Other Similar products are found below :

[619691C](#) [MCH4017-TL-H](#) [MJ15024/WS](#) [MJ15025/WS](#) [BC546/116](#) [BC556/FSC](#) [BC557/116](#) [BSW67A](#) [HN7G01FU-A\(T5L,F,T](#)  
[NJVMJD148T4G](#) [NSVMMBT6520LT1G](#) [NTE187A](#) [NTE195A](#) [NTE2302](#) [NTE2330](#) [NTE2353](#) [NTE316](#) [IMX9T110](#) [NTE63](#) [NTE65](#)  
[C4460](#) [SBC846BLT3G](#) [2SA1419T-TD-H](#) [2SA1721-O\(TE85L,F\)](#) [2SA1727TLP](#) [2SA2126-E](#) [2SB1202T-TL-E](#) [2SB1204S-TL-E](#) [2SC5488A-](#)  
[TL-H](#) [2SD2150T100R](#) [SP000011176](#) [FMC5AT148](#) [2N2369ADCSM](#) [2SB1202S-TL-E](#) [2SC2412KT146S](#) [2SC4618TLN](#) [2SC5490A-TL-H](#)  
[2SD1816S-TL-E](#) [2SD1816T-TL-E](#) [CMXT2207 TR](#) [CPH6501-TL-E](#) [MCH4021-TL-E](#) [BC557B](#) [TTC012\(Q\)](#) [BULD128DT4](#) [JANTX2N3810](#)  
[Jantx2N5416](#) [US6T6TR](#) [KSF350](#) [068071B](#)