

## RF TERMINATION Type 65\_BNC-75-0-1

### Description

Standard Termination, Low Power



### Product Configuration

Connector	BNC plug (male)
Interface standards	IEC 60169-8_MIL-STD-348A/301_CECC 22120

### Technical Data

#### Electrical Data

Nominal Impedance	75 $\Omega$
Frequency range	0 to 1 GHz
VSWR max.	1.1
Power rating	1 Watt average power up to 30 °C ambient temperature, linearly derated to 0 Watt at 130 °C ambient temperature. 800 Watt peak power

#### Mechanical Data

Weight	0.014 kg
--------	----------

#### Environmental Data

Operating temperature 2011/65/EU (RoHS)	-40 °C to 130 °C compliant
--	-------------------------------

#### Material Data

Piece Part	Material	Surface Plating
Centre contact	Brass	Gold Plating (Nickel underplated)
Outer contact	Brass	SUCOPLATE (R) Plating
Body	Brass	SUCOPLATE (R) Plating
Insulator	PFA / PTFE	
Coupling nut	Brass	SUCOPLATE (R) Plating

### Related Documents

Outline drawing	DOU-00020116
-----------------	--------------

### Ordering Information

Single Packaging Packaging	65_BNC-75-0-1/133_NE
-------------------------------	----------------------

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [RF Terminators](#) category:*

*Click to view products by [Huber & Suhner](#) manufacturer:*

Other Similar products are found below :

[M39030/3-09S](#) [M39030/3-01S](#) [M39030/3-04N](#) [M39030/3-11N](#) [M39030/3-11S](#) [TNA2-50](#) [TNGFL1-1-78](#) [R4042N5000](#) [32S17B-1.0E3](#)  
[28S1ER-001N5](#) [NF-C-1\(40\)](#) [53S1RR-001N3](#) [142275](#) [56S1RR-001N4](#) [18S15R-0.5E3](#) [65\\_BNC-50-0-7/133\\_NE](#) [71S1RR-001N4](#) [02S17R-](#)  
[001D3](#) [6500.19.A](#) [R404240120](#) [HT-50-1\(40\)](#) [NF-A-PJ-1\(40\)](#) [R404260000](#) [NF-TMJ-P\(50\)](#) [HT-10-2](#) [000-1075](#) [DCA-17-01](#) [27-9245](#)  
[M85049/124-13N](#) [R4041D1000](#) [1-221629-6](#) [SF8015-6007](#) [R4041D2121](#) [R4041D2000](#) [R4041D1121](#) [65010\\_N-50-1/199\\_NE](#) [65\\_N-75-0-](#)  
[11/133\\_NE](#) [SF8016-6404](#) [6550.17.AA](#) [65\\_N-50-0-51/113\\_NE](#) [65\\_BNC-50-0-2/133\\_NE](#) [6560.41.AA](#) [65\\_QMA-50-0-4/111\\_NE](#) [65\\_N-50-0-](#)  
[1/133\\_NE](#) [65002\\_N-50-1/122\\_NE](#) [65\\_SMB-50-0-31/111\\_NE](#) [65\\_BNC-50-0-6/113\\_NE](#) [2702702](#) [1100.19.0001](#) [6701.01.B](#)