

400A AC Clamp Meter + NCV

Integrated Non-Contact Voltage Detector

To quickly check for the presence of live wires before testing plus 40A and 400A current ranges

Features:

- Built-in non-contact Voltage detector with LED alert
- 4000 count, backlit LCD display
- 1.2" (30mm) jaw size for conductors up to 350MCM
- Includes Multimeter functions AC/DC Voltage, Resistance, Capacitance, Frequency, Temperature, Duty Cycle, Diode, and Continuity
- Relative Mode for Capacitance Zero and Offset Adjustment
- Data Hold
- Auto Power Off
- Complete with test leads, general purpose Type K bead wire temperature probe, two AAA batteries, and carrying case



Built-in non-contact Voltage detector with LED alert



Compact size allows measurements in tight locations

Specifications	Range	Max. Resolution	Basic Accuracy (% readings+digits)
Display counts	4000		
AC Current	40.00A, 400.0A	0.01A	±(2.5% + 8d)
AC Voltage	4.000V, 40.00V, 400.0V, 600V	0.001V	±(1.8% + 8d)
DC Voltage	400.0mV, 4.000V, 40.00V, 400.0V, 600V	0.1mV	±(0.8% + 2d)
Resistance	400.0Ω, 4.000kΩ, 40.00kΩ, 400.0kΩ, 4.000MΩ, 40.00MΩ	0.1Ω	±(0.8% + 2d)
Frequency	10Hz to 10kHz	0.01Hz	±(1.5% + 2d)
Capacitance	40.00nF, 400.0nF, 40.00μF, 100.0μF	0.01nF	±(3.0% + 5d)
Temperature	-4 to 1400°F (-20 to 760°C)	0.1°	±(3% + 9°F/5°C)
Duty Cycle	0.5 to 99.0%	0.1%	±(1.2% + 2d)
Diode	Yes		
Continuity	Yes		
Dimensions	7.9x2.6x1.5" (200x66x37mm)		
Weight	7.2oz (205g)		

Ordering Information

MA410400A AC Clamp Meter + NCV
MA410-NIST.....MA410 with Calibration Traceable to NIST



X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Clamp Multimeters & Accessories](#) category:

Click to view products by [Extech](#) manufacturer:

Other Similar products are found below :

[I800](#) [FLUKE 1630-2](#) [ZAPDUMOD-03](#) [ZARKMS-01-99](#) [UT233](#) [TESTO 770-3](#) [0590 7703](#) [AX-3550](#) [AX-M266C](#) [BM079](#) [BM089](#) [BM157](#)
[BM162](#) [BM197](#) [KEW2210R](#) [FLUKE 80I-110S](#) [FLUKE I200](#) [FLUKE I200S](#) [FLUKE I3000FLEX-24](#) [FLUKE I310S](#) [FLUKE I400](#) [CIE600](#)
[TESTO 770-2](#) [0590 7702](#) [34194A](#) [KEW2433R](#) [KEW8112](#) [FLUKE 772](#) [380976-K](#) [MA3110](#) [MA440](#) [MA443](#) [MA445](#) [FLUKE-374 FC](#)
[TA74](#) [AMP-320](#) [CM55](#) [CM46](#) [I200](#) [ACD-6 PRO](#) [FLUKE-1630-2FC](#) [I410](#) [CM44](#) [CM42](#) [FLK-A3000 FC](#) [FLUKE-376 FC](#) [ACD-14-PRO](#)
[MA610](#) [F201](#) [F205](#) [MA193 \(250 MM\)](#) [DIGIFLEX 4000A 350MM](#)