



## 600A Clamp Multimeters

Amprobe's ACD-10 PLUS meters offer thinner jaws over standard clamp meters. Allowing access to tight measurement areas and still accommodating conductors up to 25 mm (1 in). Both meters also measure Capacitance and Frequency. Frequency is measured by either jaws or test leads. Very versatile clamp multimeters.

### ACD-10 PLUS, ACD-10 TRMS-PLUS Clamp Multimeters with Unique Thin Jaws

- TRMS Measurement (ACD-10 TRMS PLUS only)
- AC and DC Voltage to 600V
- AC Current to 600A
- Resistance to 40 MΩ with Continuity Buzzer
- Capacitance to 3000 μF
- Frequency measurement
- Hold & Maximum reading functions
- Auto ranging
- Thinner jaws (approx 6.35mm thinner)
- In Rush Current
- Jaw opening 25 mm
- Safety acc. EN 61010, CAT III/600 V

FEATURES	ACD-10 TRMS-PLUS	ACD-10 PLUS
TRMS Measurement	Yes	N/A
AC Voltage	4.000, 40.00, 400.0, 600V	
DC Voltage	400.0m, 4.000, 40.00, 400.0, 600V	
AC Current	40.00, 400.0, 600A	
Resistance with Continuity Buzzer	0-400.0 Ω, 4.000 kΩ, 40.00 kΩ, 400.0 kΩ, 4.000 MΩ, 40.00 MΩ	
Capacitance	500.0nF, 5.000μF, 50.00μF, 500.0μF, 3000μF	
Frequency (Using Jaw or Test Leads)	40-400Hz with Jaw, 10Hz to 100kHz with test leads	

- 400 A AC range
- 600 V AC and range (AC40B)
- 4000-count display with bargraph
- 10mA resolution in lowest range
- 

- Data Hold
- Auto power-off
- Jaw opening 25 mm
- Safety EN 61010, CAT III/600 V

## 400A Clamp Multimeters

The ACD-14 Plus is the professionals' choice for both HVAC & Electrical applications due to its complete set of measuring features. Its dual displays allows viewing amperage and voltage measurements simultaneously.

### ACD-14 PLUS, ACD-14 TRMS-PLUS Digital Clamp Multimeters

- TRMS Measurement (ACD-14 TRMS-PLUS only)
- Dual Displays - Permits simultaneous reading of Amperage & Voltage
- Micro Amps measurement for testing "Flame Sensors"
- Capacitance to 3000 μF
- Temperature w/Type-K Thermocouple
- AC and DC Voltage to 600V
- AC current to 400A
- Resistance to 40MΩ
- Continuity Buzzer
- Frequency Measurement
- Auto Power Off
- Auto Ranging
- Hold & Maximum Readings
- In Rush Current
- Jaw opening 26 mm
- Safety acc. EN 61010, CAT III/600 V



This versatile clamp multimeter offers numerous measurement features in a professional sized package. Versatile and rugged for facility maintenance to field service.

### ACDC-400 Digital AC/DC Clamp Multimeter

- AC/DC Current up to 400A
- AC/DC Voltage up to 600V
- Resistance measurement
- Continuity test
- Data Hold
- MAX/MIN recording
- Relative measurement
- Backlight
- Analog bargraph
- Auto or Manual range selection
- "Third hand" - test probe holder
- Jaw opening 30 mm
- Safety acc. EN 61010, CAT III/600 V

FEATURES	ACD-14 FX	ACD-14 TRMS-FX	ACDC-400
TRMS Measurement	N/A	Yes	N/A
AC Voltage	4.000, 40.00, 400.0, 600 V		400.0 m, 4.000, 40.00, 400.0, 600 V
DC Voltage	4.000, 40.00, 400.0, 600 V		400.0 m, 4.000, 40.00, 400.0, 600 V
AC Current	40.00 / 400.0 A		40.00 / 400.0 A
DC Current	N/A		40.00 / 400.0 A
AC/DC Micro Amps (Using Test Leads)	400μA, 2000 μA		N/A
Resistance with Continuity Buzzer	0-400.0 Ω, 4.000 kΩ, 40.00 kΩ, 400.0 kΩ, 4.000MΩ, 40.00 MΩ		
Capacitance	500.0nF, 5.000μF, 50.00μF, 500.0μF, 3000μF		N/A
Frequency (Using Jaw or Test Leads)	10Hz to 100kHz		N/A
Temperature	-20°C to 300°C		N/A



## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Clamp Multimeters & Accessories](#) category:*

*Click to view products by [Beha-Amprobe](#) manufacturer:*

Other Similar products are found below :

[I800](#) [FLUKE 1630-2](#) [ZAPDUMOD-03](#) [ZARKMS-01-99](#) [UT233](#) [TESTO 770-3](#) [0590 7703](#) [AX-3550](#) [AX-M266C](#) [BM079](#) [BM089](#) [BM157](#)  
[BM162](#) [BM197](#) [KEW2210R](#) [FLUKE 80I-110S](#) [FLUKE I200](#) [FLUKE I200S](#) [FLUKE I3000FLEX-24](#) [FLUKE I310S](#) [FLUKE I400](#) [CIE600](#)  
[TESTO 770-2](#) [0590 7702](#) [34194A](#) [KEW2433R](#) [KEW8112](#) [FLUKE 772](#) [380976-K](#) [MA3110](#) [MA440](#) [MA443](#) [MA445](#) [FLUKE-374 FC](#)  
[TA74](#) [AMP-320](#) [CM55](#) [CM46](#) [I200](#) [ACD-6 PRO](#) [FLUKE-1630-2FC](#) [I410](#) [CM44](#) [CM42](#) [FLK-A3000 FC](#) [FLUKE-376 FC](#) [ACD-14-PRO](#)  
[MA610](#) [F201](#) [F205](#) [MA193 \(250 MM\)](#) [DIGIFLEX 4000A 350MM](#)