

Hold-Down Springs and Clips Selection Guide

DIN Rail Snap-Mount Sockets

Socket Part No.	Applicable Relays, Timer	Hold-Down Spring	Hold-Down Clip
SR2P-05 SR2P-05C	RR2P, RAPP, RBPP	SR2B-02F1	SFA-203
	RTE-P1, GT3, GT5P	—	SFA-203
SR2P-06	RR2P, RAPP, RBPP	SR2B-02F1	SFA-202
	GT3 (8-pin), RTE-P1, GT5P	—	SFA-202
SR3P-05 SR3P-05C	RR3PA	SR3B-02F1	SFA-203
	RR2KP	SR3P-06F3	SFA-203
	RTE-P2, GT3 (11-pin)	—	SFA-203
SR3P-06	RR3PA	SR3B-02F1	SFA-202
	RR2KP	SR3P-06F3	SFA-202
	RTE-P2, GT3 (11-pin)	—	SFA-202
SR3B-05	RR1BA, RR2BA, RR3B, RTE-B	SR3B-02F1	SFA-202
SH1B-05 SH1B-05C	RH1B, RAHB, RBHB	SY2S-02F1	SFA-101 SFA-202
SH2B-05 SH2B-05C	RH2B, RAMB, RBMB	SY4S-02F1	SFA-101 SFA-202
SH3B-05 SH3B-05C	RH3B, RH2LB	SH3B-05F1	SFA-101 SFA-202
SH4B-05 SH4B-05C	RH4B	SH4B-02F1	SFA-101 SFA-202
SY2S-05 SY2S-05C	RY2S, RY22S	SY2S-02F1	SFA-101 SFA-202
SY4S-05 SY4S-05C	RY4S, RY42S, RY2LS, RM2S	SY4S-51F1	SFA-101 SFA-202
	RY2KS, GT5Y	(SY4S-51F3)	SFA-202

Panel and PC Board Mount Sockets

Socket Part No.	Applicable Relays, Timer	Hold-Down Spring	Hold-Down Clip
SR2P-51	RR2P, RAPP, RBPP	SR3P-01F1	—
	GT3 (8-pin), RTE-P1	—	SFA-402
SR3P-51	RR3PA	SR3P-01F1	—
	RR2KP	SR3P-51F3	—
	GT3 (11-pin), RTE-P2	—	SFA-402
SR3B-51	RR1BA, RR2BA, RR3B, RTE-B	SR3B-02F1	—
SH1B-51 SH1B-62	RH1B, RAHB, RBHB	SY4S-51F1	SFA-301 SFA-302
SH2B-51	RH2B, RAMB, RBMB	SY4S-51F1 (SY4S-02F1)	SFA-301 SFA-302
SH2B-62	RH2B, RAMB, RBMB	SY4S-51F1 (SY4S-02F1)	—
SH3B-51 SH3B-62	RH3B, RH2LB	SY4S-51F1 (SY4S-02F1)	SFA-301 SFA-302
SH4B-51 SH4B-62	RH4B	SY4S-51F1 (SY4S-02F1)	SFA-301 SFA-302
SY2S-51 SY2S-61	RY2S, RY22S	SY4S-51F1	SFA-301 SFA-302
SY4S-51 SY4S-61	RY4S, RY42S, RY2LS	SY4S-51F1 (SY4S-02F1)	SFA-301 SFA-302
	RY2KS	SY4S-51F1 (SY4S-02F3)	SFA-302
	GT5Y	—	SFA-302
SY4S-62 *	RY4S, RY42S, RY2LS, RM2S	SY4S-51F1 (SY4S-02F1)	—
	RY2KS	SY4S-51F1 (SY4S-02F3)	—

* Does not accept hold down clips

F

- When mounting relays with a check button onto panel mount or PC board mount sockets, use the hold-down spring shown in parenthesis. Hold-down springs for relays with check buttons are not available for SR2P-51.
- For close mounting of panel mount or PC mount sockets, use hold-down clips rather than hold-down springs.



SFA-101



SFA-202



SFA-302



SFA-402



SR3P-01F1



SY4S-51F1

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Accessories for Robotics and RC](#) category:

Click to view products by [Idec](#) manufacturer:

Other Similar products are found below :

[56T705](#) [015-9516-002](#) [01.001.6453.0](#) [641763-8](#) [CW106-01X](#) [CW30101A](#) [CW31701A](#) [D2041839](#) [70.352.0628.0](#) [73.353.4028.1](#) [FB22001A](#)
[FB30601A](#) [9009030000](#) [9501](#) [121587-0026](#) [1218510-1](#) [1218629-4](#) [1218630-4](#) [1261000A00M001](#) [128-26-5](#) [RFI77-14](#) [1367251-2](#) [14](#) [1-](#)
[449604-1](#) [1460g4](#) [1470g4](#) [DV0PM20034](#) [MS27488-16-1](#) [MS3057-12A W/B](#) [MS3057-8A-624](#) [MS600-2-XP-1A](#) [MS-602-GEE-14-07C](#)
[MS603-12-01A](#) [MS90376-14R](#) [MS90376-16RB](#) [MTB1-11PH3](#) [1676610000](#) [1A9224 REV A](#) [210-115](#) [CA20L22](#) [2227383-1](#) [225-0090-000](#)
[225-0098-000](#) [KA-89-82](#) [CB20201X](#) [KC-89-104](#) [CB30601A](#) [CB31201A](#) [236-600](#) [CBC120210-752](#)