

Clamp-On Ground Resistance Tester

✓ Enables non-contact measurements of ground conductors
Without the need for auxiliary spikes

Features:

- Autoranging ground resistance measurements from 0.03 to 1500 with 0.02 resolution
- True RMS AC Leakage current range of 0.2mA to 30.00A
- Programmable datalogging with 116 data points
- Programmable Hi/Lo alarm
- 0.9" (23mm) Jaw size for large ground rods
- Simplifies ground resistance measurements on multiple point ground systems
- Auto power off
- Verification resistors confirm accuracy of meter
- Automatic Self Calibration when powered on
- 9999 Count LCD display with Data Hold
- Electrical Noise Detection feature prevents inaccurate readings
- Data hold
- Complete with 9V battery, Resistance check plate, and durable metal storage case



Verify resistance of cellular and communication tower ground grids

Specifications	Range	Resolution	Accuracy (%rdg)
Ground Resistance	0.025 to 0.25	0.002	±(1.5% + 0.05)
	0.250 to 1.000	0.02	±(1.5% + 0.05)
	1.001 to 9.999	0.02	±(1.5% + 0.1)
	10.00 to 50.00	0.04	±(1.5% + 0.1)
	50.01 to 99.99	0.04	±(1.5% + 0.5)
	100.0 to 200.0	0.4	±(1.5% + 0.5)
	200.1 to 400.0	2	±(5.0% + 5)
	400.0 to 600.0	5	±(10% + 10)
	600.1 to 1500	20	±20%
	AC Leakage Current (Trms)	0.300 to 1.000mA	0.001mA
1.00 to 10.00mA		0.01mA	±(2.0% ± 0.03mA)
10.0 to 100.0mA		0.1mA	±(2.0% ± 0.3mA)
100 to 1000mA		0.1mA	±(2.0% ± 0.3mA)
0.20 to 4.00A		0.01A	±(2.0% ± 0.03A)
4.00 to 30.00A		0.01A	±(3.0% ± 0.03A)
Resistance Test Frequency	1.667kHz		
Dimensions	10.2 x 4.4 x 1.9" (258 x 110 x 47mm)		
Weight	24.7oz (700g)		

Ordering Information:

382357 Clamp-On Ground Resistance Tester

382357-NIST Clamp-On Ground Resistance Tester with Calibration Traceable to NIST.



X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Clamp Multimeters & Accessories](#) category:

Click to view products by [Extech](#) manufacturer:

Other Similar products are found below :

[I800](#) [FLUKE 1630-2](#) [ZAPDUMOD-03](#) [ZARKMS-01-99](#) [UT233](#) [TESTO 770-3](#) [0590 7703](#) [AX-3550](#) [AX-M266C](#) [BM079](#) [BM089](#) [BM157](#)
[BM162](#) [BM197](#) [KEW2210R](#) [FLUKE 80I-110S](#) [FLUKE I200](#) [FLUKE I200S](#) [FLUKE I3000FLEX-24](#) [FLUKE I310S](#) [FLUKE I400](#) [CIE600](#)
[TESTO 770-2](#) [0590 7702](#) [34194A](#) [KEW2433R](#) [KEW8112](#) [FLUKE 772](#) [380976-K](#) [MA3110](#) [MA440](#) [MA443](#) [MA445](#) [FLUKE-374 FC](#)
[TA74](#) [AMP-320](#) [CM55](#) [CM46](#) [I200](#) [ACD-6 PRO](#) [FLUKE-1630-2FC](#) [I410](#) [CM44](#) [CM42](#) [FLK-A3000 FC](#) [FLUKE-376 FC](#) [ACD-14-PRO](#)
[MA610](#) [F201](#) [F205](#) [MA193 \(250 MM\)](#) [DIGIFLEX 4000A 350MM](#)