

## NL668-EAU LTE Module

Perfect Wireless Experience


 4 Modes

 50Mbps LTE Uplink

 150Mbps LTE Downlink

 Temperature Range  
-40°C~+85°C

FIBOCOM NL668-EAU模块是一款LCC封装的LTE无线通信模块,支持LTE-TDD/LTE-FDD/WCDMA/GSM 4种制式16个频段,支持FDD/TDD混合组网的LTE网络,最高可达Cat4 150Mbps下行和50Mbps上行网络速度。FIBOCOM NL668可应用于工业路由、安防、车联网等行业。



### 适用于

- 澳大利亚
- 欧洲

## NL668-EAU LTE Module

Perfect Wireless Experience

### NL668-EAU LTE Module Technical Specifications

#### Product Feature

- LTE FDD: Band 1/3/5/7/8/20/28
- LTE TDD: Band 38/40/41
- WCDMA: Band 1/5/8
- GSM/GPRS/EDGE: 850/900/1800MHz
- LCC 32x29x2.4mm
- Operating Temperature: -30°C~+75°C
- Optional Operating Temperature: -40°C~+85°C
- Storage Temperature: -40°C~+85°C
- Operating Voltage: 3.3V~4.3V typical 3.8V
- AT Command Set: 3GPP TS 27.007 and 27.005, and proprietary FIBOCOM AT commands
- TX Power
  - GSM850: 32.5 dBm±1dB
  - GSM900: 32.5 dBm±1dB
  - DCS1800: 29.5dBm±1dB
  - WCDMA: 23.5dBm±1dB
  - LTE FDD: 23.0dBm±1dB
  - LTE TDD: 23.0dBm±1dB

#### Data

- LTE FDD: 150Mbps DL/50Mbps UL
- LTE TDD: 130Mbps DL/35Mbps UL
- UMTS: 384 kbps DL/384 kbps UL
- HSPA/HSPA+: 42Mbps DL/5.76Mbps UL
- EDGE: 296Kbps DL/236.8Kbps UL
- GPRS: 107Kbps DL/85.6Kbps UL
- MUX: Basic Mode
- SMS: MO/MT Text and PDU modes
- HTTP(S)/PPP/FTP(S)/TCP/UDP/TTS/SMTP/IPV4/IPV6
- ECM/RNDIS/Gobinet/NDIS
- DFOTA/FOAT
- eCall/SRLTE/VoLTE
- GNSS/LBS
- OpenLinux\*

#### Interface

- SIM Card: 1.8V/3.0Vx 1
- USB 2.0 x 1
- UART x 2
- I2C x 1
- PCM/I2S x 1
- ADC x 2
- SDIO x 2
- SPI x 1
- SGMII x 1
- GPIO
- Antenna:Main/Div/GNSS

#### Driver

- Linux/Android
- Win7/8/10

#### Certification

- CE-RED/GCF/RCM/Telstra/Anatel

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [RF Modules](#) category:*

*Click to view products by [Fibocom](#) manufacturer:*

Other Similar products are found below :

[HMC-C009](#) [nRF24L01P-MODULE-PCB](#) [HMC-C001](#) [HMC-C021](#) [HMC-C024](#) [XB9XT-DPRS-721](#) [XBP24BZ7PIT-004J](#) [XBP9B-DMUTB022](#) [nRF24L01P-MODULE-SMA](#) [CMD-KEY2-418-CRE](#) [XM-C92-2P-UA](#) [XB9XT-DPUS-721](#) [V640-A90](#) [HMC-C583](#) [MAAM-008818-TR3000](#) [MTSMC-H5-U](#) [SIMSA868-PRO](#) [SIMSA915C-PRO](#) [SIMSA868C-PRO](#) [SIMSA433C-PRO](#) [SIMSA915-PRO](#) [XBP9B-DMUT-042](#) [HMC-C582](#) [HMC-C022](#) [XBP9B-DPST-041](#) [XBP9B-DMWT-042](#) [SM-MN-00-HF-RC](#) [HMC-C031](#) [MT-02](#) [M1002GB](#) [702-W](#) [SIMSA868C-N-PRO](#) [SIMSA433C-N-PRO](#) [SIMSA915C-N-PRO](#) [PEPPER WIRELESS C1 USB](#) [S2-1050J-Z0K4J](#) [S2-10732-Z1T61](#) [S2-10716-Z1W4E](#) [S2-107ET-Z1W6D](#) [S2-10686-Z1L1D](#) [S2-10688-Z1L1T](#) [S2-106BA-Z1P20](#) [UC15EA-MINIPCIE](#) [SU60-2230C-PU](#) [RC-TFSK3-868](#) [NANO RFID POE](#) [650201424G](#) [H330 A30-00](#) [CMD-HHCP-433-MD](#) [RC-CC1101-SPI-868](#)