

2510KG2C

Manual Switch 30A, Non-Reversing, 3-Pole, Toggle Oper., Type: K, 3-Phase



List Price \$221.00 USD

Availability **Stock Item: This item is normally stocked in our distribution facility.****Technical Characteristics**

Width	2.44 Inches
Depth	2.88 Inches
Type	K
Height	4.25 Inches
Horsepower Rating (3-Phase)	2HP@115VAC - 7.5HP@230VAC - 10HP@460/575VAC
Terminal Type	Screw Clamp
Handle Guard/Lockoff	Yes
Maximum Voltage Rating	600VAC/230VDC
Mounting Type	Surface
Number of Poles	3-Pole
Operator Type	Toggle
Phase	3-Phase
Pilot Light	Red (400/600VAC)
Switch Type	Non-Reversing
Short Circuit Current Rating	5000 AIR
Ampere Rating	30A
Application	Provides manual ON/OFF control of single or three phase AC motors where overload protection is not required or provided separately
Approvals	UL Listed - CSA Certified - CE Marked
Conduit Size	0.5 and 0.75 Inch Knockouts (top and bottom)
Enclosure Type	Single Unit Metal Box - General Purpose
Enclosure Rating	NEMA 1

Shipping and Ordering

Category	21102 - Starters, Manual, Type K
Discount Schedule	CP1
GTIN	00785901554523
Package Quantity	3
Weight	0.88 lbs.
Availability Code	Stock Item: This item is normally stocked in our distribution facility.
Returnability	Y
Country of Origin	MX

Generated: 08/06/2012 06:59:05

As standards, specifications, and designs change from time to time, please ask for confirmation of the information given in this document.

Generated: 08/06/2012 06:59:05

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Schneider manufacturer](#):

Other Similar products are found below :

[HMIGTO2310](#) [GS1AE21](#) [METSEPM8240](#) [LC1DT25B7](#) [LU9M1](#) [7D](#) [7S](#) [7XA1](#) [8501RS44V24](#) [8501RSD14P14V51](#) [8501XM4](#)
[8501XO20V03Y414](#) [9001KXRK](#) [9001SKR9P35RH25](#) [9001SKT35L31](#) [9003K2C003GA](#) [9007AA1](#) [9007BA1](#) [9007C54D](#) [9007C62A2](#)
[9007C68T5](#) [9007CA11](#) [9007FA3](#) [9007HA4](#) [9007HA6](#) [9007KA1](#) [9007KB11](#) [9007MS01S0206](#) [9007MS10S0100](#) [9012GAR4](#) [9012GAW2](#)
[9012GBW1](#) [9012GDW5E3](#) [9012GFW1](#) [9012GNG1](#) [9012GNG3](#) [9012GNG6](#) [9013FHG39J69](#) [9013GHG2J30](#) [9050JCK2F30V14](#) [GZ1E02](#)
[A9F07125](#) [ATS01N222RT](#) [ATV12H018F1](#) [RSL1PRJU](#) [9001KA35](#) [9001KA3G](#) [9001KR1GH5](#) [9001KXSDC](#) [9007C52A2](#)