

### Mini Strobe Siren (Indoor/Outdoor Use)

**SL-1312-SA/R** Red Lens

**SL-1312-SA/B** Blue Lens

*Synchronized piezo siren and LED strobe helps to deter would-be thieves*

#### Features:

- Synchronized piezo siren and long operating life LED
- Available with red or blue lens
- Mounts in single-gang box or surface-mount (2 mounting screws included)
- High-impact plastic casing and weatherproof design allows for indoor and outdoor use
- Simple 2-wire connection: red to positive, black to negative
- Alarm siren sound is 110dB@1ft (30cm) at 12VDC

#### Specifications:

| Model              | SL-1312-SA/R                                                                                                             | SL-1312-SA/B |
|--------------------|--------------------------------------------------------------------------------------------------------------------------|--------------|
| Lens Color         | Red                                                                                                                      | Blue         |
| Built-in siren     | Piezo                                                                                                                    |              |
| Sound level        | 110dB@1ft (30cm) at 12VDC                                                                                                |              |
| Rated voltage      | 12VDC                                                                                                                    |              |
| Operating voltage  | 6~15 VDC                                                                                                                 |              |
| Current draw (max) | 90mA@12VDC                                                                                                               |              |
| Connections        | Red to positive                                                                                                          |              |
|                    | Black to negative                                                                                                        |              |
| Dimensions         | 2 <sup>15</sup> / <sub>16</sub> " x 4 <sup>7</sup> / <sub>8</sub> " x 1 <sup>7</sup> / <sub>8</sub> " ( 74 x 123 x 50mm) |              |



SL-1312-SA/R shown

SL-1312-SA/B shown

LED

### Also Available from SECO-LARM®:

#### LED Strobe Light with Siren

SL-1301-SAQ



- 10-24 VCA/V CC Volt use
- LEDs last up to 50,000 hours
- 54 LEDs for increased brightness
- Programmable flash patterns and flash speed
- Provides for battery backup
- Includes 100dB siren

#### 32 LED Strobe Light

SL-1301-BAQ



- 9-12V CC, 12 VCA Volt use
- LEDs last up to 50,000 hours
- 32 High-intensity LEDs
- Programmable flash patterns and flash speed
- Provides for battery backup
- Simple 2-wire installation

#### 12 LED Strobe Light

SL-1301-EAQ



- 6-12 V CC Volt use
- LEDs last up to 50,000 hours
- 12 High-intensity LEDs
- Simple 2-wire installation

#### 12VDC Strobe Light

SL-126Q



- 6-12 Volt use
- Easy 2-wire installation
- Over 300 continuous hours of use
- High-impact resistant acrylic

#### 24VDC Strobe Light

SL-126-A24



- 6-24 Volt use
- Easy 2-wire installation
- Over 300 continuous hours of use
- High-impact resistant acrylic

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [SECO-LARM](#) manufacturer:*

Other Similar products are found below :

[SS-090-2H1](#) [ST-2406-5A](#) [SL-1301-BAQ/C](#) [SA-027WQ](#) [SD-7202GC-PT](#) [SL-1301-BAQ/B](#) [SM-4105-LQ/B](#) [82-12781](#) [E-936-S45RRGQ](#) [SM-4103-TQ/W](#) [E-941SA-1200](#) [SD-7201GCPE1Q](#) [SK-990AQ](#) [SS-090-2H0](#) [SM-226R-3Q](#) [SD-7202GC-PEQ](#) [E-941SA-300RQ](#) [SM-4104-TQ/W](#) [SM-205Q/BR](#) [SR-1212-C2ALQ](#) [SM-4601-LQ](#) [SA-025Q](#) [SL-126Q/C](#) [SM-200Q/BR](#) [CA-1615-06LQ](#) [SS-074Q/BG](#) [CA-1515Q](#) [SM-4201-LQ](#) [SK-91ERSD](#) [SM-4303-TQ/W](#) [SK-1011-SDQ](#) [SM-216Q/GY](#) [NE-SE01-020Q](#) [CA-1610-3FLQ](#) [NJ-P101M-PQ](#) [SM-226RQ](#) [SS-073Q](#) [SL-126Q/R](#) [SL-126Q/A](#) [SL-1312-SA/R](#) [SL-126Q/B](#) [SM-204Q/W](#) [SM-207-5Q/BR](#) [SM-4102-TQ/W](#) [SM-4301-TQW](#) [CA-1616Q](#) [SM-4601-L3Q](#) [SL-1301-BAQ/R](#) [SM-226LQ](#) [SM-226L-3Q](#)