

Triplett Line-Bug 4 Features

- ▲ Tests standard telephone jacks and LAN jacks for connection to telephone system
- ▲ Protect your Expensive LAN Tester!!! - checks LAN Lines (RJ-45) wired to 568 A/B standard for damaging telephone line current
- ▲ Has both RJ-11 and RJ-45 style plugs
- ▲ 4 Tri-color (Red / Green / Amber) LEDs indicate Current, Polarity, & Ringing / AC Voltage on each line
- ▲ Tests Single Line, 2 Line, 3 Line, or 4 Line jacks to USOC (telephone) standard
- ▲ RJ-45 test plug is selectable via front panel switch for USOC (telephone) or 568 (LAN) connection
- ▲ Compact design - fits in shirt pocket
- ▲ Self powered - no batteries required
- ▲ Economical and Convenient
- ▲ One Year Limited Warranty

Instructions

RJ-11 Phone Lines:

Plug RJ-11 connector into jack and observe LEDs. Switch position does not effect test.

RJ-45 Phone Lines:

Set switch appropriately. (USOC for standard phone or 568 A/B for LAN). Plug RJ-45 connector into jack and observe LEDs.

NOTES:

Do not plug RJ-11 into RJ-45 jacks. Damage may result. Newer phone lines are often wired to 568 A/B instead of USOC.

LAN Lines

Some LAN lines have telephone current on previously unused pairs. Pre-testing LAN lines with the Line-Bug 4 before testing with a LAN tester may prevent damage to your LAN tester.

Plug RJ-45 connector into jack. Set switch to 568 A/B and observe LEDs. Next, set switch to USOC and observe LEDs. If any LED lights in either switch position, voltage is present. **DO NOT USE LAN TESTER AS DAMAGE MAY OCCUR!**

PHONE LINE RESULTS

- Green - Line OK
- Red - Reversed Line
- Amber - Ringing / AC Voltage
- Not Lit - Dead Line



PATENT PENDING

Cat. No. 9615

Made in China



TRIPLETT

Triplett Corporation One Triplett Drive Bluffton, OH 45817
PHONE: 800-TRIPLETT FAX: 419-358-7956

www.triplett.com

X-ON Electronics

Authorized
Distributor

*Click to view similar
products for [Triplett](#)
manufacturer.*

Other Similar products
are found below :

[1101](#) [2030](#) [2030C](#)

[3018](#) [3145](#) [3207131](#)

[3240](#) [3397](#) [3399](#)

[3450](#) [531371](#) [79127](#)

[79153](#) [79416](#) [79417](#)

[79767](#) [8071](#) [9000](#)

[9020](#) [9325](#) [9615](#)

[BREAKERSNIFFIT](#)

[CABLCUT](#)

[CAMVIEWIPPRO](#)

[CAMVIEWITPRO](#)

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [triplett](#) manufacturer:

Other Similar products are found below :

[DT-4412-01](#) [8115](#) [3145](#) [53-1371](#) [8071](#) [1101](#) [3399](#) [3450](#) [79-767](#) [9325](#) [79-127](#) [TAL-012](#) [2030](#) [79-153](#) [79-416](#) [79-417](#) [CABLCUT](#) [3207-131](#)