

Palm Size Digital Multimeter



Description

The new generation Palm Size Multimeters redefines the performance standards for entry-level digital multimeters. These models ensure that users can work safely in CAT II 250V environment.

Features

- Clear LCD Display
- Equipped with Comfortable Protective Cover, Test Probe Holder
- 2 Meters Drop Test, Precision Protection
- Auto Power Off
- Auto Backlight Off
- Loud Buzzer Sound
- Knobs Shift Smoothly, In-line with Ergonomics

Specification Table

| Characteristics | 72-13430 | 72-13435 | 72-13440 |
|------------------------|--|--|--|
| Max Display | 1999 | | |
| Range Selection | Auto | Manual | |
| Diode Test | | ✓ | |
| Continuity Buzzer | | ✓ | |
| Overload Alarm | | ✓ | |
| Data Hold | | ✓ | |
| Relative Mode | ✓ | - | |
| Low Battery Indication | | ✓ | |
| NCV | - | - | ✓ |
| DC Voltage | 200mV/2V/20V/200V/250V, ±(0.8%+1) | 200mV/2000mV/20V/200V/250V, ±(0.5%+2) | 200mV/2000mV/20V/200V/250V, ±(0.5%+2) |
| AC Voltage | 200mV/2V/20V/200V/250V, ±(1% +2) | 200V/250V, ± (1.2%+3) | 200V/250V, ±(1.2%+10) |
| AC Current | 200µA/2000µA/20mA/ 200mA/2A/10A, ±(1.2%+3) | - | - |
| DC Current | 200µA/2000µA/20mA/ 200mA/2A/10A, ±(1%+3) | 2000µA/20mA/ 200mA/10A, ±(1%+3) | 2000µA/20mA/ 200mA/10A, ±(1%+3) |
| Capacitance | 2nF/20nF/200nF/2µF/ 20µF/200µF, ±(3%+5) | - | - |

www.element14.com
www.farnell.com
www.newark.com
www.cpc.co.uk



Palm Size Digital Multimeter



| Characteristics | 72-13430 | 72-13435 | 72-13440 |
|----------------------|--|--|--|
| Resistance | 200Ω/2kΩ/20kΩ/200kΩ/ 2MΩ/20MΩ/200MΩ, ±(0.8%+2) | 200Ω/2kΩ/20kΩ/200kΩ/20MΩ, ±(0.8%+2) | 200Ω/2kΩ/20kΩ/200kΩ/ 2MΩ/20MΩ/200MΩ, ±(0.8%+2) |
| Temperature | - | -40°C to 1000°C | - |
| | - | -40°F to 1832°F | - |
| Power | AAA 1.5V × 2 | | |
| Standard Accessories | Type K Thermocouple (Part Number 72-13435 only), English Manual, Test Leads, Protective Case | | |
| Product Weight | 206g (Battery Included) | | |
| Product Size | 134mm × 77mm × 47mm | | |

Part Number Table

| Description | Part Number |
|--|-------------|
| DMM, Handheld, Auto/Manual, 2000 Count | 72-13430 |
| DMM, Handheld, Manual, 2000 Count | 72-13435 |
| DMM, Handheld, Manual, 2000 Count | 72-13440 |

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Tenma is the registered trademark of the Group. © Premier Farnell Limited 2016.



X-ON Electronics

Authorized Distributor

Click to view similar products for [Tenma manufacturer](#).

Other Similar products are found below :

[BEBKQRT](#) [7210160727770A](#) [722630](#) [76090](#) [76097](#) [76300](#) [76350](#) [761444](#) [76020](#) [21685](#)
[7213300](#) [7213768](#) [7214058](#) [7214316](#) [7214320](#) [7214322](#) [ST5C](#) [76270](#) [BECKKRT](#)
[BECKMRT](#) [7210179727770A](#) [727635](#) [76082](#) [761662](#) [76021](#)