



### Features:

- Used in the rework and repair of printed circuit boards, computers, cell phones, or other electronics
- Easily removes solder from components or pads on a circuit board
- Concentrated fine copper braiding utilizes less length of wick for each desoldering application
- Made of clean, oxide-free copper wire
- Tight weave enables quick “on and off” desoldering
- 5’ and 10’ lengths available on static-dissipative bobbins in compliance with ESD Association Standard
- Leaves a residue that is environmentally safe

### Wire Specifications:

Wire Type	Width	Configuration
A Wire	0.025" (±0.003") 6.35mm (±0.8mm)	2 strands of 42awg X 16 (total 32 strands), 31 PPI
B Wire	0.050" (±0.004") 12.70mm (±1.0mm)	4 strands of 42awg X 16 (total 64 strands), 12.5 PPI
C Wire	0.075" (±0.005") 19.5mm (±1.3mm)	6 strands of 42awg X 16 (total 96 strands), 16 PPI
D Wire	0.095" (±0.007") 24.1mm (±1.8mm)	5 strands of 42awg X 24 (120 total strands), 19 PPI
E Wire	0.117" (±0.008") 29.7mm (±2.0mm)	5 strands of 40awg X 24 (120 total strands), 16 PPI

### Bobbin Identification:

Width	Color Code	Letter Signifier
.025"	Silver	A
.050"	Gold	B
.075"	Green	C
.100"	Blue	D
.125"	Brown	E

EasyBraid expressly warrants that for a period of two (2) years from the date of manufacture, Quick Braid will be free of defects in material (parts) and workmanship (labor) when stored appropriately and contained within its original container. Each bobbin is individually stamped with a lot code. A certificate of compliance is available on our [website](#).

Specifications and procedures subject to change without notice.



### QUICK BRAID DESOLDERING BRAID

11543 K-TEL DRIVE, MINNETONKA, MN 55343  
 PHONE: (952) 929-3040  
 WEBSITE: [EASYBRAIDCO.COM](http://EASYBRAIDCO.COM)

**DRAWING NUMBER**  
 Quick Braid

**DATE:**  
 February 2018

# EasyBraid

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [easy braid manufacturer](#):*

Other Similar products are found below :

[EB41D2120](#) [ETZ-KIT-1](#) [SHP-PM](#) [Q-A-100](#) [OS-E-100](#) [OS-A-100](#) [S-B-5AS](#) [OS-E-25](#) [S2626-O-T](#) [OS-E-10AS](#) [S-E-100](#) [Q-B-100](#) [S-A-100](#)  
[Q-D-100](#) [OS-C-100](#) [Q-E-10AS](#) [Q-B-25](#) [Q-E-25](#) [LF-A-5AS](#) [Q-A-25](#) [Q-E-100](#) [LF-E-5AS](#) [S3030R-O-T](#) [S-B-100](#) [S2235-O-T](#) [OS-D-100](#) [Q-](#)  
[A-10AS](#) [LF-B-5AS](#) [Q-A-5AS](#) [S-A-10AS](#) [S-D-10AS](#) [LF-D-5AS](#) [LF-C-10AS](#) [S-B-10AS](#) [LF-D-10AS](#) [Q-D-10AS](#) [S-C-5AS](#) [OS-D-5AS](#) [Q-E-](#)  
[5AS](#) [S-D-5AS](#) [Q-D-25](#) [Q-C-100](#) [OS-B-25](#) [OS-B-100](#) [S-E-5AS](#) [OS-D-10AS](#) [Q-C-25](#) [S-E-10AS](#) [Q-B-10AS](#) [OS-E-5AS](#)