


Fuse holder terminal blocks
for 6,35 x 25,4 mm 1/4 x 1 in.
and 6,35 x 32 mm 1/4 x 1 1/4 in. fuses
Compression clamp
DIN 1 - DIN 3

DIN 1 - DIN 3

MU 10/13.SF2


Spacing 13 mm (.512")



13 mm block for blown fuse indicator (to be ordered separately).

MU 10/14,5.SF2

Spacing 14,5 mm (.571")



14,5 mm block for blown fuse indicator (to be ordered separately).

Color	Type	Part numbers	Color	Type	Part numbers
Black V0	MU 10/13.SF2	0199 014.11	Black V0	MU 10/14,5.SF2	0199 013.10

Characteristics

Wire size	Wire size		
	NFC DIN	UL	CSA
Compression Solid wire	0,5-16 mm ²	22-10 AWG	6 AWG max.
clamp Stranded wire	0,5-10 mm ²	22-10 AWG	6 AWG max.

Characteristics

Wire size	Wire size		
	NFC DIN	UL	CSA
Compression Solid wire	0,5-16 mm ²	22-10 AWG	6 AWG max.
clamp Stranded wire	0,5-10 mm ²	22-10 AWG	6 AWG max.

Voltage			
Rated	750 V Gr.C (1)	600 V (1)	600 V (1)
Pulse			
Pollution degree			
Current			
Rated	16 A	16 A	16 A
Wire size			
Rated / Gauge	10 mm ²	10 AWG	6 AWG
Wire stripping length	Recomm. screwdriver 5,5 mm .22"	Recomm. torque 1,2-1,4 Nm 10.6-12.3 lb.in	Protection IP 20 NEMA 1

Voltage			
Rated	750 V Gr.C (1)	600 V (1)	600 V (1)
Pulse			
Pollution degree			
Current			
Rated	16 A	16 A	16 A
Wire size			
Rated / Gauge	10 mm ²	10 AWG	6 AWG
Wire stripping length	Recomm. screwdriver 5,5 mm .22"	Recomm. torque 1,2-1,4 Nm 10.6-12.3 lb.in	Protection IP 20 NEMA 1

End stop th. 9,1 mm **BADL** V0 **0199 408.02**
 End stop th. 9,1 mm **BAM** **0103 002.26**
 Other end stops : See Accessories section
 Rail 35 x 7,5 x 1 **PR30** prepunched **0173 220.05**
 Rail 35 x 15 x 2,3 **PR4** **0168 500.12**
 Rail 35 x 15 x 1,5 **PR5** prepunched **0101 598.26**
 Rail 32 x 15 **PR1Z2** **0163 050.04**
 Other rails : See Accessories section

Notes

The use of some accessories may decrease the block's voltage rating. For more information, consult us.

Accessories

Type	Part numbers
1 End section black	FEM13U V0 th. 1,5 mm 0199 635.24
2 Test plug	FC2 DIA. 2 mm 0007 865.26
3 Test socket	FC4 DIA. 4 mm 0167 860.01
4 Standard jumper bar	AL2 DIA. 2 mm 0163 043.21
5 Screw for BJ	AL3 DIA. 3 mm 0163 261.00
6 Washer for BJ	AL4 DIA. 4 mm 0163 262.01
7 Fuse 6,35 x 32 mm Quick blow fuse cartridge as per UTE 93435	BJS131 10 poles 0175 991.11
8 Blown fuse indicator	VJS11 0163 394.26
	RDJ11 0168 783.01
	FU633 6,35 x 32
	0,25 A 0168 554.03
	0,63 A 0168 555.04
	1 A 0168 556.05
	1,6 A 0168 557.06
	2,5 A 0168 558.17
	4 A 0168 559.10
	6,3 A 0168 560.15
	10 A 0168 561.02
	16 A 0168 562.03
	LEN Neon 110 - 230 VAC 0167 075.25
	Neon 480 VAC 0103 909.00
	Leakage current with neon indicator < 0,5 mA (110 & 480 VAC) < 0,7 mA (230 VAC)
R See section on marking method	

Type	Part numbers
FC2 DIA. 2 mm	0007 865.26
FC4 DIA. 4 mm	0167 860.01
AL2 DIA. 2 mm	0163 043.21
AL3 DIA. 3 mm	0163 261.00
AL4 DIA. 4 mm	0163 262.01
FU633 6,35 x 32	
0,25 A	0168 554.03
0,63 A	0168 555.04
1 A	0168 556.05
1,6 A	0168 557.06
2,5 A	0168 558.17
4 A	0168 559.10
6,3 A	0168 560.15
10 A	0168 561.02
16 A	0168 562.03
LEN Neon 110 - 230 VAC	0167 075.25
Neon 480 VAC	0103 909.00
Leakage current with neon indicator < 0,5 mA (110 & 480 VAC) < 0,7 mA (230 VAC)	

Note : (1) Insulation voltage of terminal block - operating voltage : In accordance with fuse rating.

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for te connectivity manufacturer:

Other Similar products are found below :

[570416-000](#) [CLTEQ-M81CE-SSRELAY-4-20V](#) [D38999/24FJ4AN](#) [358838-000](#) [4-1195131-0](#) [650069-000](#) [SMD100-2](#) [CB-1022B-78](#)
[RM707012](#) [RP410012](#) [MMS42](#) [1-640426-8](#) [2EDL4CM](#) [DTS20W19-11PD-3028-LC](#) [RM202615](#) [NC6-P104-06](#) [MSPS103B](#) [DTS26F21-41AE](#) [DTS26F21-41PE-LC](#) [DTS26F21-11SE-3028-LC](#) [1932144-1](#) [293545-4](#) [LVR125S](#) [MS27466T25F4PB](#) [CKB-38-78010](#)
[1206SFF150F/63-2](#) [D38999/20JB35HA](#) [D38999/24WJ20PA](#) [1754138-1](#) [TE1500A2R2J](#) [DTS24F25-29PC-3028-LC](#) [D38999/24WG11HA](#)
[D38999/24WG11HN](#) [MS27467T21F11H](#) [DJT16E21-11HA](#) [1206SFH150F/24-2](#) [DTS24F19-11SC-3028-LC](#) [DTS24F21-41HN-LC](#)
[DTS24F21-41AN](#) [DTS24F21-41PN-LC](#) [RP330024](#) [MS27467T21F35J](#) [MS27467T21F11J](#) [MS27467T21F16H-LC](#) [MS27467T21F35H](#)
[MS27467T21F41H-LC](#) [DJT16E21-11PA-LC](#) [DJT16E21-11HA-LC](#) [DJT16E21-11AA](#) [MS27467T21B11JA](#)