

## MG300-ETK Electrical Troubleshooting Kit



**This Extech Electrical Troubleshooting Kit includes three compact tools that are indispensable at a customer site for electrical installation, troubleshooting, and repair.**



### Kit Includes:

- MG300 or MG302 — 13 Function, Wireless PC Interface, True RMS Multimeter/Insulation Tester
- 42509 — 12:1 Infrared Thermometer with high/low alarm and fast 2-color display for processes that require temperature control and monitoring; measures from -4 to 950°F (-20 to 510°C)
- MA430T — 400A True RMS AC Clamp Meter with built-in non-contact voltage detector and ideal for noisy or non-sinusoidal AC measurement
- 1.2" (30mm) jaw size for conductors up to 350MCM
- Exceptional Value Kit is supplied with test leads, Type K thermocouple bead wire probe, batteries, and attractive storage case that provides protection and organization for the meters and accessories

MG300/MG302 Specifications	Range	Max Resolution
Wireless frequency	915MHz (MG300); 433MHz (MG302)	
Insulation Resistance	4MΩ, 40MΩ, 400MΩ, 4000MΩ	0.001MΩ
Insulation Test Voltages	125V, 250V, 500V, 1000V	
AC/DC Voltage	1000V	0.1mV AC/ 0.01mV DC
AC/DC Current	10A	0.1μA AC/ 0.01μA DC
Resistance	40MΩ	0.01Ω
Capacitance	40mF	0.001nF
Frequency	100MHZ	0.001HZ
Duty Cycle	0.1 to 99.9%	0.01
Temperature	-58 to 2192°F (-50 to 1200°C)	0.1°
4-20mA%	-25 to 125%	0.01%
Continuity/Diode	Yes	

MA430T Specifications	Range (Max Resolution)
AC Current	400A (0.01A) True RMS
AC Voltage	600V (0.1mV) True RMS
DC Voltage	600V (0.1mV)
Resistance	20MΩ (0.1Ω)
Continuity / Diode	Yes

### Ordering

MG300-ETK ..... Electrical Troubleshooting Kit (includes MG300)  
 MG302-ETK ..... Electrical Troubleshooting Kit (includes MG302)



## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Digital Multimeters](#) category:*

*Click to view products by [Extech](#) manufacturer:*

Other Similar products are found below :

[8009](#) [6111-517](#) [FS881](#) [40705X](#) [USB390A](#) [780417A](#) [GPT-9904](#) [382099](#) [589250](#) [780418](#) [C.A 6131](#) [C.A 6133](#) [30XR](#) [34XR](#) [35XP](#) [TESTO](#)  
[745](#) [0590 7450](#) [TESTO 760-3](#) [0590 7603](#) [440012](#) [AX-155](#) [AX-174](#) [AX-178](#) [AX-18B](#) [AX-190A](#) [AX-503](#) [AX-507B](#) [AX-572](#) [AX-594](#) [AX-](#)  
[LCR41A](#) [AX-MS8221A](#) [AX-MS8250](#) [AX-PDM01](#) [AX-T520](#) [AX-T901](#) [AX-T903](#) [BAT-250-EUR](#) [BM233](#) [BM805S](#) [BM807S](#) [BM817S](#)  
[BM827S](#) [BM829S](#) [BM857S](#) [BM859S](#) [BM867S](#) [BM905S](#) [33XR](#) [UNITEST TESTFIX 9023](#) [37XR](#) [UT56](#) [UT58C](#)