

DCP42 160W Single Continuous Switching Power Supply with USB

Continuous switching Power Supply offers high efficiency electrical power conversion for greater energy conservation and lighter weight.

Applications:

- Laboratory use
- Bench Testing, Service, and Repair
- Research and Development facilities
- Educational and Institutional Training



Features

- Constantly calculates and adjusts the Voltage and Current limit points according to available maximum power (160W)
- At maximum current (10A), voltage is limited to 16V; at maximum voltage (42V), current is limited to 3.8A
- Dual action rotary encoder control with push knob for fine and coarse tuning
- Remote control for Programming, Output Voltage/Current, and ON/OFF using supplied software, driver, and USB
- Three on-board user-defined Voltage/Current presets
- Store 20 presets with up to 999 cycles each on a PC via USB and supplied Software
- Software also includes DC Ramp and Waveform Generator
- Complete with power cord, software, and USB cable

Specifications

Output Voltage	0 to 42V
Output Current	0 to 10A
Basic Accuracy	±(0.2%+5 counts)
Load Voltage Regulation	≤0.15% (10-100% rated current)
Line Voltage Regulation	≤0.02% (90-264V AC)
Load Current Regulation	≤0.5% (10-90% rated voltage)
Line Current regulation	≤0.1% (90-264V AC)
Ripple and Noise	≤5m Vrms, ≤50m Vp-p
Dimensions/ Weight	7.9 x 3.7 x 9.5" (200 x 95 x 245mm)/ 5lbs (2.3kg)

Ordering

DCP42 160W Single Continuous Switching Power Supply with USB (100-240V)



X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Switching Power Supplies](#) category:

Click to view products by [Extech](#) manufacturer:

Other Similar products are found below :

[70841011](#) [73-551-0005](#) [AAD600S-4-OP](#) [R22095](#) [HWS50A-5/RA](#) [KD0204](#) [9021](#) [S-15F-12](#) [LDIN100150](#) [LPM000-BBAR-01](#) [LPX17S-C](#)
[EVS57-10R6/R](#) [FDC40-24S12](#) [FRV7000G](#) [22929](#) [CQM1IA121](#) [40370121900](#) [VI-PU22-EXX](#) [40370121910](#) [LDIN5075](#) [432703037161](#)
[WRB01X-U](#) [LPX140-C](#) [08-30466-1040G](#) [09-160CFG](#) [70841004](#) [70841025](#) [VPX3000-CBL-DC](#) [LPM000-BBAR-05](#) [LPM000-BBAR-08](#)
[LPM124-OUTA1-48](#) [LPM000-BBAR-07](#) [LPM109-OUTA1-10](#) [LPM616-CHAS](#) [08-30466-1055G](#) [08-30466-2175G](#) [DMB-EWG](#) [TVQF-](#)
[1219-18S](#) [6504-226-2101](#) [CQM1IPS01](#) [XPFM201A+](#) [MAP80-4000G](#) [LFP300F-24-TY](#) [SMP21-L20-DC24V-5A](#) [VI-MUL-ES](#) [08-30466-](#)
[0065G](#) [CME240P-24](#) [VI-RU031-EWWX](#) [08-30466-0028G](#) [S82Y-TS01](#)