

AMP-200 Series TRMS Clamp Meters

The Modern Evolution of the Professional Clamp Meter

Amprobe's AMP-210 and AMP-220 600 A TRMS Clamp Meters offer a complete range of measuring functions for today's modern electrical environments. Both models feature True-RMS sensing, low pass filters and fast response processors for quick, error-free measurements. The Amp-Tip function allows for precise measurement of current down to the tenth of an Amp, enabling accurate current measurement of both large and small diameter wires.

AMP-200 Series Features

- **True-RMS**
- **Low Pass Filter**
- **Amp-Tip Functions**
- **Non-Contact Voltage Detection (NCV)**
- **Audible Continuity and Diode Test**
- **Data Hold, Relative Zero**
- **Large LCD Backlit Display**
- **Safety Rated:
CAT III 600 V**



AMP-210
AC Clamp Meter



AMP-220
AC/DC Clamp Meter

AMP-200 Series Product Details

True-RMS for accurate voltage measurements in noisy environments.

Low pass filter for current and voltage measurements on variable frequency drives.

Amp-Tip function for precise low current measurement of small diameter wires down to 0.1 Amp to help with electrical system troubleshooting.

Non-contact voltage detection (NCV)

Audible continuity and diode test

Data hold, relative zero, MAX/MIN/AVG mode

Large LCD backlit display

Safety rated
CAT III 600 V



Measurements:

Voltage
Up to 600 V AC/DC

AC current
Up to 600 A

DC Current
Up to 600 A
(AMP-220 only)

Frequency
5.00 to 999.9 Hz

Resistance
Up to 60.00 kΩ

Capacitance
Up to 2500 μF



AMP-200 Series Applications



AMP-210 AC Clamp Meter



AMP-220 AC/DC Clamp Meter

- **Accurate measurement of current, voltage and frequency** on all electrical systems including distorted, non-sinusoidal signals (True-RMS function) and variable frequency drives (low-pass filter).
- **Capacitance measurement** for start and run motor capacitors.
- **Resistance and continuity** functions to verify quality of electrical connections and to check if motor and transformer coils are working properly.
- **Low pass filter** allows measurement of current and voltage on variable frequency drives (motors with speed controlled by frequency). Without this feature, the meter would provide erroneous readings when measuring voltage and current.

Model	AMP-210	AMP-220	AMP-310	AMP-320	AMP-330
	AC Clamp Meter Electrical	AC/DC Clamp Meter Electrical	AC Clamp Meter HVAC	AC/DC Clamp Meter Electrical Motor Maintenance	AC/DC 1000 A Clamp Meter Industrial Motor Maintenance
Safety Rating	CAT III 600 V	CAT III 600 V	CAT III 600 V	CAT III 600 V	CAT IV 600 V, CAT III 1000 V
Jaw Opening	1.18 in (30 mm)	1.37 in (35 mm)	1.18 in (30 mm)	1.37 in (35 mm)	2.0 in (51 mm)
AC Voltage (True-RMS)	Range: 0 to 600.0 V Accuracy: ±1.0% + 5LSD (50 to 60 Hz)		Range: 0 to 600.0 V Accuracy: ±1.0% + 5LSD (50 to 60 Hz)		Range: 0 to 1000 V Accuracy: ±0.8% + 5LSD (50 to 60 Hz) ±1.5% + 5LSD (20 to 200 Hz) ±10% + 5LSD (200 to 400 Hz)
DC Voltage	Range: 0 to 600.0 V Accuracy: ±1.0% + 5LSD		Range: 0 to 600.0 V Accuracy: ±1.0% + 5LSD		Range: 0 to 1000 V Accuracy: ±0.8% + 5LSD
AC+DC Voltage	–	Range: 0 to 600.0 V Accuracy: 1.2% ± 7LSD (DC, 50 to 60 Hz)	–	Range: 0 to 600.0 V Accuracy: 1.2% ± 7LSD (DC, 50 to 60 Hz)	Range: 0 to 1000 V Accuracy: ±1.0% + 7LSD (50 to 60 Hz) ±1.8% + 7LSD (DC, 40 to 200 Hz) ±12% + 7LSD (200 to 400 Hz)
AC Current (True-RMS)	Range: 0 to 600.0 A Accuracy: ±1.8% + 5LSD (50 to 100 Hz) ±2.0% + 5LSD (100 to 400 Hz)		Range: 0 to 600.0 A Accuracy: ±1.8% + 5LSD (50 to 100 Hz) ±2.0% + 5LSD (100 to 400 Hz)		Range: 0 to 1000 A Accuracy: ±1.8% + 5LSD (40 to 100 Hz) ±2.2% + 5LSD (100 to 400 Hz)
DC Current	–	Range: 0 to 600.0 A Accuracy: ±2.0% + 5LSD	–	Range: 0 to 600.0 A Accuracy: ±2.0% + 5LSD	Range: 0 to 1000 A Accuracy: ±1.8% + 5LSD
AC+DC Current	–	Range: 0 to 600.0 A Accuracy: ±2.2% + 7LSD (DC, 50 to 100 Hz) ±2.7% + 7LSD (100 to 400 Hz)	–	Range: 0 to 600.0 A Accuracy: ±2.2% + 7LSD (DC, 50 to 100 Hz) ±2.7% + 7LSD (100 to 400 Hz)	Range: 0 to 1000 A Accuracy: ±2.2% + 7LSD (DC, 40 to 100 Hz) ±2.5% + 7LSD (100 to 400 Hz)
Precise Low Current AC	Range: 0 to 60.00 A Accuracy: ±1.5% + 5LSD (50 to 60 Hz)		Range: 0 to 60.00 A Accuracy: ±1.5% + 5LSD (50 to 60 Hz)		Range: 0 to 60.00 A Accuracy: ±1.5% + 5LSD (0.00 to 20.00 A, 40 to 100 Hz) ±2.0% + 5LSD (0.00 to 20.00 A, 100 to 400 Hz) ±3.0% + 5LSD (20.00 to 60.00 A, 40 to 100 Hz) ±3.0% + 5LSD (20.00 to 60.00 A, 100 to 400 Hz)
Precise Low Current DC	–	Range: 0 to 60.00 A Accuracy: ±2.0% + 5LSD	–	Range: 0 to 60.00 A Accuracy: ±2.0% + 5LSD	Range: 0 to 60.00 A Accuracy: ±1.5% + 5LSD (0.00 to 20.00 A) ±3.0% + 5LSD (20.00 to 60.00 A)
Precise Low Current AC+DC	–	Range: 0 to 60.00 A Accuracy: ±2.0% + 5LSD (DC, 50 to 60 Hz)	–	Range: 0 to 60.00 A Accuracy: ±2.0% + 5LSD (DC, 50 to 60 Hz)	Range: 0 to 60.00 A Accuracy: ±2.0% + 7LSD (0.00 to 20.00 A, DC, 40 to 100 Hz) ±2.2% + 7LSD (0.00 to 20.00 A, 100 to 400 Hz) ±3.0% + 7LSD (20.00 to 60.00 A, DC, 40 to 100 Hz) ±3.0% + 7LSD (20.00 to 60.00 A, 100 to 400 Hz)
Frequency	Range: 5.00 to 999.9 Hz Accuracy: ±1.0% + 5LSD (600 V range) Range: 50.0 to 400.0 Hz Accuracy: ±1.0% + 5LSD (600 A range)		Range: 5.00 to 999.9 Hz Accuracy: ±1.0% + 5LSD (600 V range) Range: 50.0 to 400.0 Hz Accuracy: ±1.0% + 5LSD (600 A range)		Range: 5.00 to 999.9 Hz Accuracy: ±1.0% + 5LSD (1000 V range) Range: 40.0 to 400.0 Hz Accuracy: ±1.0% + 5LSD (1000 A range)
Resistance	Range: 0.0 to 60.00 kΩ Accuracy: ±1.0% + 5LSD		Range: 0.0 to 60.00 kΩ Accuracy: ±1.0% + 5LSD		
Capacitance	Range: 0.0 to 2500 μF Accuracy: ±2.0% + 4LSD		Range: 0.0 to 2500 μF Accuracy: ±2.0% + 4LSD		
Continuity Beeper	ON ≤ 10 Ω OFF > 250 Ω		ON ≤ 10 Ω OFF > 250 Ω		
Non-Contact Voltage	10V to 1000V AC, 50/60Hz		10V to 1000V AC, 50/60Hz		
True-RMS	•	•	•	•	•
Low Pass Filter	•	•	•	•	•
Autoranging	•	•	•	•	•
Relative Zero	•	•	•	•	•
MAX/MIN/AVG	•	•	•	•	•
Diode Test	•	•	•	•	•
Data Hold	•	•	•	•	•
Backlight	•	•	•	•	•
Auto Power Off	•	•	•	•	•
300 Series:					
DC Microamps	–	–	Range: 0.0 to 2000 μA Accuracy: ±1.0% + 5LSD		
Temperature* (Type K thermocouple) *Error does not include Type-K thermocouple errors	–	–	Range: -40.0 to 752°F, -40.0 to 400°C Accuracy: -40.0 to 14.0°F (±1.0% +3.0°F), >14.0 to 99.9°F (±1.0% +1.5°F) 100 to 752°F (±1.0% +2°F), -40.0 to -10.0°C (±1.0% +1.5°C) >-10.0 to 99.9°C (±1.0% +0.8°C), 100 to 400°C (±1.0% +1°C)		
3-Phase and Motor Rotation Indication	–	–	Rotation-R for mains supply Rotation-M for motors		
Inrush Current	–	–	•	•	•
Peak Hold (Crest)	–	–	–	–	•
Work Light	–	–	–	–	•



Model	AMP-210	AMP-220	AMP-310	AMP-320	AMP-330
Display	3-5/6 digits 6000 counts	3-5/6 digits 6000 counts	3-5/6 digits 6000 counts	3-5/6 digits 6000 counts	3-5/6 digits 6000 counts
Polarity	Automatic	Automatic	Automatic	Automatic	Automatic
Update Rate	5 per second nominal	5 per second nominal	5 per second nominal	5 per second nominal	5 per second nominal
Operating Temperature	32 to 104°F (0 to 40°C)	32 to 104°F (0 to 40°C)	32 to 104°F (0 to 40°C)	32 to 104°F (0 to 40°C)	14 to 122°F (-10 to 50°C)
Relative Humidity	80% at 30°C, 50% at 40°C	80% at 30°C, 50% at 40°C	80% at 30°C, 50% at 40°C	80% at 30°C, 50% at 40°C	Non condensing at ≤10°C 90% at 10 to 30°C 75% at 30 to 40°C 45% at 40 to 50°C
Operating Altitude	0 to 2000 m	0 to 2000 m	0 to 2000 m	0 to 2000 m	0 to 2000 m
Pollution Degree	2	2	2	2	2
Storage Temperature	-4 to 140°F (-20°C to 60°C), < 80% RH	-4 to 140°F (-20°C to 60°C), < 80% RH	-4 to 140°F (-20°C to 60°C), < 80% RH	-4 to 140°F (-20°C to 60°C), < 80% RH	-4 to 140°F (-20°C to 60°C), < 80% RH
Temperature Coefficient	Nominal 0.15 x (specified accuracy)/ °C @ (0°C to 18°C or 28°C to 40°C)	Nominal 0.15 x (specified accuracy)/ °C @ (0°C to 18°C or 28°C to 40°C)	Nominal 0.15 x (specified accuracy)/ °C @ (0°C to 18°C or 28°C to 40°C)	Nominal 0.15 x (specified accuracy)/ °C @ (0°C to 18°C or 28°C to 40°C)	Nominal 0.10 x (specified accuracy)/ °C @ (0°C to 18°C or 28°C to 50°C)
Battery	Two AAA 1.5 V battery	Two AAA 1.5 V battery	Two AAA 1.5 V battery	Two AAA 1.5 V battery	Two AA 1.5 V battery
EMC	Meets EN 61326-1:2006	Meets EN 61326-1:2006	Meets EN 61326-1:2006	Meets EN 61326-1:2006	Meets EN 61326-1:2006
Safety Compliance	UL/IEC/EN 61010-1 ed. 3.0, IEC/EN 61010-2-033 ed. 1.0, CAN/CSA C22.2 NO. 61010-1 ed. 3.0, IEC/EN 61010-2-032 ed. 3.0 & IEC/EN 61010-031 ed. 1.1	UL/IEC/EN 61010-1 ed. 3.0, IEC/EN 61010-2-033 ed. 1.0, CAN/CSA C22.2 NO. 61010-1 ed. 3.0, IEC/EN 61010-2-032 ed. 3.0 & IEC/EN 61010-031 ed. 1.1	UL/IEC/EN 61010-1 ed. 3.0, IEC/EN 61010-2-033 ed. 1.0, CAN/CSA C22.2 NO. 61010-1 ed. 3.0, IEC/EN 61010-2-032 ed. 3.0 & IEC/EN 61010-031 ed. 1.1	UL/IEC/EN 61010-1 ed. 3.0, IEC/EN 61010-2-033 ed. 1.0, CAN/CSA C22.2 NO. 61010-1 ed. 3.0, IEC/EN 61010-2-032 ed. 3.0 & IEC/EN 61010-031 ed. 1.1	UL/IEC/EN 61010-1 ed. 3.0, IEC/EN 61010-2-033 ed. 1.0, CAN/CSA C22.2 NO. 61010-1 ed. 3.0, IEC/EN 61010-2-032 ed. 3.0 & IEC/EN 61010-031 ed. 1.1
Certification	UL (c/us) and CE	UL (c/us) and CE	UL (c/us) and CE	UL (c/us) and CE	UL (c/us) and CE
Dimensions (L x W x H):	8.62 x 3.03 x 1.46 in (219 x 77 x 37 mm)	8.82 x 3.03 x 1.46 in (224 x 77 x 37 mm)	8.62 x 3.03 x 1.46 in (219 x 77 x 37 mm)	8.82 x 3.03 x 1.46 in (224 x 77 x 37 mm)	10.16 x 3.70 x 1.73 in (258 x 94 x 44 mm)
Weight:	208 g (0.46 lb)	254 g (0.56 lb)	208 g (0.46 lb)	254 g (0.56 lb)	420 g (0.93 lb)

Accessories Included:					
User's Manual	•	•	•	•	•
Test Leads	•	•	•	•	•
Carrying Case	•	•	•	•	•
Batteries	AAA (2)		AAA (2)		AA (2)
Alligator Clip Set	–	–	•	•	•
Banana plug K-type Thermocouple	–	–	•	•	•

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Clamp Multimeters & Accessories](#) category:

Click to view products by [Amprobe](#) manufacturer:

Other Similar products are found below :

[I800](#) [FLUKE 1630-2](#) [ZAPDUMOD-03](#) [ZARKMS-01-99](#) [UT233](#) [TESTO 770-3](#) [0590 7703](#) [AX-3550](#) [AX-M266C](#) [BM079](#) [BM089](#) [BM157](#)
[BM162](#) [BM197](#) [KEW2210R](#) [FLUKE 80I-110S](#) [FLUKE I200](#) [FLUKE I200S](#) [FLUKE I3000FLEX-24](#) [FLUKE I310S](#) [FLUKE I400](#) [CIE600](#)
[TESTO 770-2](#) [0590 7702](#) [34194A](#) [KEW2433R](#) [KEW8112](#) [FLUKE 772](#) [380976-K](#) [MA3110](#) [MA440](#) [MA443](#) [MA445](#) [FLUKE-374 FC](#)
[TA74](#) [AMP-320](#) [CM55](#) [CM46](#) [I200](#) [ACD-6 PRO](#) [FLUKE-1630-2FC](#) [I410](#) [CM44](#) [CM42](#) [FLK-A3000 FC](#) [FLUKE-376 FC](#) [ACD-14-PRO](#)
[MA610](#) [F201](#) [F205](#) [MA193 \(250 MM\)](#) [DIGIFLEX 4000A 350MM](#)