

# Manual Switches

## Lighted Indicators

# AML41/42 Series

To order lamps see page 58.

### FEATURES

- Pushbutton style indicators match display of standard bezel lighted switches. Choice of incandescent or LED illumination.
- Lens style indicators use a special cap-like button which covers the bezel to present a larger display area, without affecting family appearance. Up to 3-lamp split screen capability. Incandescent illumination.



AML41  
(Use AML51 push-buttons only. Page 42.)



AML41  
(Use AML51-J/-K/-L lens buttons only. Page 42.)

### AML41 INCANDESCENT DISPLAY INDICATORS ORDER GUIDE

AML41 C		B	A	2
Housing Type		Bezel Color	Incand. Lamp Type	Terminal Type
Pushbutton Style:	Lens Style:			
<b>AML41 C</b> Square 1 lamp ckt.	<b>AML41 J</b> Rectangular 1 lamp ckt.	<b>B</b> Black	<b>A</b> No lamp installed	<b>2</b> .110 × .020 (Solder or Quick-Connect)
<b>AML41 D</b> Square 2 lamp ckts.	<b>AML41 K</b> Rectangular 2 lamp ckts.		<b>B</b> 6 V Lamp*	<b>3</b> .025 × .025 (Printed Circuit or Push-On)
<b>AML41 F</b> Rectangular 1 lamp ckt.	<b>AML41 L</b> Rectangular 3 lamp ckts.		<b>C</b> 14 V Lamp*	
<b>AML41 G</b> Rectangular 2 lamp ckts.			<b>E</b> 28 V Lamp*	

\* Lamps will be installed per each lamp circuit specified in the Housing Type.

Examples:

#### AML41CBA2

Square (pushbutton style) indicator housing with one lamp circuit; black bezel; .110 × .020 termination.

#### AML41JBA2

Rectangular (lens style) indicator housing with one lamp circuit; black bezel; .110 × .020 termination.



AML42C  
(Use AML52-C/-A pushbuttons only. Page 43.)



AML42S

### AML42 LED DISPLAY INDICATORS ORDER GUIDE

LEDs are not replaceable.

AML42 S	B	C	2
Housing Type	Bezel Color	LED Color/Voltage	Terminal Type/Diode Protection
<b>AML42 C</b> Square 1 LED	<b>B</b> Black	<b>Red</b> B V* C 5 V D 10 V E 15 V F 24 V	<b>2</b> .110 × .020 (Solder or Q.C.)
<b>AML42 S</b> Compact 1 LED	<b>Yellow</b> H V* J 5 V K 10 V L 15 V M 24 V	<b>Green</b> R V* S 5 V T 10 V W 15 V X 24 V	<b>3</b> .025 × .025 (Printed Circuit or Push-On)
			<b>8</b> .110 × .020 w/diode to protect LED
			<b>9</b> .025 × .025 w/diode to protect LED

Example: **AML42SBC2**

Compact indicator with black bezel; 5 volt red LED; .110 × .020 termination.

\* See LED application data, page 58, for these devices without current-limiting resistor.

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Industrial Panel Mount Indicators / Switch Indicators](#) category:*

*Click to view products by [Honeywell](#) manufacturer:*

Other Similar products are found below :

[LW1A-P1-W](#) [LW1B-A0L](#) [01-952.0](#) [01-152.025](#) [D38999/20FJ29PB L/C](#) [704-6012](#) [704-6020](#) [704-6023](#) [704-6026](#) [73.362.4028.0](#) [EUS-704.000.7](#) [750-1520](#) [9001OA120](#) [99-455.837](#) [99-486.837](#) [99-901.9](#) [99-902.9](#) [99-908.0](#) [99-909.4](#) [99-909.5](#) [A0244J1](#) [A3DT-500Y](#) [AL6M-P7P-A](#) [AOLQW-2B0600](#) [AP1M255-A](#) [APD106LN-A](#) [APD106LN-G](#) [APN1126-G](#) [APS122DN-W](#) [ATN2100](#) [AYLW4L-A](#) [18-237.035](#) [C0180AANA](#) [HW1A-L1-GD](#) [HW1A-P2-GL](#) [HW1F-3G](#) [HW1R-2DF20-R](#) [HW1X-BM411-R](#) [HW2A-L1-GL](#) [HW2A-P1-GD](#) [HW4S-31L](#) [HWAZ1N-OB](#) [PA2200/1](#) [PA2SHIELD](#) [21-931.0](#) [21-931.2](#) [96-923.5](#) [1625006](#) [99-451.837](#) [99-480.837](#)