

Description

Semicoa Semiconductors offers:

- Screening and processing per MIL-PRF-19500 Appendix E
- JAN level (2N2219AJ)
- JANTX level (2N2219AJX)
- JANTXV level (2N2219AJV)
- JANS level (2N2219AJS)
- QCI to the applicable level
- 100% die visual inspection per MIL-STD-750 method 2072 for JANTXV and JANS
- Radiation testing (total dose) upon request

Please contact Semicoa for special configurations
www.SEMICOA.com or (714) 979-1900

Applications

- General purpose
- Low power
- NPN silicon transistor



Features

- Hermetically sealed TO-39 metal can
- Also available in chip configuration
- Chip geometry 0400
- Reference document:
MIL-PRF-19500/251

Benefits

- Qualification Levels: JAN, JANTX, JANTXV and JANS
- Radiation testing available

Absolute Maximum Ratings		$T_C = 25^\circ\text{C}$ unless otherwise specified	
Parameter	Symbol	Rating	Unit
Collector-Emitter Voltage	V_{CEO}	50	Volts
Collector-Base Voltage	V_{CBO}	75	Volts
Emitter-Base Voltage	V_{EBO}	6	Volts
Collector Current, Continuous	I_C	800	mA
Power Dissipation, $T_A = 25^\circ\text{C}$ Derate linearly above 25°C	P_T	0.8 4.6	W mW/°C
Power Dissipation, $T_C = 25^\circ\text{C}$ Derate linearly above 25°C	P_T	3.0 17.0	W mW/°C
Operating Junction Temperature	T_J	-55 to +200	°C
Storage Temperature	T_{STG}	-55 to +200	°C

ELECTRICAL CHARACTERISTICS

characteristics specified at $T_A = 25^\circ\text{C}$

Off Characteristics						
Parameter	Symbol	Test Conditions	Min	Typ	Max	Units
Collector-Emitter Breakdown Voltage	$V_{(BR)CEO}$	$I_C = 10\text{ mA}$	50			Volts
Collector-Base Cutoff Current	I_{CBO1}	$V_{CB} = 75\text{ Volts}$			10	μA
Collector-Base Cutoff Current	I_{CBO2}	$V_{CB} = 60\text{ Volts}$			10	nA
Collector-Base Cutoff Current	I_{CBO3}	$V_{CB} = 60\text{ Volts}, T_A = 150^\circ\text{C}$			10	μA
Collector-Emitter Cutoff Current	I_{CES}	$V_{CE} = 50\text{ Volts}$			10	nA
Emitter-Base Cutoff Current	I_{EBO1}	$V_{EB} = 6\text{ Volts}$			10	μA
Emitter-Base Cutoff Current	I_{EBO2}	$V_{EB} = 4\text{ Volts}$			10	nA
On Characteristics			Pulse Test: Pulse Width = 300 μs , Duty Cycle $\leq 2.0\%$			
Parameter	Symbol	Test Conditions	Min	Typ	Max	Units
DC Current Gain	h_{FE1}	$I_C = 0.1\text{ mA}, V_{CE} = 10\text{ Volts}$	30			
	h_{FE2}	$I_C = 1.0\text{ mA}, V_{CE} = 10\text{ Volts}$	75		325	
	h_{FE3}	$I_C = 10\text{ mA}, V_{CE} = 10\text{ Volts}$	100			
	h_{FE4}	$I_C = 150\text{ mA}, V_{CE} = 10\text{ Volts}$	100		300	
	h_{FE5}	$I_C = 500\text{ mA}, V_{CE} = 10\text{ Volts}$	30			
	h_{FE6}	$I_C = 10\text{ mA}, V_{CE} = 10\text{ Volts}$ $T_A = -55^\circ\text{C}$	35			
Base-Emitter Saturation Voltage	V_{BEsat1}	$I_C = 150\text{ mA}, I_B = 15\text{ mA}$	0.6		1.2	Volts
	V_{BEsat2}	$I_C = 500\text{ mA}, I_B = 50\text{ mA}$			2.0	
Collector-Emitter Saturation Voltage	V_{CEsat1}	$I_C = 150\text{ mA}, I_B = 15\text{ mA}$			0.3	Volts
	V_{CEsat2}	$I_C = 500\text{ mA}, I_B = 50\text{ mA}$			1.0	
Dynamic Characteristics						
Parameter	Symbol	Test Conditions	Min	Typ	Max	Units
Magnitude – Common Emitter, Short Circuit Forward Current Transfer Ratio	$ h_{FE} $	$V_{CE} = 20\text{ Volts}, I_C = 20\text{ mA}, f = 100\text{ MHz}$	2.5		12	
Small Signal Short Circuit Forward Current Transfer Ratio	h_{FE}	$V_{CE} = 10\text{ Volts}, I_C = 1\text{ mA}, f = 1\text{ kHz}$	75			
Open Circuit Output Capacitance	C_{OBO}	$V_{CB} = 10\text{ Volts}, I_E = 0\text{ mA}, 100\text{ kHz} < f < 1\text{ MHz}$			8	pF
Open Circuit Input Capacitance	C_{IBO}	$V_{EB} = 0.5\text{ Volts}, I_C = 0\text{ mA}, 100\text{ kHz} < f < 1\text{ MHz}$			25	pF
Switching Characteristics						
Saturated Turn-On Time	t_{ON}				35	ns
Saturated Turn-Off Time	t_{OFF}				300	ns

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [semicoa](#) manufacturer:

Other Similar products are found below :

[JANS2N2907AUA](#) [JANTXV2N2907AUB](#) [JANTXV2N4033UB](#) [GRP-DATA-JANS2N2222A](#) [GRP-DATA-JANS2N3700](#) [GRP-DATA-JANS2N3866A](#) [JANTXV2N6193](#) [GRP-DATA-JANS2N2907AUB](#) [JANTX2N4150](#) [JANTX2N5237](#) [2N4033JANTX](#) [2N2907AJAN](#) [JANTX2N3737](#) [JANTX2N3637](#) [2N3019JVJANTXV](#) [JANTX2N2222AUB](#) [JANTX2N2907AUA](#) [2N3501JANTX](#) [2N6193JANTXV](#) [2N3737JANTX](#) [2N3637JANTX](#) [JANS2N2369A](#) [JANS2N4033UB](#) [2N3501JAN](#) [JANSR2N6990](#) [2N3811JANTX](#) [2N2222AUAJANTX](#) [JANS2N2222AUB](#) [JANS2N3501UB](#) [2N2369AUBJANTX](#) [JANTX2N4261](#) [2N3486AJANTX](#) [2N3507JANTX](#) [2N2857JANTX](#) [2N3499JANTX](#) [2N2219AJANTX](#) [JANTX2N4029](#) [2N2906AJAN](#) [JANTX2N6193](#) [2N3637UBJANTXV](#) [2N2907AUAJANTXV](#) [2N3810JANTX](#) [2N2484JANTX](#) [JANTX2N2222AUA](#) [2N3019JANTX](#) [2N6193JANTX](#) [2N2905AJANTX](#) [2N3700UBJANTXV](#) [JANTXV2N2907A](#) [2N3700JANTX](#)