

### Description

SEMICOA offers:

- Screening and processing per MIL-PRF-19500 Appendix E
- JAN level (2N3507J)
- JANTX level (2N3507JX)
- JANTXV level (2N3507JV)
- JANS level (2N3507JS)
- QCI to the applicable level
- 100% die visual inspection per MIL-STD-750 method 2072 for JANTXV and JANS
- Radiation testing (total dose) upon request

Please contact SEMICOA for special configurations  
[www.SEMICOA.com](http://www.SEMICOA.com) or (714) 979-1900

### Applications

- General purpose switching transistor
- Low power
- NPN silicon transistor



### Features

- Hermetically sealed TO-39 metal can
- Also available in chip configuration
- Chip geometry 1506
- Reference document: MIL-PRF-19500/349

### Benefits

- Qualification Levels: JAN, JANTX, JANTXV and JANS
- Radiation testing available

### Absolute Maximum Ratings

$T_C = 25^\circ\text{C}$  unless otherwise specified

Parameter	Symbol	Rating	Unit
Collector-Emitter Voltage	$V_{CEO}$	50	Volts
Collector-Base Voltage	$V_{CBO}$	80	Volts
Emitter-Base Voltage	$V_{EBO}$	5	Volts
Collector Current, Continuous	$I_C$	3	A
Power Dissipation, $T_A = 25^\circ\text{C}$ Derate linearly above $25^\circ\text{C}$	$P_T$	1 5.71	W mW/°C
Power Dissipation, $T_C = 25^\circ\text{C}$ Derate linearly above $25^\circ\text{C}$	$P_T$	5 28.6	W mW/°C
Thermal Resistance	$R_{\theta JA}$	175	°C/W
Operating Junction Temperature	$T_J$	-65 to +200	°C
Storage Temperature	$T_{STG}$		

### ELECTRICAL CHARACTERISTICS

characteristics specified at  $T_A = 25^\circ\text{C}$

#### Off Characteristics

Parameter	Symbol	Test Conditions	Min	Typ	Max	Units
Collector-Base Breakdown Voltage	$V_{(BR)CBO}$	$I_C = 100 \mu\text{A}$	80			Volts
Collector-Emitter Breakdown Voltage	$V_{(BR)CEO}$	$I_C = 10 \text{ mA}$	50			Volts
Emitter-Base Breakdown Voltage	$V_{(BR)EBO}$	$I_E = 10 \mu\text{A}$	5			Volts
Collector-Emitter Cutoff Current	$I_{CEX1}$	$V_{CE} = 60 \text{ Volts}, V_{EB} = 4 \text{ Volts}$			1	$\mu\text{A}$
Collector-Emitter Cutoff Current	$I_{CEX2}$	$V_{CE} = 60 \text{ Volts}, V_{EB} = 4 \text{ Volts}, T_A = 150^\circ\text{C}$			1.5	mA

#### On Characteristics

Pulse Test: Pulse Width = 300  $\mu\text{s}$ , Duty Cycle  $\leq 2.0\%$

Parameter	Symbol	Test Conditions	Min	Typ	Max	Units
DC Current Gain	$h_{FE1}$	$I_C = 500 \text{ mA}, V_{CE} = 1 \text{ Volts}$	35		175	
	$h_{FE2}$	$I_C = 1.5 \text{ A}, V_{CE} = 2 \text{ Volts}$	30		150	
	$h_{FE3}$	$I_C = 2.5 \text{ A}, V_{CE} = 3 \text{ Volts}$	25			
	$h_{FE4}$	$I_C = 3.0 \text{ A}, V_{CE} = 5 \text{ Volts}$	20			
	$h_{FE5}$	$I_C = 500 \text{ mA}, V_{CE} = 1 \text{ Volts}, T_A = -55^\circ\text{C}$	17			
Base-Emitter Saturation Voltage	$V_{BEsat1}$	$I_C = 500 \text{ mA}, I_B = 50 \text{ mA}$	0.8		1.0	Volts
	$V_{BEsat2}$	$I_C = 1.5 \text{ A}, I_B = 150 \text{ mA}$		1.3		
	$V_{BEsat3}$	$I_C = 2.5 \text{ A}, I_B = 250 \text{ mA}$		2.0		
Collector-Emitter Saturation Voltage	$V_{CEsat1}$	$I_C = 500 \text{ mA}, I_B = 50 \text{ mA}$			0.5	Volts
	$V_{CEsat2}$	$I_C = 1.5 \text{ A}, I_B = 150 \text{ mA}$			1.0	
	$V_{CEsat3}$	$I_C = 2.5 \text{ A}, I_B = 250 \text{ mA}$			1.5	

#### Dynamic Characteristics

Parameter	Symbol	Test Conditions	Min	Typ	Max	Units
Magnitude – Common Emitter, Short Circuit Forward Current Transfer Ratio	$ h_{FE} $	$V_{CE} = 5 \text{ Volts}, I_C = 100 \text{ mA}, f = 20 \text{ MHz}$	3		15	
Open Circuit Output Capacitance	$C_{OBO}$	$V_{CB} = 10 \text{ Volts}, I_E = 0 \text{ mA}, 100 \text{ kHz} < f < 1 \text{ MHz}$			40	pF
Open Circuit Input Capacitance	$C_{IBO}$	$V_{EB} = 3 \text{ Volts}, I_C = 0 \text{ mA}, 100 \text{ kHz} < f < 1 \text{ MHz}$			300	pF
Delay Time	$t_d$	$I_C = 1.5 \text{ A}, I_{B1} = 150 \text{ mA}$			15	ns
Rise Time	$t_r$	$I_C = 1.5 \text{ A}, I_{B1} = 150 \text{ mA}$			30	ns

#### Switching Characteristics

Storage Time	$t_s$	$I_C = 1.5 \text{ A}, I_{B1}=I_{B2} = 150 \text{ mA}$			55	ns
Fall Time	$t_f$	$I_C = 1.5 \text{ A}, I_{B1}=I_{B2} = 150 \text{ mA}$			35	ns

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [semicoa](#) manufacturer:*

Other Similar products are found below :

[JANS2N2907AUA](#) [JANTXV2N2907AUB](#) [JANTXV2N4033UB](#) [GRP-DATA-JANS2N2222A](#) [GRP-DATA-JANS2N3700](#) [GRP-DATA-JANS2N3866A](#) [JANTXV2N6193](#) [GRP-DATA-JANS2N2907AUB](#) [JANTX2N4150](#) [JANTX2N5237](#) [2N4033JANTX](#) [2N2907AJAN](#) [JANTX2N3737](#) [JANTX2N3637](#) [2N3019JVJANTXV](#) [JANTX2N2222AUB](#) [JANTX2N2907AUA](#) [2N3501JANTX](#) [2N6193JANTXV](#) [2N3737JANTX](#) [2N3637JANTX](#) [JANS2N2369A](#) [JANS2N4033UB](#) [2N3501JAN](#) [JANSR2N6990](#) [2N3811JANTX](#) [2N2222AUAJANTX](#) [JANS2N2222AUB](#) [JANS2N3501UB](#) [2N2369AUBJANTX](#) [JANTX2N4261](#) [2N3486AJANTX](#) [2N3507JANTX](#) [2N2857JANTX](#) [2N3499JANTX](#) [2N2219AJANTX](#) [JANTX2N4029](#) [2N2906AJAN](#) [JANTX2N6193](#) [2N3637UBJANTXV](#) [2N2907AUAJANTXV](#) [2N3810JANTX](#) [2N2484JANTX](#) [JANTX2N2222AUA](#) [2N3019JANTX](#) [2N6193JANTX](#) [2N2905AJANTX](#) [2N3700UBJANTXV](#) [JANTXV2N2907A](#) [2N3700JANTX](#)