



## AX Series – 50/60Hz Current Transformers

### Applications


- Power Monitoring
- Current Measurement
- Instrumentation

### Features

- High Output Voltage in small package
- Good Linearity over current range
- 2.5KV Isolation
- High Saturation current
- Operating temperature range -40 deg C to +120 deg C





| Electrical Specifications @ 20°C |       |                     |                      |
|----------------------------------|-------|---------------------|----------------------|
| Part No                          | Turns | Current Rating in A | Winding Resistance Ω |
| AX-0500                          | 500   | 5.0                 | 32                   |
| AX-0750                          | 750   | 7.5                 | 55                   |
| AX-1000                          | 1000  | 10.0                | 93                   |
| AX-1500                          | 1500  | 15.0                | 140                  |




AX-0500

Output Voltage Vs Input Current


AX-0750



AX-1000




AX-1500






## AX Series – 50/60Hz Current Transformers

AX-0500




### Saturation Current Response


AX-0750



AX-1000




AX-1500






AX-0500

### Phase Angle Vs Primary Current

AX-0750



AX-1000



# X-ON Electronics

Largest Supplier of Electrical and Electronic Components

***Click to view similar products for Current Transformers category:***

***Click to view products by Talema manufacturer:***

Other Similar products are found below :

[MP3500](#) [BV UI 302 0156](#) [45029](#) [BV EI 302 2863](#) [BV EI 303 2809](#) [BV EI 303 3060](#) [BV EI 305 2309](#) [BV EI 306 3604](#) [BV EI 481 1295](#) [BV EI 481 1325](#) [BV UI 301 0133](#) [BV UI 302 0144](#) [BV UI 302 0161](#) [BV UI 304 0019](#) [BV UI 304 0129](#) [BV UI 304 0159](#) [BV UI 304 0173](#) [TI-EF16-2X4V-4W](#) [SPCT62/40150/5AVA3CL1](#) [SPCT62/30100/5AVA1CL1](#) [SPCT62/3075/5AVA1CL3](#) [SPCT62/40150/5AVA1.5CL1](#) [SPCT62/40200/5AVA2.5CL0.5](#) [SPCT62/40300/5AVA3CL0.5](#) [CTD-KIT](#) [44013](#) [44017](#) [44021](#) [44098](#) [44101](#) [44134](#) [44171](#) [44174](#) [44178](#) [44180](#) [44248](#) [44250](#) [44278](#) [44339](#) [44340](#) [44373](#) [44375](#) [44376](#) [44378](#) [44379](#) [44436](#) [44831](#) [B82801B0925A200](#) [PA3655NL](#) [PA3828NL](#)