

Audio Quad cable



Applications:
Professional audio QUAD cable for Broadcast. Cable with two pairs for double balancing between the conductors and the total shield.

Characteristics:
 Conductors: O.F.C. red copper
 Cond. Insulation: Compact XLPE
 Pair colours: Transparent-Red, Transparent-Blue
 Waste filler between conductors
 Total taping in unweaved polyester
 Shield: Braided covering 100% O.F.C. tinned copper
 Sheath: PVC
 Sheath colours: Black, Grey



tasker® Code	Cond. number	Nominal section mm ²	Cond. Format. mm.	External Core Ø mm.	External Cable Diameter mm.	Reel or Spool (* pag. II)		
						mt.	Type	Kg.
C287	2x2	2 x 2 x 0,22 (24 AWG)	28x0,10	1,1	6,6	100	B	6,0

Conductor Resistance Ω/Km ± 5%	Capacity Core/core pF/mt	Capacity Core/shield pF/mt
90	65	120
	Max rated Voltage AC - V 49	Operative Temperature °C -15 / +70

Microphone cable



Applications:
Special flexible audio cable with separate shielded cores suitable for microphone bases.

Characteristics:
 Conductors: O.F.C. tinned copper
 Cond. Insulation: PVC
 Core colours: Green, Blue, Black, Yellow
 Shields: Braided covering 95% O.F.C. red copper
 Sheath: PVC
 Sheath colour: Black



tasker® Code	Cond. number	Nominal section mm ²	Cond. Format. mm.	External Core Ø mm.	External Cable Diameter mm.	Reel or Spool (* pag. II)		
						mt.	Type	Kg.
C207	2 +2	2 x 0,15 +2 x 0,15 (25 AWG)	19x0,10	1,2	4,7	100	B	3,8

Audio cable for microphone bases

Conductor Resistance Ω/Km ± 5%	Capacity Core/core pF/mt	Capacity Core/shield pF/mt
120		260
	Max rated Voltage AC - V 49	Operative Temperature °C -15 / +70

Notes:

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Audio Cables](#) / [Video Cables](#) / [RCA Cables](#) category:

Click to view products by [Tasker](#) manufacturer:

Other Similar products are found below :

[59384500100E](#) [73-6310-10](#) [73-6311-10](#) [73-6313-3](#) [73-6313-6](#) [PCX-60-50](#) [RCA10RCA](#) [1-3737-600-3216](#) [15AK25X](#) [25FK25](#) [LF3BLX](#) [30-1511-10](#) [30AR30](#) [30AK30](#) [30AN30](#) [RCA05RCA](#) [RCA05RCAB](#) [RCA05TS](#) [RCA10RCAB](#) [420001400-3](#) [426058900-3](#) [TT6RX](#) [TT7BKX](#) [TT93602](#) [426058300-3](#) [LF1BKX](#) [LF3RX](#) [0887418300](#) [73-6312-6](#) [73-6314-3](#) [73-6352-3](#) [VMP3YX](#) [VMP2YX](#) [68767-0003](#) [TT746](#) [TT744](#) [CN13B](#) [LF4GNX](#) [LF2GYX](#) [426494200-3](#) [LF1RX](#) [VMPBNCF](#) [LF10GNX](#) [427492100-3](#) [LF4BLX](#) [TT747N2](#) [TT864](#) [LF2YX](#) [426491500-3](#) [426523700-3](#)