



ELECTRONICS, INC.  
44 FARRAND STREET  
BLOOMFIELD, NJ 07003  
(973) 748-5089  
<http://www.nteinc.com>

**NTE5452 thru NTE5458**  
**Silicon Controlled Rectifier (SCR)**  
**4 Amp Sensitive Gate, TO202**

**Description:**

The NTE5452 through NTE5458 are sensitive gate 4 Amp SCR's in a TO202 type package designed to be driven directly with IC and MOS devices. These reverse-blocking triode thyristors may be switched from off-state to conduction by a current pulse applied to the gate terminal. They are designed for control applications in lighting, heating, cooling, and static switching relays.

**Absolute Maximum Ratings:**

Repetitive Peak Reverse Voltage ( $T_C = +100^\circ\text{C}$ ),  $V_{RRM}$

NTE5452 .....	30V
NTE5453 .....	50V
NTE5454 .....	100V
NTE5455 .....	200V
NTE5456 .....	300V
NTE5457 .....	400V
NTE5458 .....	600V

Repetitive Peak Off-State Voltage ( $T_C = +100^\circ\text{C}$ ),  $V_{DRXM}$

NTE5452 .....	30V
NTE5453 .....	50V
NTE5454 .....	100V
NTE5455 .....	200V
NTE5456 .....	300V
NTE5457 .....	400V
NTE5458 .....	600V

RMS On-State Current,  $I_{T(RMS)}$  ..... 4A

Peak Surge (Non-Repetitive) On-State Current (One Cycle at 50 or 60Hz),  $I_{TSM}$  ..... 20A

Peak Gate-Trigger Current (3μs Max),  $I_{GTM}$  ..... 1A

Peak Gate-Power Dissipation ( $I_{GT} \leq I_{GTM}$  for 3μs Max),  $P_{GM}$  ..... 20W

Average Gate Power Dissipation,  $P_{G(AV)}$  ..... 200mW


Operating Temperature Range,  $T_{opr}$  .....  $-40^\circ$  to  $+100^\circ\text{C}$

Storage Temperature Range,  $T_{stg}$  .....  $-40^\circ$  to  $+150^\circ\text{C}$

Typical Thermal Resistance, Junction-to-Case,  $R_{thJC}$  .....  $+5^\circ\text{C/W}$

## Electrical Characteristics:

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Peak Off-State Current	$I_{RRM}$	$V_{RRM} = \text{Max}$ , $V_{DRXM} = \text{Max}$ , $T_C = +100^\circ\text{C}$ , $R_{G-K} = 1\text{k}\Omega$	-	-	100	$\mu\text{A}$
	$I_{DRXM}$		-	-	100	$\mu\text{A}$
Maximum On-State Voltage	$V_{TM}$	$T_C = +25^\circ\text{C}$ , $I_T = 4\text{A}$ (Peak)	-	-	2.2	V
DC Holding Current	$I_{HOLD}$	$T_C = +25^\circ\text{C}$	-	-	3	mA
DC Gate-Trigger Current	$I_{GT}$	$V_D = 6\text{VDC}$ , $R_L = 100\Omega$ , $T_C = +25^\circ\text{C}$	-	50	200	$\mu\text{A}$
DC Gate-Trigger Voltage	$V_{GT}$	$V_D = 6\text{VDC}$ , $R_L = 100\Omega$ , $T_C = +25^\circ\text{C}$	-	-	0.8	V
Total Gate Controlled Turn-On Time	$t_{gt}$	$T_C = +25^\circ\text{C}$	-	1.2	-	$\mu\text{s}$
$I^2t$ for Fusing Reference	$I^2t$	$> 1.5\text{msoc}$	-	-	0.5	$\text{A}^2\text{sec}$
Critical rate of Applied Forward Voltage	$dv/dt$ (critical)	$R_{G-K} = 1\text{k}\Omega$ , $T_C = +100^\circ\text{C}$	-	8	-	$\text{V}/\mu\text{s}$



# X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [SCRs](#) category:*

*Click to view products by [NTE manufacturer:](#)*

Other Similar products are found below :

[NTE5428](#) [NTE5448](#) [NTE5457](#) [NTE5511](#) [T1500N16TOF VT](#) [T720N18TOF](#) [T880N14TOF](#) [T880N16TOF](#) [TN1205H-6G](#) [TN1215-800B-TR](#)  
[TS110-7UF](#) [TT104N12KOF-A](#) [TT104N12KOF-K](#) [TT162N16KOF-A](#) [TT162N16KOF-K](#) [TT330N16AOF](#) [VS-111RKI120PBF](#) [VS-16RIA100](#)  
[VS-22RIA20](#) [VS-2N5206](#) [VS-2N685](#) [VS-40TPS08A-M3](#) [VS-50RIA10](#) [057219R](#) [T1190N16TOF VT](#) [T1220N22TOF VT](#) [T201N70TOH](#)  
[T830N14TOF](#) [T830N18TOF](#) [TD92N16KOF-A](#) [TT250N12KOF-K](#) [VS-ST180S12P0V](#) [VS-25RIA40](#) [VS-16RIA120](#) [VS-30TPS08PBF](#)  
[TN1215-800G-TR](#) [NTE5427](#) [NTE5442](#) [X0405NF 1AA2](#) [VS-ST300S20P0PBF](#) [T2160N28TOF VT](#) [TT251N16KOF-K](#) [VS-22RIA100](#) [VS-16RIA40](#) [CR02AM-8#F00](#) [VS-ST110S12P0VPBF](#) [TD250N16KOF-A](#) [GA301A](#) [VS-ST110S16P0](#) [VS-10RIA10](#)