

Storage Adapters

November
2013



LSI Storage Adapters

Nytro™ Application Acceleration Solutions	Page 3
MegaRAID® Solutions	Page 5
3ware® Solutions	Page 6
Syncro® Shared Solutions	Page 6
Host Bus Adapter Solutions	Page 7
Cables	Page 8
Cache Protection Options	Page 9
Advanced Software Options	Page 9

Nytro Application Acceleration Solutions

Row	Nytro	Ordering Part No.	PKG	Host Bus Type	Memory	Form Factor	Description	Applications	Kit Contents
NYTRO WARP DRIVE CARD									
1	NWD-WLP4-200	LSI00323	Kit Only	PCI Express 2.0 x8	200 GB SLC	Low Profile	The Nytro WarpDrive NWD-WLP4-200, low profile, small form factor PCIe 2.0 enterprise NAND flash card	Write Intensive	NWD-WLP4-200, USB drive with drivers, software and documentation, One Full Height Bracket
2	NWD-WLP4-400	LSI00324	Kit Only	PCI Express 2.0 x8	400 GB SLC	Low Profile	The Nytro WarpDrive NWD-WLP4-400, low profile, small form factor PCIe 2.0 enterprise NAND flash card	Write Intensive	NWD-WLP4-400, USB drive with drivers, software and documentation, One Full Height Bracket
3	NWD-BLP4-400	LSI00318	Kit Only	PCI Express 2.0 x8	400 GB eMLC	Low Profile	The Nytro WarpDrive NWD-BLP4-400, low profile, small form factor PCIe 2.0 enterprise NAND flash card	Balanced Reads and Writes	NWD-BLP4-400, USB drive with drivers, software and documentation, One Full Height Bracket
4	NWD-BLP4-800	LSI00319	Kit Only	PCI Express 2.0 x8	800 GB eMLC	Low Profile	The Nytro WarpDrive NWD-BLP4-800, low profile, small form factor PCIe 2.0 enterprise NAND flash card	Balanced Reads and Writes	NWD-BLP4-800, USB drive with drivers, software and documentation, One Full Height Bracket
5	NWD-BLP4-1600	LSI00320	Kit Only	PCI Express 2.0 x8	1600 GB eMLC	Low Profile	The Nytro WarpDrive NWD-BLP4-1600, low profile, small form factor PCIe 2.0 enterprise NAND flash card	Balanced Reads and Writes	NWD-BLP4-1600, USB drive with drivers, software and documentation, One Full Height Bracket
6	NWD-BFH8-3200	LSI00393	Kit Only	PCI Express 3.0 x8	3200 GB eMLC	Full Height	The Nytro WarpDrive NWD-BFH8-3200, Full Height form factor PCIe 3.0 enterprise NAND flash card	Balanced Reads and Writes	NWD-BFH8-3200, USB drive with drivers, software and documentation, auxiliary power cable

Nytro Application Acceleration Solutions

Row	Nytro	Ordering Part No.	PKG	Host Bus Type	Channel/Ports	I/O Processor	Internal Connector	Cache Protection Option	Memory	No. of Devices Supported	RAID Levels Supported	Cable(s) Included in Kit	Form Factor	Description	Applications	Kit Contents
NYTRO MegaRAID CARD																
7	NMR 8100-4i	LSI00350	Kit Only	PCI Express 3.0 x8	4	LSI SAS2208	1 x SAS SFF 8087 x4	Nytro MegaRAID SCM01	100 GB SLC	128	0, 1, 5, 6, 10, 50, 60	No	Low Profile	The LSI Nytro MegaRAID NMR 8100-4i, 100GB NAND flash, Low profile, MD2, x8 PCIe 3.0, x4 SAS ports with automatic hot spot data caching	Balanced Reads and Writes across data with significant hot spots	NMR-8100-4i, USB drive with drivers, software and documentation, One Full Height Bracket
8	NMR 8110-4i	LSI00351	Kit Only	PCI Express 3.0 x8	4	LSI SAS2208	1 x SAS SFF 8087 x4	Nytro MegaRAID SCM01	200 GB eMLC	128	0, 1, 5, 6, 10, 50, 60	No	Low Profile	The LSI Nytro MegaRAID NMR 8110-4i, 200GB NAND flash, Low profile, MD2, x8 PCIe 3.0, x4 SAS ports with automatic hot spot data caching	Balanced Reads and Writes across data with significant hot spots	NMR-8110-4i, USB drive with drivers, software and documentation, One Full Height Bracket
9	NMR 8120-4i	LSI00351	Kit Only	PCI Express 3.0 x8	4	LSI SAS2208	1 x SAS SFF 8087 x4	Nytro MegaRAID SCM01	800GB eMLC	128	0, 1, 5, 6, 10, 50, 60	No	Low Profile	The LSI Nytro MegaRAID NMR 8120-4i, 800GB NAND flash, Low profile, MD2, x8 PCIe 3.0, x4 SAS ports with automatic hot spot data caching	Balanced Reads and Writes across data with significant hot spots	NMR-8120-4i, USB drive with drivers, software and documentation, One Full Height Bracket
10	NMR-8110-4e	LSI00395	Kit Only	PCI Express 3.0 x8	4	LSI SAS2208	1 x SAS SFF 8088 x4	Nytro MegaRAID SCM01	200 GB eMLC	128	0, 1, 5, 6, 10, 50, 60	No	Low Profile	The LSI Nytro MegaRAID NMR 8110-4e, 200GB NAND flash, Low profile, MD2, x8 PCIe 3.0, x4 SAS ports with automatic hot spot data caching	Balanced Reads and Writes across daa with significant hot spots	NMR-8110-4e, USB drive with drivers, software and documentation, one full height bracket
11	NMR-8120-4e	LSI00396	Kit Only	PCI Express 3.0 x8	4	LSI SAS2208	1 x SAS SFF 8088 x4	Nytro MegaRAID SCM01	800 GB eMLC	128	0, 1, 5, 6, 10, 50, 60	No	Low Profile	The LSI Nytro MegaRAID NMR 8120-4e, 800GB NAND flash, Low profile, MD2, x8 PCIe 3.0, x4 SAS ports with automatic hot spot data caching	Balanced Reads and Writes across daa with significant hot spots	NMR-8120-4e, USB drive with drivers, software and documentation, one full height bracket
12	Nytro MegaRAID SCM01	LSI00355	Kit Only	-	-	-	-	-	-	-	-	-	-	Optional SuperCap kit for DRAM Cache Protection for the LSI Nytro MegaRAID NMR 8100-4i, 8110-4i, and 8120-4i	-	-

MegaRAID® Solutions

Row	MegaRAID	Ordering Part No.	PKG	Host Bus Type	Channel/Ports	I/O Processor	External Connector	Internal Connector	Cache Protection Option	Memory (MB)	No. of Drives Supported	RAID Levels	Cable(s) Included in Kit
12 Gb/s SATA+SAS RAID CONTROLLERS													
1	MegaRAID SAS 9361-8i	LSI00416 LSI00417	KIT SGL	PCI Express 3.0 x8	8	LSI SAS3108 ROC	N/A	2 x SFF-8643 Mini-SAS HD	LSICVM02	1GB	128	0, 1, 5, 6, 10, 50, 60	Two Mini-SAS HD to (4) SATA
2	MegaRAID SAS 9361-4i	LSI00414 LSI00415	KIT SGL	PCI Express 3.0 x8	4	LSI SAS3108 ROC	N/A	1 x SFF-8643 Mini-SAS HD	LSICVM02	1GB	128	0, 1, 5, 6, 10, 50, 60	One Mini-SAS HD to (4) SATA
3	MegaRAID SAS 9341-8i	LSI00408 LSI00407	KIT SGL	PCI Express 3.0 x8	8	LSI SAS3008	N/A	2 x SFF-8643 Mini-SAS HD	N/A	N/A	64	0, 1, 5, 10, 50, JBOD	Two Mini-SAS HD to (4) SATA
4	MegaRAID SAS 9341-4i	LSI00406 LSI00419	KIT SGL	PCI Express 3.0 x8	4	LSI SAS3008	N/A	1 x SFF-8643 Mini-SAS HD	N/A	N/A	64	0, 1, 5, 10, 50, JBOD	One Mini-SAS HD to (4) SATA
6 Gb/s SATA+SAS RAID CONTROLLERS													
5	MegaRAID SAS 9280-24i4e	LSI00211	SGL	PCI Express 2.0 x8	28	LSI SAS2108 ROC	1 x SAS SFF-8088 x4	6 x SAS SFF-8087 x4	LSIiBBU07 or LSIiBBU08	512MB	240	0, 1, 5, 6, 10, 50, 60	N/A
6	MegaRAID SAS 9280-16i4e	LSI00210	SGL	PCI Express 2.0 x8	20	LSI SAS2108 ROC	1 x SAS SFF-8088 x4	4 x SAS SFF-8087 x4	LSIiBBU07 or LSIiBBU08	512MB	240	0, 1, 5, 6, 10, 50, 60	N/A
7	MegaRAID SAS 9286CV-8e	LSI00333	SGL	PCI Express 3.0 x8	8	LSISAS2208 ROC	2 x SAS SFF-8088 x4	N/A	CacheVault Included	1GB	240	0, 1, 5, 6, 10, 50, 60	N/A
8	MegaRAID SAS 9286CV-8eCC	LSI00335	SGL	PCI Express 3.0 x8	8	LSISAS2208 ROC	2 x SAS SFF-8088 x4	N/A	CacheVault Included	1GB	240	0, 1, 5, 6, 10, 50, 60	N/A
9	MegaRAID SAS 9285CV-8e	LSI00298	SGL	PCI Express 2.0 x8	8	LSISAS2208 ROC	2 x SAS SFF-8088 x4	N/A	CacheVault Included	1GB	240	0, 1, 5, 6, 10, 50, 60	N/A
10	MegaRAID SAS 9286-8e	LSI00332	SGL	PCI Express 3.0 x8	8	LSISAS2208 ROC	2 x SAS SFF-8088 x4	N/A	LSIiBBU09	1GB	240	0, 1, 5, 6, 10, 50, 60	N/A
11	MegaRAID SAS 9280-8e	LSI00205	SGL	PCI Express® 2.0 x8	8	LSI SAS2108 ROC	2 x SAS SFF-8088 x4	N/A	LSIiBBU07 or LSIiBBU08	512	240	0, 1, 5, 6, 10, 50, 60	N/A
12	MegaRAID SAS 9280-4i4e	LSI00209	SGL	PCI Express 2.0 x8	8	LSI SAS2108 ROC	1 x SAS SFF-8088 x4	1 x SAS SFF-8087 x4	LSIiBBU07 or LSIiBBU08	512	240	0, 1, 5, 6, 10, 50, 60	N/A
13	MegaRAID SAS 9260-16i	LSI00208	SGL	PCI Express 2.0 x8	16	LSI SAS2108 ROC	N/A	4 x SAS SFF-8087 x4	LSIiBBU07 or LSIiBBU08	512	128	0, 1, 5, 6, 10, 50, 60	N/A
14	MegaRAID SAS 9271-8i	LSI00331 LSI00330	KIT SGL	PCI Express 3.0 x8	8	LSISAS2208 ROC	N/A	2 x SAS SFF-8087 x4	LSIiBBU09 or LSICVM01	1GB	128	0, 1, 5, 6, 10, 50, 60	Two Mini-SAS to (4) SATA
15	MegaRAID SAS 9271-8iCC	LSI00334	SGL	PCI Express 3.0 x8	8	LSISAS2208 ROC	N/A	2 x SAS SFF-8087 x4	LSIiBBU09 or LSICVM01	1GB	128	0, 1, 5, 6, 10, 50, 60	N/A
16	MegaRAID SAS 9270-8i	LSI00327 LSI00326	KIT SGL	PCI Express 3.0 x8	8	LSISAS2208 ROC	N/A	2 x SAS SFF-8087 x4	LSIiBBU09	1GB	128	0, 1, 5, 6, 10, 50, 60	Two Mini-SAS to (4) SATA
17	MegaRAID SAS 9266-8i	LSI00296 LSI00295	KIT SGL	PCI Express 2.0 x8	8	LSISAS2208 ROC	N/A	2 x SAS SFF-8087 x4	LSIiBBU09 or LSICVM01	1GB	128	0, 1, 5, 6, 10, 50, 60	Two Mini-SAS to (4) SATA
18	MegaRAID SAS 9260-8i	LSI00202 LSI00198	KIT SGL	PCI Express 2.0 x8	8	LSI SAS2108 ROC	N/A	2 x SAS SFF-8087 x4	LSIiBBU07 or LSIiBBU08	512	128	0, 1, 5, 6, 10, 50, 60	Two Mini-SAS to (4) SATA
19	MegaRAID SAS 9261-8i	LSI00212	SGL	PCI Express 2.0 x8	8	LSI SAS2108 ROC	N/A	2 x SAS SFF-8087 x4	LSIiBBU07 or LSIiBBU08	512	128	0, 1, 5, 6, 10, 50, 60	N/A
20	MegaRAID SAS 9271-4i	LSI00329 LSI00328	KIT SGL	PCI Express 3.0 x8	4	LSISAS2208 ROC	N/A	2 x SAS SFF-8087 x4	LSIiBBU09 or LSICVM01	1GB	128	0, 1, 5, 6, 10, 50, 60	One Mini-SAS to (4) SATA
21	MegaRAID SAS 9266-4i	LSI00306 LSI00305	KIT SGL	PCI Express 2.0 x8	4	LSISAS2208 ROC	N/A	1 x SAS SFF-8087 x4	LSIiBBU09 or LSICVM01	1GB	128	0, 1, 5, 6, 10, 50, 60	One Mini-SAS to (4) SATA
22	MegaRAID SAS 9260-4i	LSI00201 LSI00197	KIT SGL	PCI Express 2.0 x8	4	LSI SAS2108 ROC	N/A	1 x SAS SFF-8087 x4	LSIiBBU07 or LSIiBBU08	512	128	0, 1, 5, 6, 10, 50, 60	One Mini-SAS to (4) SATA
23	MegaRAID SAS 9240-8i	LSI00204 LSI00200	KIT SGL	PCI Express 2.0 x8	8	LSISAS2008	N/A	2 x SAS SFF-8087 x4	N/A	N/A	64	0, 1, 5, 10, 50, JBOD	Two Mini-SAS to (4) SATA
24	MegaRAID SAS 9240-4i	LSI00203 LSI00199	KIT SGL	PCI Express 2.0 x8	4	LSISAS2008	N/A	1 x SAS SFF-8087 x4	N/A	N/A	64	0, 1, 5, 10, 50, JBOD	One Mini-SAS to (4) SATA

3ware® Solutions

Row	3ware	Ordering Part No.	PKG	Host Bus Type	Channel/ Ports	I/O Processor	External Connector	Internal Connector	Battery Option	Memory (MB)	No. of Drives Supported	RAID Levels	Cable(s) Included in Kit
6 Gb/s SATA+SAS RAID CONTROLLERS													
1	3ware SAS 9750-24i4e	LSI00253 LSI00251	KIT SGL	PCI Express 2.0 x8	28	LSI SAS2108 ROC	1 x SAS SFF-8088 x4	6 x SAS SFF-8087 x4	LSIIBBU07	512	127	0, 1, 5, 6, 10, 50, and Single Disk	(6) CBL-SFF8087SB-08M 80cm Multi-lane SATA+SAS with Sideband (1) CBL-SFF8088SAS-10M 1m Multi-lane SATA+SAS
2	3ware SAS 9750-16i4e	LSI00254 LSI00252	KIT SGL	PCI Express 2.0 x8	20	LSI SAS2108 ROC	1 x SAS SFF-8088 x4	4 x SAS SFF-8087 x4	LSIIBBU07	512	127	0, 1, 5, 6, 10, 50, and Single Disk	(4) CBL-SFF8087SB-08M 80cm Multi-lane SATA+SAS with Sideband (1) CBL-SFF8088SAS-10M 1m Multi-lane SATA+SAS
3	3ware SAS 9750-8e	LSI00250 LSI00243	KIT SGL	PCI Express 2.0 x8	8	LSI SAS2108 ROC	2 x SAS SFF-8088 x4	N/A	LSIIBBU07	512	127	0, 1, 5, 6, 10, 50, and Single Disk	(2) CBL-SFF8088SAS-10M 1m Multi-lane SATA+SAS
4	3ware SAS 9750-4i4e	LSI00241 LSI00242	KIT SGL	PCI Express 2.0 x8	8	LSI SAS2108 ROC	1 x SAS SFF-8088 x4	1 x SAS SFF-8087 x4	LSIIBBU07	512	127	0, 1, 5, 6, 10, 50, and Single Disk	(1) CBL-SFF8087SB-08M 80cm Multi-lane SATA+SAS with Sideband (1) CBL-SFF8088SAS-10M 1m Multi-lane SATA+SAS
5	3ware SAS 9750-8i	LSI00213 LSI00214	KIT SGL	PCI Express 2.0 x8	8	LSI SAS2108 ROC	N/A	2 x SAS SFF-8087 x4	LSIIBBU07	512	127	0, 1, 5, 6, 10, 50, and Single Disk	(2) CBL-SFF8087-06M 60cm Multi-lane SATA+SAS
6	3ware SAS 9750-4i	LSI00215 LSI00216	KIT SGL	PCI Express 2.0 x8	4	LSI SAS2108 ROC	N/A	2 x SAS SFF-8087 x4	LSIIBBU07	512	127	0, 1, 5, 6, 10, 50, and Single Disk	(1) CBL-SFF8087-06M 60cm Multi-lane SATA+SAS

Syncro Shared Solutions

Row	Syncro	Ordering Part No.	PKG	Host Bus Type	Channel/ Ports	Bootable	External Connector	Internal Connector	Form Factor	No. of Drives Supported	Cache Memory	Cache Protection	RAID Levels
1	Syncro CS 9271-8i	LSI00392	KIT	PCI Express 3.0 x8	8	Yes	N/A	2 x SFF-8087	Low-profile MD2	96	1GB	CacheVault Included	0, 1, 5, 6, 10, 50
2	Syncro CS 9286-8e	LSI00356	KIT	PCI Express 3.0 x8	8	Yes	2 x SFF-8088	N/A	Low-profile MD2	96	1GB	CacheVault Included	0, 1, 5, 6, 10, 50

Host Bus Adapter Solutions

Row	HBA	Ordering Part No.	PKG	Host Bus Type	Channel/Ports	Bootable	External Connector	Internal Connector	No. of Devices Supported	Form Factor	Transfer Rate/Sec	RAID Levels	Cable(s) Included in Kit
12Gb/s SATA+SAS HBAs													
1	LSI SAS 9300-16e	LSI00344	SGL	PCI Express 3.0 x8	16	Yes	4 x SFF8644 Mini-SAS HD	N/A	2048	Full-Height	6.4GB/s (Full Duplex)	JBOD	N/A
2	LSI SAS 9300-8e	LSI00343	SGL	PCI Express 3.0 x8	8	Yes	2 x SFF8644 Mini-SAS HD	N/A	1024	Low-profile MD2	6.4 GB/s (Full Duplex)	JBOD	N/A
3	LSI SAS 9300-8i	LSI00345 LSI00344	KIT SGL	PCI Express 3.0 x8	8	Yes	N/A	2 x SFF8643 Mini-SAS HD	1024	Low-profile MD2	6.4 GB/s (Full Duplex)	JBOD	Includes 2 ea, 4 x 1 SAS (with power) to x4 Mini HD cables
4	LSI SAS 9300-4i4e	LSI00349 LSI00348	KIT SGL	PCI Express3.0 x8	8	Yes	1 x SFF8644 Mini-SAS HD	1 x SFF8643 Mini-SAS HD	1024	Low profile MD2	6.4 GB/s (Full Duplex)	JBOD	Includes 1 ea, 4 x 1 SAS (with power) to x4 Mini HD cable
5	LSI SAS 9300-4i	LSI00347 LSI00346	KIT SGL	PCI Express 3.0 x8	4	Yes	N/A	1 x SFF8643 Mini-SAS HD	1024	Low-profile MD2	4.8 GB/s (Full Duplex)	JBOD	Includes 1 ea, 4 x 1 SAS (with power) to x4 Mini HD cable
6Gb/s SATA+SAS HBAs													
6	LSI SAS 9207-8e	LSI00300	SGL	PCI Express 3.0 x8	8	Yes	2 x SFF8088	N/A	1024	Low-profile MD2	4.8 GB/s (Full Duplex)	JBOD	N/A (Active cable supported)
7	LSI SAS 9207-8i	LSI00302 LSI00301	KIT SGL	PCI Express 3.0 x8	8	Yes	N/A	2 x SAS SFF-8087 x4	256	Low-profile MD2	4.8 GB/s (Full Duplex)	JBOD	Two Mini-SAS to Four SAS
8	LSI SAS 9207-4i4e	LSI00304 LSI00303	KIT SGL	PCI Express3.0 x8	8	Yes	1 x SAS SFF-8088 x4	1 x SAS SFF-8087 x4	256	Low-Profile	4.8 GB/s (Full Duplex)	JBOD	One Mini-SAS to Four SAS
9	LSI SAS 9206-16e	LSI00299	SGL	PCI Express 3.0 x8	16	Yes	4 x SFF8644	N/A	1024	Low-profile MD2	6.4 GB/s (Full Duplex)	JBOD	N/A (Active cable supported)
10	LSI SAS 9201-16e	LSI00276	SGL	PCI Express 2.0 x8	16	Yes	4 x SAS SFF-8088 x4	N/A	1024	Full-Height	4.8 GB/s (Full Duplex)	JBOD	N/A (Active cable supported)
11	LSI SAS 9205-8e	LSI00285	SGL	PCI Express 2.0 x8	8	Yes	2 x SFF8088	N/A	1024	Low-profile MD2	4.8 GB/s (Full Duplex)	JBOD	N/A
12	LSI SAS 9200-8e	LSI00188	SGL	PCI Express 2.0 x8	8	Yes	2 x SAS SFF-8088 x4	N/A	512	Low-profile MD2	4.8 GB/s (Full Duplex)	JBOD	N/A
13	LSI SAS 9212-4i4e	LSI00193 LSI00192	KIT SGL	PCI Express2.0 x8	8	Yes Yes	1 x SAS SFF-8088 x4	4 x SATA x1	256	Low-Profile	4.8 GB/s (Full Duplex)	0, 1, 1E, 10, JBOD	(1) 4 x1 SATA connectors to x 4 SAS
14	LSI SAS 9201-16i	LSI00244	SGL	PCI Express x8	8	Yes	N/A	4 x SAS SFF-8087 x4	512	Full-Height, half-length	4.8 GB/s (Full Duplex)	JBOD	N/A
15	LSI SAS 9211-8i	LSI00195 LSI00194	KIT SGL	PCI Express 2.0 x8	8	Yes	N/A	2 x SAS SFF-8087 x4	256	Low-profile MD2	4.8 GB/s (Full Duplex)	0, 1, 1E, 10, JBOD	Two Mini-SAS to Four SAS
16	LSI SAS 9211-4i	LSI00191 LSI00190	KIT SGL	PCI Express 2.0 x8	4	Yes	N/A	1 x SAS SFF-8087 x4	256	Low-profile MD2	2.4 GB/s (Full Duplex)	0, 1, 1E, 10, JBOD	One Mini-SAS to Four SAS

Cables

Row	Cable P/N	Cable Name	Length	Connector to Connector		Compatible Controllers
				To Controller	To Drives/Backplane	
1	CBL-SAS80870CF-06M	CBL-SAS80870CF-06M	0.6m	SFF-8087	SFF-8482	9750 (-4i, -8i, -4i4e, -24i4e), 9240 (-4i, -8i), 9260 (-4i, -8i, -16i), 9261-8i, 9265-8i, 9266 (-4i, -8i), 9270-8i, 9271 (-4i, -8i, -8iCC), 9280 (-4i4e, -24i4e), 9201-16i, 9211 (-4i, -8i), 9212-4i4e
2	CBL-SFF8087-05M	CBL-SFF8087-05M	0.5m	SFF-8087	SFF-8087	9750 (-4i, -8i, -4i4e, -24i4e), 9240 (-4i, -8i), 9260 (-4i, -8i, -16i), 9261-8i, 9265-8i, 9266 (-4i, -8i), 9270-8i, 9271 (-4i, -8i, -8iCC), 9280 (-4i4e, -24i4e), 9201-16i, 9211 (-4i, -8i), 9212-4i4e
3	CBL-SFF8087-06M	CBL-SFF8087-06M	0.6m	SFF-8087	SFF-8087	9750 (-4i, -8i, -4i4e, -24i4e), 9240 (-4i, -8i), 9260 (-4i, -8i, -16i), 9261-8i, 9265-8i, 9266 (-4i, -8i), 9270-8i, 9271 (-4i, -8i, -8iCC), 9280 (-4i4e, -24i4e), 9201-16i, 9211 (-4i, -8i), 9212-4i4e
4	CBL-SFF80870CF-05M	CBL-SFF80870CF-05M	0.5m	SFF-8087	SFF-8087	9750 (-4i, -8i, -4i4e, -24i4e), 9240 (-4i, -8i), 9260 (-4i, -8i, -16i), 9261-8i, 9265-8i, 9266 (-4i, -8i), 9270-8i, 9271 (-4i, -8i, -8iCC), 9280 (-4i4e, -24i4e), 9201-16i, 9211 (-4i, -8i), 9212-4i4e
5	CBL-SFF80870CF-06M	CBL-SFF80870CF-06M	0.6m	SFF-8087	Discrete	9750 (-4i, -8i, -4i4e, -24i4e), 9240 (-4i, -8i), 9260 (-4i, -8i, -16i), 9261-8i, 9265-8i, 9266 (-4i, -8i), 9270-8i, 9271 (-4i, -8i, -8iCC), 9280 (-4i4e, -24i4e), 9201-16i, 9211 (-4i, -8i), 9212-4i4e
6	CBL-SFF80870CF-10M	CBL-SFF80870CF-10M	1.0m	SFF-8087	Discrete	9750 (-4i, -8i, -4i4e, -24i4e), 9240 (-4i, -8i), 9260 (-4i, -8i, -16i), 9261-8i, 9265-8i, 9266 (-4i, -8i), 9270-8i, 9271 (-4i, -8i, -8iCC), 9280 (-4i4e, -24i4e), 9201-16i, 9211 (-4i, -8i), 9212-4i4e
7	CBL-SFF8088SAS-10M	CBL-SFF8088SAS-10M	1.0m	SFF-8088	SFF-8088	9750 (-8e, -4i4e, -16i4e, -24i4e), 9280 (-8e, -4i4e, -16i4e, -24i4e), 9285-8e, 9286 (-8e, CV-8e, CV-8eCC), 9200-8e, 9201-16e, 9212-4i4e
8	CBL-SFF8088SAS-20M	CBL-SFF8088SAS-20M	2.0m	SFF-8088	SFF-8088	9750 (-8e, -4i4e, -16i4e, -24i4e), 9280 (-8e, -4i4e, -16i4e, -24i4e), 9285-8e, 9286 (-8e, CV-8e, CV-8eCC), 9200-8e, 9201-16e, 9212-4i4e
9	LSIO0249	CBL-SFF80875B-08M	0.8m	SFF-8087	SFF-8087	9750 (-4i, -8i, -4i4e, -24i4e), 9240 (-4i, -8i), 9260 (-4i, -8i, -16i), 9261-8i, 9265-8i, 9266 (-4i, -8i), 9270-8i, 9271 (-4i, -8i, -8iCC), 9280 (-4i4e, -24i4e), 9201-16i, 9211 (-4i, -8i), 9212-4i4e
10	LSIO0255	CBL-SFF80875B-05M	0.5m	SFF-8087	SFF-8087	9750 (-4i, -8i, -4i4e, -24i4e), 9240 (-4i, -8i), 9260 (-4i, -8i, -16i), 9261-8i, 9265-8i, 9266 (-4i, -8i), 9270-8i, 9271 (-4i, -8i, -8iCC), 9280 (-4i4e, -24i4e), 9201-16i, 9211 (-4i, -8i), 9212-4i4e
11	LSIO0256	CBL-SFF80875B-06M	0.6m	SFF-8087	SFF-8087	9750 (-4i, -8i, -4i4e, -24i4e), 9240 (-4i, -8i), 9260 (-4i, -8i, -16i), 9261-8i, 9265-8i, 9266 (-4i, -8i), 9270-8i, 9271 (-4i, -8i, -8iCC), 9280 (-4i4e, -24i4e), 9201-16i, 9211 (-4i, -8i), 9212-4i4e
12	LSIO0258	CBL-SFF8087-SATASB-10M	1.0m	SFF-8087	x4 SATA	9750 (-4i, 8i, -8e, -4i4e, -16i4e, -24i4e)
13	LSIO0259	CBL-SFF8087-SATASB-06M	0.6m	SFF-8087	x4 SATA	9750 (-4i, 8i, -8e, -4i4e, -16i4e, -24i4e)
14	LSIO0271	CBL-SFF8088ASAS-100M	10.0m	SFF-8088*	SFF-8088*	9201-16e, 9207-8e, SAS6160 SAS Switch
15	LSIO0272	CBL-SFF8088ASAS-200M	20.0m	SFF-8088*	SFF-8088*	9201-16e, 9207-8e, SAS6160 SAS Switch
16	LSIO0274	CBL-RA8087SATASB-10M	1.0m	SFF-8087	x4 SATA	9750 (-16i4e, -24i4e), 9280 (-16i4e, -24i4e)
17	LSIO0275	CBL-RA80875B-10M	1.0m	SFF-8087	SFF-8087	9750 (-16i4e, -24i4e), 9280 (-16i4e, -24i4e)
18	LSIO0312	CBL-RA8087-08M	0.8m	SFF-8087	SFF-8087	9750 (-16i4e, -24i4e)
19	LSIO0313	CBL-RA8087-10M	1.0m	SFF-8087	SFF-8087	9750 (-16i4e, -24i4e)
20	LSIO0314	CBL-SFF8087-10M	1.0m	SFF-8087	SFF-8087	9690SA (-4i, -8i, -4i4e), 9750 (-4i, -8i, -4i4e, -24i4e)
21	LSIO0336	CBL-SFF8644-8088-10M	1.0m	SFF8644	SFF8088	9206-16e, 9300-8e, 9300-4i4e
22	LSIO0337	CBL-SFF8644-8088-20M	2.0m	SFF8644	SFF8088	9206-16e, 9300-8e, 9300-4i4e
23	LSIO0338	CBL-SFF8644-8088-60M	6.0m	SFF8644	SFF8088	9206-16e, 9300-8e, 9300-4i4e
24	LSIO0339	CBL-SFF8644-10M	1.0m	SFF8644	SFF8644	9206-16e, 9300-8e, 9300-4i4e
25	LSIO0340	CBL-SFF8644-20M	2.0m	SFF8644	SFF8644	9206-16e, 9300-8e, 9300-4i4e
26	LSIO0341	CBL-SFF8644-60M	6.0m	SFF8644	SFF8644	9206-16e, 9300-8e, 9300-4i4e
27	LSIO0400	CBL-SFF8643-8087-06M	0.6m	SFF8643	SFF8087	9300-4i, 9300-8i, 9300-4i4e, 9361-4i, 9361-8i, 9341-4i, 9341-8i
28	LSIO0401	CBL-SFF8643-8087-08M	0.8m	SFF8643	SFF8087	9300-4i, 9300-8i, 9300-4i4e, 9361-4i, 9361-8i, 9341-4i, 9341-8i
29	LSIO0402	CBL-SFF8643-8087-10M	1.0m	SFF8643	SFF8087	9300-4i, 9300-8i, 9300-4i4e, 9361-4i, 9361-8i, 9341-4i, 9341-8i
30	LSIO0403	CBL-SFF8643-06M	0.6m	SFF8643	SFF8643	9300-4i, 9300-8i, 9300-4i4e, 9361-4i, 9361-8i, 9341-4i, 9341-8i
31	LSIO0404	CBL-SFF8643-08M	0.8m	SFF8643	SFF8643	9300-4i, 9300-8i, 9300-4i4e, 9361-4i, 9361-8i, 9341-4i, 9341-8i
32	LSIO0405	CBL-SFF8643-10M	1.0m	SFF8643	SFF8643	9300-4i, 9300-8i, 9300-4i4e, 9361-4i, 9361-8i, 9341-4i, 9341-8i
33	LSIO0409	CBL-SFF8643-SATASB-05M	0.5m	SFF8643	x4 SATA	9300-4i, 9300-8i, 9300-4i4e, 9361-4i, 9361-8i, 9341-4i, 9341-8i
34	LSIO0410	CBL-SFF8643-SATASB-06M	0.6m	SFF8643	x4 SATA	9300-4i, 9300-8i, 9300-4i4e, 9361-4i, 9361-8i, 9341-4i, 9341-8i
35	LSIO0411	CBL-SFF8643-SATASB-10M	1.0m	SFF8643	x4 SATA	9300-4i, 9300-8i, 9300-4i4e, 9361-4i, 9361-8i, 9341-4i, 9341-8i
36	LSIO0412	CBL-SFF8643-SAS84825B-06M	0.6m	SFF8643	SFF8482	9300-4i, 9300-8i, 9300-4i4e, 9361-4i, 9361-8i, 9341-4i, 9341-8i
37	LSIO0413	CBL-RA8643-04M	0.4m	SFF8643	SFF8643	9300-4i, 9300-8i, 9300-4i4e, 9361-4i, 9361-8i, 9341-4i, 9341-8i

* keyed for "Active Cable" support

Cache Protection Options

Row	Product Name	Ordering P/N	Description / Compatible Controllers
1	LSICVM02	LSI00418	CacheVault Module for 9361 Series
2	LSICVM01	LSI00297	CacheVault Module for 9266 and 9271 Series
3	LSiIBBU09	LSI00279	Battery Backup Unit for 9265, 9266, 9270, 9271, 9285 and 9286 Series
4	LSiIBBU08	LSI00264	Battery Backup Unit for 9260/1-xx, 9280-xx
5	LSiIBBU07	LSI00161	Battery Backup Unit for 8880EM2, 9260/1-xx, 9280-xx and 9750-xx
6	LSiIBBU06	LSI00160	Battery Backup Unit for 8708EM2 and 8704EM2
7	LSiIBBU05	LSI00183	Battery Backup Unit for 8708ELP, 8704ELP and 8888ELP
8	BBU-BRACKET-05	LSI00291	Remote Mounting Bracket for LSiIBBU06/07/08/09 and CacheVault Power Modules
9	Remote Cable/Interposer Kit	LSI00260	Needed ONLY if require remote cable for LSiIBBU06/07 OR connecting LSiIBBU07/08 remotely to 9260-4i or 9260-8i

Advanced Software Options

Row	Advanced Software Option	Enablement	Ordering Part No.	Compatible Controllers
1	MegaRAID CacheCade Pro 2.0 Software Pack	Hardware Key	LSI00292	With LSI00292: 9260 (-4i, -8i, -16i), 9280 (-4i4e, -16i4e, -24i4e) With LSI00290: 9265-8i, 9266 (-4i, -8i), 9270-8i, 9271 (-4i, -8i, -8iCC), 9285 (-8e, CV-8e), 9286 (-8e, CV-8e, CV-8eCC), 9361 (-4i, -8i)
2	MegaRAID CacheCade Pro 2.0 Software Pack	Electronic License	LSI00293	With LSI00293: MR SAS 9260/9261/9265/9266/9270/9271/9280/9285/9286/9361 series
3	MegaRAID SafeStore Software	Hardware Key	LSI00245 LSI00287	With LSI00245: 9260 (-4i, -8i, -16i), 9280 (-4i4e, -16i4e, -24i4e) With LSI00287: 9265-8i, 9266 (-4i, -8i), 9270-8i, 9271 (-4i, -8i, -8iCC), 9285 (-8e, CV-8e), 9286 (-8e, CV-8e, CV-8eCC), 9361 (-4i, -8i)
4	MegaRAID SafeStore Software	Electronic License	LSI00268	With LSI00268: 9260/9261/9265/9266/9270/9271/9280/9285/9286/9361 series
5	MegaRAID Recovery Software	Hardware Key	LSI00246 LSI00288	With LSI00246: 9260 (-4i, -8i, -16i), 9280 (-4i4e, -16i4e, -24i4e) With LSI00288: 9265-8i, 9266 (-4i, -8i), 9270-8i, 9271 (-4i, -8i, -8iCC), 9285 (-8e, CV-8e), 9286 (-8e, CV-8e, CV-8eCC)
6	MegaRAID Recovery Software	Electronic License	LSI00267	With LSI00267: 9260/9261/9265/9266/9270/9271/9280/9285/9286 series
7	MegaRAID Fast Path Software*	Hardware Key	LSI00247	With LSI00247: 9260 (-4i, -8i, -16i), 9280 (-4i4e, -16i4e, -24i4e)
8	MegaRAID Fast Path Software*	Electronic License	LSI00266	With LSI00266: 9260 and 9280 Series

* With MegaRAID Release 5.7 firmware or later, LSI FastPath software is now included as a standard feature on the following 6Gb/s MegaRAID SAS controller cards based on the LSI SAS 2208 ROC: 9265/9266/9270/9271/9285/9286 Series Controllers. It is also included as a standard feature on all 12Gb/s MegaRAID controllers

Committed to fulfilling all of your storage needs, LSI provides you with tools and resources to support you and your customers.



Where to Buy

www.lsi.com/channel/wheretobuy



Support Contacts

(800) 633-4545 or 00-800-5745-6442
www.lsi.com/support



Sales Contacts

North American Headquarters

San Jose, CA
T: +1.866.574.5741 (within U.S.)
T: +1.610.712.4323 (outside U.S.)

LSI Europe Ltd. European Headquarters

United Kingdom
T: [+44] 1344.413200

LSI KK Headquarters

Tokyo, Japan
T: [+81] 3.5463.7811



Become a Reseller Partner

www.lsi.com/resellerprogram



Storage. Networking. Accelerated.™

For more information and sales office locations, please visit the LSI website at: www.lsi.com

LSI, LSI and Design logo, 3ware, MegaRAID, MegaRAID Management Suite, MegaRAID Storage Manager, SafeStore, 3DM2, StorSwitch, FusionMPT, StreamFusion+ and Multi-lane are trademarks or registered trademarks of LSI Corporation. All other brand and product names may be trademarks of their respective companies.

LSI Corporation reserves the right to make changes to any products and services herein at any time without notice. LSI does not assume any responsibility or liability arising out of the application or use of any product or service described herein, except as expressly agreed to in writing by LSI; nor does the purchase, lease, or use of a product or service from LSI convey a license under any patent rights, copyrights, trademark rights, or any other of the intellectual property rights of LSI or of third parties.

Copyright ©2013 by LSI Corporation. All rights reserved. > 1113

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [D-Sub Micro-D Connectors](#) category:

Click to view products by [LSI manufacturer](#):

Other Similar products are found below :

[M243082311F](#) [M2430834F](#) [M24308/4-6F](#) [65-1920-15](#) [M83513/01-HN](#) [M83513/03-A10N](#) [M83513/03-B14C](#) [M83513/03-D09C](#) [M83513/03-D11N](#) [M83513/03-G02N](#) [M83513/03-G05N](#) [M83513/03-G08C](#) [M83513/03-G09N](#) [M83513/03-G12N](#) [M83513/03-H13N](#) [M83513/04-E15N](#) [M83513/04-G04C](#) [M83513/10-E01NP](#) [M83513/13-B01NP](#) [M83513/13-C01NN](#) [M83513/16-A01CP](#) [M83513/22-D01NP](#) [M83513/25-B01NP](#) [6R2004A30F015](#) [6R4006A28A120](#) [703006A13F060](#) [704002A03F200](#) [705001A13F120](#) [7-1532020-5](#) [748567-1-P](#) [MDB1-31SH003](#) [MDM-15PBS-L58](#) [MDM-15PCBRM7T](#) [MDM-15PH003B-A174](#) [75-068624-59S](#) [MDM-15PH034B](#) [MDM-15SH001L](#) [MDM-15SH004B](#) [MDM-21PH003K](#) [MDM-25PH003B-A174](#) [MDM-25PHW01F-A174](#) [MDM-37PH006L-A174](#) [MDM-37PH048M5-A174](#) [MDM-37SCBRP-A174](#) [MDM-51PBS-L56](#) [MDM-51PSF](#) [MDM-51SH003M7](#) [MDM-51SSM7-A174](#) [MDM-9PBSP-L58](#) [MDM-9PH003M7](#)