

## **Switchmode/High Frequency** Common Mode Inductors

# ET2835-035

### **Description:**

Common-mode coils are useful in a wide range of applications for the prevention of electromagnetic interference (EMI) and radio frequency interference (RFI) from power supply lines and for prevention of malfunctioning of various electronic equipments. Features include low leakage flux, high self-resonant frequency, high impedance at applicable frequency and low stray capacitance in section winding. Designed to meet UL, CSA and IEC standards.

## **Electrical Specifications (@20°C):**

Min.	Inductance	Max. DC (Ω)	Amps
Inductance*	Difference	Resistance	RMS
(mH)	(µH) Max		
92.00	92.00 2000		0.60

<sup>\*</sup>inductance per winding.

## **Specifications:**

Rated Voltage = 250VAC Temperature Rise = 45°C Max Insulation Resistance =  $100M \Omega Min$ Operating Temperature Range = -20 to 105°C Dielectric Withstanding Voltage = 2,000 VAC


## **Dimensions:**

W	L	Н	Α	В
1.240	.925	1.457	.512	.393


Units in inches.


Weight: .88 oz.


#### **Schematic:**



RoHS Compliance: As of manufacturing date February 2005, all standard products meet the requirements of 2002/95/EC, known as the RoHS initiative.







Web: www.TriadMagnetics.com Phone 951-277-0757 Fax 951-277-2757

22520B Temescal Canyon Road Corona, California 92883

Publish Date: July 12, 2006

<sup>\*</sup> Upon printing, this document is considered "uncontrolled". Please contact Triad Magnetics' website for the most current version.