

PRODUCT-DETAILS

HKF1-20

HKF1-20 Auxiliary Contact



General Information

| | |
|-----------------------|---|
| Extended Product Type | HKF1-20 |
| Product ID | 1SAM201901R1002 |
| EAN | 4013614480614 |
| Catalog Description | HKF1-20 Auxiliary Contact |
| Long Description | Auxiliary contacts HKF1 with screw terminals change position with the main contacts of the manual motor starter. They are mounted on the front side of manual motor starters MS116, MS132 or MS165. Auxiliary contacts HKF1 are available as normally open or normally closed contacts. |

Ordering

| | |
|------------------------|----------|
| Minimum Order Quantity | 1 piece |
| Customs Tariff Number | 85365080 |

Popular Downloads

| | |
|-----------------------------------|--|
| Data Sheet, Technical Information | 1SBC100214C0202 |
| Instructions and Manuals | 2CDC131011M6802 2CDC131034M6801 2CDC131022M6802 2CDC131120M6801 2CDC131081M6801 2CDC131082M6801 |
| Instructions and Manuals (Part 3) | 1SBC100214C0202 |

CAD Dimensional
Drawing

2CDC001079B0201

Dimensions

| | |
|-------------------------------|----------|
| Product Net Width | 45 mm |
| Product Net Height | 12.5 mm |
| Product Net Depth / Length | 26.5 mm |
| Product Net Weight | 0.015 kg |

Technical

| | |
|---|--|
| Terminal Type | Screw Terminals |
| Rated Operational Voltage | 250 V |
| Rated Operational Current AC-15 (I_{θ}) | (24 V) 3 A (120 V) 3 A (240 V) 1.5 A |
| Rated Operational Current DC-13 (I_{θ}) | (24 V) 1 A (125 V) 0.27 A (250 V) 0.11 A |
| Rated Frequency (f) | Auxiliary Circuit DC Auxiliary Circuit 50 Hz Auxiliary Circuit 60 Hz |
| Rated Impulse Withstand Voltage (U_{imp}) | Auxiliary Circuit 6 kV |
| Rated Insulation Voltage (U_i) | 250 V |
| Degree of Protection | IP20 |
| Electrical Durability | 100000 cycle |
| Mechanical Durability | 100000 cycle |
| Connecting Capacity Auxiliary Circuit | Flexible with Ferrule 1/2x 0.75 ... 1.5 mm ² Flexible with Insulated Ferrule 1/2x 0.75 ... 1.5 mm ² Flexible 1/2x 0.75 ... 1.5 mm ² Rigid 1/2x 1.0 ... 2.5 mm ² |
| Tightening Torque | Auxiliary Circuit 0.8 ... 1.2 N·m |
| Wire Stripping Length | Auxiliary Circuit 8 mm |
| Recommended Screw Driver | M3 Pozidriv 2 |
| Number of Auxiliary Contacts NO | 2 |
| Number of Auxiliary Contacts NC | 0 |
| Standards | CSA 22.2 No. 14 IEC/EN 60947-1 IEC/EN 60947-5-1 UL 508 UL 60947-1 UL 60947-5-1 |
| Product Name | Auxiliary Contact |
| Suitable For | MS116 MS132 MO132 MS165 MO165 |
| Suitable for Product Class | Manual Motor Starter |
| Accessory Group | Electrical |
| Accessory Type | Auxiliary Contact |

Technical UL/CSA

| | |
|---|--|
| Maximum Operating Voltage UL/CSA | Main Circuit 250 V AC |
| Connecting Capacity Auxiliary Circuit UL/CSA | Flexible 1/2x 16-14 AWG Stranded 1/2x 16-14 AWG |

| | |
|-----------------------------|---------------------------|
| Tightening Torque UL/CSA | Auxiliary Circuit 7 in-Ib |
| Contact Rating UL/CSA | B300 R300 |

Environmental

| | |
|---|--|
| Ambient Air Temperature | Operation -25 ... +60 °C Storage -50 ... +80 °C |
| Resistance to Shock acc. to IEC 60068-2-27 | 11 ms Pulse 25g |
| Resistance to Vibrations acc. to IEC 60068-2-6 | 5g / 3 ... 150 Hz |
| RoHS Status | Following EU Directive 2011/65/EU and Amendment 2015/863 July 22, 2019 |

Certificates and Declarations

| | |
|-------------------------------------|--|
| ABS Certificate | 1SAA963001-0101 |
| BV Certificate | 1SAA963000-0202 |
| CB Certificate | 1SAA963003-2002 |
| CQC Certificate | CQC2017010304032779 |
| cUL Certificate | cUL E137861 |
| Declaration of Conformity - CCC | 2020980304001251 |
| Declaration of Conformity - CE | 1SAD101100-3410 |
| Declaration of Conformity - UKCA | 1SAD201100-3410 |
| DNV Certificate | 1SAA963001-0302 |
| GL Certificate | 1SAA963001-0401 1SAA963000-0402 |
| LR Certificate | 1SAA963001-0501 1SAA963001-0502 1SAA963000-0505 1SAA918001-0501 |
| RINA Certificate | 1SAA963002-0802 |
| UL Certificate | UL E137861 |

Container Information

| | |
|-----------------------------------|---------------|
| Package Level 1 Width | 148 mm |
| Package Level 1 Depth / Length | 36 mm |
| Package Level 1 Height | 50 mm |
| Package Level 1 Gross Weight | 0.195 kg |
| Package Level 1 EAN | 4013614481420 |
| Package Level 1 Units | box 10 piece |
| Package Level 2 Width | 280 mm |
| Package Level 2 Depth / Length | 395 mm |
| Package Level 2 Height | 210 mm |
| Package Level 2 Gross Weight | 10.125 kg |
| Package Level 2 EAN | 4013614522734 |
| Package Level 2 Units | 500 piece |

Classifications

| | |
|----------------------------|--|
| Object Classification Code | Q |
| ETIM 4 | EC002498 - Accessories for low-voltage switch technology |
| ETIM 5 | EC000041 - Auxiliary contact block |

| | |
|---------------------------------------|------------------------------------|
| ETIM 6 | EC000041 - Auxiliary contact block |
| ETIM 7 | EC000041 - Auxiliary contact block |
| ETIM 8 | EC000041 - Auxiliary contact block |
| eClass | V11.0 : 27371302 |
| UNSPSC | 39121522 |
| IDEA Granular Category Code (IGCC) | 4743 >> Auxiliary contact block |
| E-Number (Finland) | 3705898 |

Categories

Low Voltage Products and Systems → Control Products → Manual Motor Starters → Manual Motor Starters Accessories



X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Circuit Breaker Accessories](#) category:

Click to view products by [ABB](#) manufacturer:

Other Similar products are found below :

[CSC-403PS](#) [D11CEU1](#) [8T1-E-125](#) [CAP-16-3P-BK-PB](#) [8C1-C-721](#) [8T1-E-275](#) [8T1-E-278](#) [A01ED62](#) [FAS-001](#) [FBS0054](#) [506-11315-001](#)
[3803221](#) [6720005316](#) [9-1393249-0](#) [802-ESB50UL489](#) [30.329](#) [X22261102](#) [CX2.5/4/O](#) [JX2.5/4](#) [JX2.5/5](#) [HSP6/10U](#) [DB16/BU](#) [932146100](#)
[930120000](#) [601.1231.909](#) [600.6101.036](#) [3PRG1](#) [3PLBR4LU](#) [3803241](#) [351.5900.149](#) [2624.0](#) [17BSSV](#) [1-1423696-8](#) [X20080104](#) [LS3-WH](#)
[Y30028402](#) [30.617](#) [DKR2](#) [8T1-E-114](#) [SF06-5,08](#) [PLLA3](#) [G32S22](#) [2LP199](#) [ZG20-2](#) [3PSML401](#) [3PSML402](#) [930122000](#) [PAM-1](#)
[930136101](#) [CMB4/W](#)