

Digital Modules

ND-6050

Digital I/O Module



Digital Input

- Channels: 7
- Switching Level: TTL
- Internal Pull-Up Resistor: 10 k Ω
- Maximum Current: 0.5 mA
- Programmable input polarity

Digital Output

- Channels: 8
- Maximum Current Sink: 50 mA
- Maximum Power Dissipation: 300 mW
- Programmable output polarity
- Programmable power on/safety state

Power

- Requirement: unregulated +10 V to +30 Vdc
- Power Consumption: 0.336 W typical

ND-6052

8-CH Isolated Digital Input Module



Digital Input

- Channels: 8
 - 6 independent isolated channels
 - 2 isolated channels with common ground

Switching Levels

- Low (0): +1 V (max.)
- High (1): +3.5 V to +24 V

- Internal Current Limit Resistor: 1.2 k Ω

- Isolated Voltage: 5,000 VRMS

- Programmable input polarity

Power

- Requirement: unregulated +10 V to +30 Vdc
- Power Consumption: 0.264 W

ND-6053

16-CH Digital Input Module



Digital Input

- Channels: 16
- Dry Contact
 - Logical level 0: close to GND
 - Logical level 1: open
 - Effective distance: 500 m (max)
- TTL Contact

- Internal Pull-Up Resistor: 10 k Ω

- Programmable input polarity

Power

- Requirement: unregulated +10 V to +30 Vdc
- Power Consumption: 0.408 W typical

ND-6054

15-CH Isolated Digital Input Module



Digital Input

- Channels: 15-bit digital input with 24 V external common power

Switching Level:

- Low (0): +1 V (max.)
- High (1): +3.5 V to +24 V

- Internal Pull-Up Resistor: 1.2 k Ω

- Isolated Voltage: 5,000 VRMS

- Programmable input polarity

Power

- Requirement: unregulated +10 V to +30 Vdc
- Power Consumption: 0.216 W typical

ND-6056

15-CH Isolated Digital Output Module



Digital Output

- Channels: 15-bit digital open collector output with common ground

- Maximum Load Current: 300 mA

- Isolated Voltage: 3,750 VRMS

- Programmable input polarity

Power

- Requirement: unregulated +10 V to +30 Vdc

- Power Consumption: 1.32 W

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Data Logging & Acquisition category](#):

Click to view products by [ADLINK Technology manufacturer](#):

Other Similar products are found below :

[PCI-6208A](#) [DAQe-2502](#) [PXI-2208](#) [ACL-8112DG](#) [SpotBotBLE](#) [LPCI-7230](#) [USB-4761-BE](#) [SE028](#) [PCI-1761-BE](#) [AR207/8/S1/PPPP/IP65](#)
[PCI-1711UL-CE](#) [USB-4702-AE](#) [USB-4704-AE](#) [USB-4716-AE](#) [USB-4750-BE](#) [USB-4751-AE](#) [PCI-1714U-BE](#) [PCIE-1810-AE](#) [PCI-1713U-](#)
[BE](#) [PCI-1710U-DE](#) [PCI-1710HGU-DE](#) [AR207/8/S1/PPPP/IP30](#) [U2781A](#) [4610](#) [EL-USB-5](#) [AR407/S1/P/P/P/P](#) [AR207/8/S2/PPPP/IP30](#)
[ACL-8112PG](#) [cPCI-7248](#) [cPCI-7433](#) [DAQ-2213](#) [ND-6053](#) [ND-6060](#) [PCI-7230](#) [PCI-7432](#) [PCI-9111DG](#) [PCI-9112](#) [PCI-9112A](#) [PCI-9113A](#)
[PCI-9221](#) [PCM-7248+](#) [USB-1903](#) [USB-2401](#) [PCIE-1813-AE](#) [PCIE-1816-AE](#) [PCIE-1816H-AE](#) [PCIE-1884-AE](#) [USB-5856-AE](#) [USB-5862-](#)
[AE](#) [AR654/S2/P/P/P/P/IP30](#)