

NPN SILICON RF POWER TRANSISTOR

DESCRIPTION:

The **ASI 2N5643** is Designed for wideband large-signal amplifier stages in the 125 – 175 MHz range.

FEATURES:

- Minimum Gain = 7.6 dB
- Output Power = 40 W
- **Omnigold™** Metalization System

MAXIMUM RATINGS

I_C	5.0 A
V_{CB0}	65 V
V_{CEO}	35 V
V_{EBO}	4.0 V
P_{DISS}	60 W @ T _C = 25 °C
T_J	-65 °C to +200 °C
T_{STG}	-65 °C to +200 °C
θ_{JC}	2.9 °C/W

PACKAGE STYLE .380 4L STUD

DIM	MINIMUM inches / mm	MAXIMUM inches / mm
A	.220 / 5.59	.230 / 5.84
B	.980 / 24.89	
C	.370 / 9.40	.385 / 9.78
D	.004 / 0.10	.007 / 0.18
E	.320 / 8.13	.330 / 8.38
F	.100 / 2.54	.130 / 3.30
G	.450 / 11.43	.490 / 12.45
H	.090 / 2.29	.100 / 2.54
I	.155 / 3.94	.175 / 4.45
J		.750 / 19.05

CHARACTERISTICS T_C = 25 °C

SYMBOL	TEST CONDITIONS			MINIMUM	TYPICAL	MAXIMUM	UNITS
BV_{CEO}	I _C = 200 mA			35			V
BV_{CES}	I _C = 200 mA			65			V
BV_{EBO}	I _E = 10 mA			4.0			V
I_{CB0}	V _{CB} = 30 V					1.0	mA
h_{FE}	V _{CE} = 5.0 V	I _C = 500 mA		5.0		---	---
C_{OB}	V _{CB} = 30 V	f = 1.0 MHz			45	65	pF
G_P	V _{CE} = 28 V	P _{OUT} = 40 W	f = 175 MHz	7.6	8.1	---	dB
η_C	V _{CE} = 10 V	I _C = 200 mA	f = 100 MHz		60		%

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [RF Bipolar Transistors](#) category:

Click to view products by [Advanced Semiconductor](#) manufacturer:

Other Similar products are found below :

[MAPRST0912-50](#) [MCH4016-TL-H](#) [MMBT5551-G](#) [MRF10120](#) [15GN01CA-TB-E](#) [PH1214-25M](#) [MAPRST0912-350](#) [MMBTH10-TP](#) [BFP640F H6327](#) [BFP 720F H6327](#) [BFP 740F H6327](#) [BFR 360F H6765](#) [MRF10031](#) [NSVF4009SG4T1G](#) [BFP 182R E7764](#)
[BFP405H6740XTSA1](#) [MRF10350](#) [BFR360FH6765XTSA1](#) [BFP410H6327XTSA1](#) [BFP620FH7764XTSA1](#) [BFP720ESDH6327XTSA1](#)
[BFP720FH6327XTSA1](#) [BFR360L3E6765XTMA1](#) [BFP420H6433XTMA1](#) [BFP420H6740XTSA1](#) [BFP420H6801XTSA1](#) [MCH4015-TL-H](#)
[BF888H6327XTSA1](#) [MMBT2222A-G](#) [BFP196WH6327XTSA1](#) [BFP405FH6327XTSA1](#) [BFP640ESDH6327XTSA1](#)
[BFR193L3E6327XTMA1](#) [BFS483H6327XTSA1](#) [NSVF4020SG4T1G](#) [NSVF6003SB6T1G](#) [MRF10005](#) [BFP420FH6327XTSA1](#)
[BFP740FESDH6327XTSA1](#) [BFR181E6327HTSA1](#) [BFR181WH6327XTSA1](#) [BFR182E6327HTSA1](#) [BFR193E6327HTSA1](#)
[BFP181E7764HTSA1](#) [BFP183WH6327XTSA1](#) [BFP720H6327XTSA1](#) [BFR182WH6327XTSA1](#) [BFU590GX](#) [MAPR-000912-500S00](#)
[BFR340FH6327XTSA1](#)