

NPN SILICON RF POWER TRANSISTOR

DESCRIPTION:

The **ASI MRF1000MB** is Designed for Class A, DME/TACAN Applications up to 1090 MHz.

FEATURES:

- Class A Operation
- $P_G = 10$ dB at 0.2 W/1090 MHz
- **Omnigold™** Metalization System

MAXIMUM RATINGS

I_C	200 mA
V_{CE}	20 V
P_{DISS}	7.0 W
T_J	-65 °C to +200 °C
T_{STG}	-65 °C to +150 °C
θ_{JC}	25.0 °C/W

PACKAGE STYLE .280 4L PILL

DIM	MINIMUM inches / mm	MAXIMUM inches / mm
A	.220 / 5.59	.230 / 5.84
B		1.055 / 26.80
C	.275 / 6.99	.285 / 7.24
D	.004 / 0.10	.006 / 0.15
E	.050 / 1.27	.060 / 1.52
F	.118 / 3.00	.130 / 3.30

CHARACTERISTICS $T_C = 25$ °C

SYMBOL	TEST CONDITIONS	MINIMUM	TYPICAL	MAXIMUM	UNITS
BV_{CBO}	$I_C = 1.0$ mA	50			V
BV_{CEO}	$I_C = 5.0$ mA	20			V
BV_{EBO}	$I_E = 1.0$ mA	3.5			V
I_{CES}	$V_{CE} = 28$ V			1.0	mA
h_{FE}	$V_{CE} = 5.0$ V $I_C = 100$ mA	15		120	---
P_G	$V_{CC} = 18$ V $P_{OUT} = 0.2$ W $f = 1090$ MHz	10			dB

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [RF Bipolar Transistors](#) *category:*

Click to view products by [Advanced Semiconductor](#) *manufacturer:*

Other Similar products are found below :

[MAPRST0912-50](#) [MCH4016-TL-H](#) [MMBT5551-G](#) [MRF10120](#) [15GN01CA-TB-E](#) [PH1214-25M](#) [MAPRST0912-350](#) [MMBTH10-TP](#) [BFP640F H6327](#) [BFP 720F H6327](#) [BFP 740F H6327](#) [BFR 360F H6765](#) [MRF10031](#) [NSVF4009SG4T1G](#) [BFP 182R E7764](#) [BFP405H6740XTSA1](#) [MRF10350](#) [BFR360FH6765XTSA1](#) [BFP410H6327XTSA1](#) [BFP620FH7764XTSA1](#) [BFP720ESDH6327XTSA1](#) [BFP720FH6327XTSA1](#) [BFR360L3E6765XTMA1](#) [BFP420H6433XTMA1](#) [BFP420H6740XTSA1](#) [BFP420H6801XTSA1](#) [MCH4015-TL-H](#) [BF888H6327XTSA1](#) [MMBT2222A-G](#) [BFP196WH6327XTSA1](#) [BFP405FH6327XTSA1](#) [BFP640ESDH6327XTSA1](#) [BFR193L3E6327XTMA1](#) [BFS483H6327XTSA1](#) [NSVF4020SG4T1G](#) [NSVF6003SB6T1G](#) [MRF10005](#) [BFP420FH6327XTSA1](#) [BFP740FESDH6327XTSA1](#) [BFR181E6327HTSA1](#) [BFR181WH6327XTSA1](#) [BFR182E6327HTSA1](#) [BFR193E6327HTSA1](#) [BFP181E7764HTSA1](#) [BFP183WH6327XTSA1](#) [BFP720H6327XTSA1](#) [BFR182WH6327XTSA1](#) [BFU590GX](#) [MAPR-000912-500S00](#) [BFR340FH6327XTSA1](#)