

# NPN SILICON RF POWER TRANSISTOR

**DESCRIPTION:**


The **ASI MRF315A** is Designed for Class C Power Amplifier Applications up to 200 MHz.

**FEATURES:**

- $P_G = 9.0$  dB min. at 45 W/ 150 MHz
- Withstands **30:1** Load VSWR
- **Omnigold™** Metalization System

**MAXIMUM RATINGS**

$I_C$	5.0 A
$V_{CB0}$	65 V
$V_{CEO}$	35 V
$V_{EBO}$	4.0 V
$P_{DISS}$	75 W
$T_J$	-65 °C to +200 °C
$T_{STG}$	-65 °C to +150 °C
$\theta_{JC}$	2.3 °C/W

**PACKAGE STYLE .380 4L STUD**


DIM	MINIMUM inches / mm	MAXIMUM inches / mm
A	.220 / 5.59	.230 / 5.84
B	.980 / 24.89	
C	.370 / 9.40	.385 / 9.78
D	.004 / 0.10	.007 / 0.18
E	.320 / 8.13	.330 / 8.38
F	.100 / 2.54	.130 / 3.30
G	.450 / 11.43	.490 / 12.45
H	.090 / 2.29	.100 / 2.54
I	.155 / 3.94	.175 / 4.45
J		.750 / 19.05

**ORDER CODE: ASI10757**
**CHARACTERISTICS**  $T_C = 25$  °C

SYMBOL	TEST CONDITIONS	MINIMUM	TYPICAL	MAXIMUM	UNITS
$BV_{CEO}$	$I_C = 200$ mA	35			V
$BV_{CES}$	$I_C = 200$ mA	65			V
$BV_{CB0}$	$I_C = 10$ mA	65			V
$BV_{EBO}$	$I_E = 10$ mA	4.0			V
$I_{CB0}$	$V_{CB} = 30$ V			4.0	mA
$h_{FE}$	$V_{CE} = 5.0$ V $I_C = 500$ mA	5.0		200	---
$C_{ob}$	$V_{CB} = 30$ V $f = 1.0$ MHz			65	pF
$P_G$	$V_{CE} = 28$ V $P_{OUT} = 45$ W $f = 150$ MHz	9.0	11		dB
$\eta_C$		50	60		%
$\Psi$		30:1 minimum without degradation in output power			

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [RF Bipolar Transistors](#) category:*

*Click to view products by [Advanced Semiconductor](#) manufacturer:*

Other Similar products are found below :

[MAPRST0912-50](#) [MCH4016-TL-H](#) [MMBT5551-G](#) [MRF10120](#) [15GN01CA-TB-E](#) [PH1214-25M](#) [MAPRST0912-350](#) [MMBTH10-TP](#) [BFP640F H6327](#) [BFP 720F H6327](#) [BFP 740F H6327](#) [BFR 360F H6765](#) [MRF10031](#) [NSVF4009SG4T1G](#) [BFP 182R E7764](#) [BFP405H6740XTSA1](#) [MRF10350](#) [BFR360FH6765XTSA1](#) [BFP410H6327XTSA1](#) [BFP620FH7764XTSA1](#) [BFP720ESDH6327XTSA1](#) [BFP720FH6327XTSA1](#) [BFR360L3E6765XTMA1](#) [BFP420H6433XTMA1](#) [BFP420H6740XTSA1](#) [BFP420H6801XTSA1](#) [MCH4015-TL-H](#) [BF888H6327XTSA1](#) [MMBT2222A-G](#) [BFP196WH6327XTSA1](#) [BFP405FH6327XTSA1](#) [BFP640ESDH6327XTSA1](#) [BFR193L3E6327XTMA1](#) [BFS483H6327XTSA1](#) [NSVF4020SG4T1G](#) [NSVF6003SB6T1G](#) [MRF10005](#) [BFP420FH6327XTSA1](#) [BFP740FESDH6327XTSA1](#) [BFR181E6327HTSA1](#) [BFR181WH6327XTSA1](#) [BFR182E6327HTSA1](#) [BFR193E6327HTSA1](#) [BFP181E7764HTSA1](#) [BFP183WH6327XTSA1](#) [BFP720H6327XTSA1](#) [BFR182WH6327XTSA1](#) [BFU590GX](#) [MAPR-000912-500S00](#) [BFR340FH6327XTSA1](#)