

ADAM-5056/D/S

ADAM-5056SO

ADAM-5057S

16-ch Digital Output Module
16-ch Source-type Isolated
Digital Output Module with LED

32-ch Isolated Digital Output Module



Specifications

General

- **Certifications** CE, FCC class A (ADAM-5056S only)
- **Connectors**
 - ADAM-5056/5056D 1 x Plug-in screw terminal (# 14 ~ 22 AWG)
 - ADAM-5056S 1 x Plug-in screw terminal (# 14 ~ 28 AWG)
- **Enclosure** ABS+PC
- **LED Indicators**
 - ADAM-5056D On: output logic level "1"
Off: output logic level "0"
 - ADAM-5056S On: active
Off: inactive
- **Power Consumption** ADAM-5056: 0.53 W (max.)
ADAM-5056D: 0.84 W (max.)
ADAM-5056S: 0.6 W (max.)

Digital Output

- **Channels** 16
- **Digital Output**
 - ADAM-5056/5056D Open collector to 30 V, 100 mA max. load
 - ADAM-5056S Open collector to 40 V, 200 mA max. load (sink)
- **Operating Voltage** ADAM-5056/5056D: 30 V_{max}
- **Power Dissipation** 300 mW for each channel
- **Protection (Only for ADAM-5056S)**
 - Optical Isolation 2500 V_{DC}
 - Overvoltage Protection 70 V_{DC}
 - Power Dissipation 300 mW

Ordering Information

- **ADAM-5056** 16-ch Digital Output Module
- **ADAM-5056D** 16-ch Digital Output Module with LED
- **ADAM-5056S** 16-ch Sink Type Iso. DO Module w/ LED

Specifications

General

- **Certifications** CE, FCC class A
- **Connectors** 1 x Plug-in screw terminal (# 14 ~ 28 AWG)
- **Enclosure** ABS+PC
- **LED Indicator** On: active
Off: inactive
- **Power Consumption** 0.6 W (Max.)
- **Digital Output**
 - **Channels** 16
 - **Digital Output** 10 ~ 35 V_{DC}
 - **Current** 200 mA max. (per channel)
Channel : 1 W max.
 - **Power Dissipation** Total : 2.2 W (8 channels)

Protection

- **Optical Isolation** 2,500 V_{DC}
- **Overvoltage Protection** 70 V_{DC}

Ordering Information

- **ADAM-5056SO** 16-ch Source Type Iso. DO Module w/ LED

Specifications

General

- **Certifications** CE, FCC class A
- **Connectors** 1 x 40 pin (wiring line)
- **Enclosure** ABS+PC
- **LED Indicator** On: active
Off: inactive
- **Power Consumption** 1W (Max.)

Digital Output

- **Channels** 32
- **Digital Output** Must connect with 2 units of ADAM-3920R

Protection

- **Optical Isolation** 2,500 V_{DC}
- **Overvoltage Protection** 70 V_{DC}

Relay Spec. of ADAM-3920R

- **Contact Rating** 10A @ 250 V_{AC}
10A @ 30 V_{DC}
- **Contact Resistance** 100 mΩ
- **Operation Time** 15 ms
- **Relay Type SPST** (Form A)
- **Release Time** 5 ms max
- **Life Expectancy** 1.7 x 10⁶ at related load
- **Insulation Resistance** 1GΩ @ 500 V_{DC}
- **Power Input** +24 V_{DC}
- **Mounting** DIN 35 rail, wall, rack (with mounting kit)

Note: ADAM-5057S must connect with 2 units of ADAM-3920R via PCL-10220

Note: only for ADAM-5550 Series

Ordering Information

- **ADAM-5057S** 32-ch Digital Output Module
- **ADAM-3920R** 20-pin Flat Cable Wiring Relay Board
- **PCL-10220** 40-pin IDC to two 20-pin IDC cable, 1m

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [I/O Modules](#) category:

Click to view products by [Advantech](#) manufacturer:

Other Similar products are found below :

[70L-OAC-L](#) [G21960000700](#) [G34960002700](#) [G88104401](#) [IDC-5B](#) [OACU](#) [C4SWOUT](#) [FC6A-T32K3](#) [SNAP-OAC5MA](#) [FC6A-N16B3](#)
[FC6A-N32B3](#) [FC6A-T16P3](#) [G3TAOD201SDC24](#) [PB32HQ](#) [PB16T](#) [PB8](#) [PB8H](#) [C200H-OD211](#) [GT1-AD04CST](#) [GT1-DA04](#) [70GRCQ24-](#)
[HS](#) [M-OAC5](#) [G4OAC24AMA](#) [2736505](#) [6202](#) [6402](#) [IL MOD BK DI8 DO4-PAC](#) [FC6A-J2C1](#) [FC6A-KC1C](#) [FC6A-N08A11](#) [FC6A-M24BR1](#)
[FC6A-K4A1](#) [FC6A-T32P3](#) [9-1393028-2](#) [GP32900003700](#) [641-480-5022](#) [PB16H](#) [WISE-4050/LAN-B](#) [WISE-S614T-A](#) [ADAM-4068-C](#)
[56475](#) [ADAM-4017+-F](#) [ADAM-4118-C](#) [AMAX-4856-B](#) [WISE-4050-B](#) [ADAM-4051-C](#) [ADAM-4053-F](#) [GT1-AD08MX](#) [TM5SDO6TBFS](#)
[70Q3446](#)