



Overview

Amphenol RF offers a full line of high-performance BNC cable assemblies utilizing a variety of popular flexible cable types. These 50 ohm assemblies are available in multiple configurations in an extensive range of standard lengths from 6 inches to 30 meters and are suitable for a number of applications including test and measurement and industrial connectivity.

BNC cable assemblies utilize high-quality BNC connectors which feature the familiar bayonet coupling mechanism for easy mating and un-mating. These connectors are manufactured from brass with nickel plating and offer reliable electrical performance up to 4 GHz.

Features and Benefits

- Bayonet coupling mechanism provides quick mating and unmating
- Various cable types allow for frequency and flexibility options
- Standard lengths from 6 inches to 30 meters available
- Vibration resistant connectors

Applications

- Telecommunications
- Test and Measurement
- Industrial Connectivity
- Antenna Connections
- Patch Panels

Amphenol RF

Four Old Newtown Road
Danbury, CT 06810

For more information visit www.amphenolrf.com
or call 800.627.7100

BNC 50 Ohm Cable Assemblies

Pre-Configured Assemblies on Flexible Cables

Ordering Information

BNC to BNC on RG-58

Part Number	Description
095-850-268XXXX	BNC Right Angle Plug to BNC Straight Jack RG-58
095-850-269XXXX	BNC Straight Plug to BNC Straight Jack RG-58

BNC to BNC on RG-142

Part Number	Description
095-850-251XXXX	BNC Right Angle Plug to BNC Right-Angle Plug RG-142
095-850-252XXXX	BNC Right Angle Plug to BNC Straight Jack RG-142
095-850-253XXXX	BNC Straight Plug to BNC Right-Angle Plug RG-142
095-850-254XXXX	BNC Straight Plug to BNC Straight Jack RG-142
095-850-255XXXX	BNC Straight Jack to BNC Straight Jack RG-142

BNC to BNC on RG-174

Part Number	Description
095-850-257XXXX	BNC Right Angle Plug to BNC Right-Angle Plug RG-174
095-850-258XXXX	BNC Right Angle Plug to BNC Straight Jack RG-174
095-850-259XXXX	BNC Straight Plug to BNC Right-Angle Plug RG-174
095-850-260XXXX	BNC Straight Plug to BNC Straight Jack RG-174
095-850-261XXXX	BNC Straight Jack to BNC Straight Jack RG-174

BNC to BNC on RG-316

Part Number	Description
095-850-265XXXX	BNC Right Angle Plug to BNC Straight Jack RG-316
095-850-266XXXX	BNC Straight Plug to BNC Right-Angle Plug RG-316
095-850-267XXXX	BNC Straight Plug to BNC Straight Jack RG-316

Note: 'XXXX' denotes length code. See available lengths in chart below.

Standard Lengths Available

Length	Length in Inches (Millimeters)
-006	6.00 in (152.40 mm)
-010	10.00 in (254 mm)
-012	12.00 in (305 mm)
-024	24.00 in (610 mm)
-036	36.00 in (914.40 mm)
-048	48.00 in (1219.20 mm)
M050	19.69 in (500 mm)
M100	39.37 in (1000 mm)
M200	196.85 in (5000 mm)

Note: Lengths listed above are standard and may vary by specific configuration. See component drawing for available options.

Amphenol® RF

Technical Specifications

Electrical

Impedance	50 Ω
Frequency Range	DC - 4 GHz*

Mechanical

Mating Cycles	500 Cycles Min.
---------------	-----------------

Environmental

Temperature Range	-40° to 85°C
RoHS	Compliant with exemption 6C

Materials

Body	Brass, Nickel Plated
Female Contact	Phosphor Bronze, Gold Plated
Male Contact	Brass, Gold Plated
Insulator	PTFE

Note: Technical specifications are typical and may vary by specific part number. Please see component drawing.

*RG-174 frequency range: DC - 1 GHz

Amphenol RF

Four Old Newtown Road
Danbury, CT 06810

For more information visit www.amphenolrf.com
or call 800.627.7100

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [RF Cable Assemblies](#) category:

Click to view products by [Amphenol](#) manufacturer:

Other Similar products are found below :

[73-6352-10](#) [73-6353-3](#) [R285001001](#) [R288940004](#) [145111-05-12.00](#) [1661-C-24](#) [1801171170914KE](#) [24P104C24J1-012](#) [24P104C24P1-006](#)
[24P104C24P1-018](#) [24P204C24J1-003](#) [172-2150-EX](#) [FCB-3030-ALT](#) [21117-046](#) [21117-050](#) [PCX-24-50](#) [24P103C24P2-003](#) [25P203C25P2-](#)
[003](#) [R284008001](#) [R285001021](#) [R285426000](#) [R288940003](#) [4814-BB-24](#) [5260-72](#) [JT2N1-CL1-1F](#) [DLP-COAX1](#) [4814-K-48](#) [115101-09-06.00](#)
[CCNTN2-MM-LL335-26](#) [73-6351-25](#) [73-6352-3](#) [73-6353-25](#) [1800920920610PJ](#) [GD0BQ0BQ024.0](#) [1-3636-600-5210](#) [TL8A-11SMA-](#)
[11SMA-01500-51](#) [R284C0351060](#) [R288940009](#) [R284C0351028](#) [R288940002](#) [9702-1SL-1](#) [PT82NSMA](#) [73-6353-10](#) [R285020301W](#) [PCX-](#)
[18-50](#) [Minibend-9](#) [Minibend-4](#) [BNC TO SMA Cable](#) [MIKROE-274](#) [Minibend-10](#)