



AD40B Digital Ammeter

- Low-cost, miniature digital ammeter
- 400 A AC range
- 4000-count display with bargraph
- Autoranging
- Data Hold
- Auto-off
- 10mA resolution



No hassle warranty

No waiting.

*No shipping
charges.*



Our commitment to high-quality products and customer service is demonstrated by our industry exclusive "No Hassle" warranty. In the unlikely event that an Amprobe Test Tool requires warranty service, any of our local dealers are authorized to replace it, on the spot.

(note: \$500 MSLP limit)

Included Accessories
Carrying case and users manual



AD40B Digital Ammeter**Data Sheet****General Specifications**

Display	3-3/4 digit LCD (max reading 3999)
Overrange Indication	"OL" indicated
Low Battery Indication	Battery symbol
Power Supply	Two (2) 1.5 V AAA batteries (UM-4)
Battery Life	Alkaline 300 hours, approx.
Maximum Jaw Opening	25.4 mm
Dimensions (WxHxD)	64 x 190 x 36 mm
Weight	250 g (incl. Battery)
Operating Temperature:	0 °C to +40 °C, < 80 % R.H. non-condensing
Storage Temperature	-10 °C to +60 °C, < 70 % R.H. non-condensing, batteries removed
Safety	EN61010-1:2001, EN61010-2-32, Pollution Degree 2
Over Voltage Category	CAT III - 600V

Specifications (23°C±5°C, <80% R.H. non-condensing)

Function	Range	Accuracy
AC Current		
	40 A, 400 A	± (2 % rdg + 10 digits)
Resolution	0.01 A in 40 A range	
Overload Protection	660 A for AC current	

Amprobe® Test Tools

website: www.Amprobe.com
email: info@amprobe.com
Everett, WA 98203
tel: 877-AMPROBE

Amprobe® Test Tools Europe

In den Engematten 14
79286 Glottertal, Germany
Tel.: +49 (0) 7684 8009 - 0

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Clamp Multimeters & Accessories](#) category:

Click to view products by [Amprobe](#) manufacturer:

Other Similar products are found below :

[I800](#) [MT-8006B](#) [3PK-NT023N](#) [MT-7057N](#) [TESTO 770-3 0590 7703](#) [AX-3550](#) [AX-M266C](#) [BM079](#) [BM089](#) [BM162](#) [BM197](#) [KEW2210R](#)
[FLUKE 80I-110S](#) [FLUKE A3002FC](#) [FLUKE I200](#) [FLUKE I310S](#) [KEW2433R](#) [KEW8112](#) [FLUKE 772](#) [ACDC-100](#) [MA440](#) [MA443](#)
[MA445](#) [FLUKE-374 FC](#) [FLUKE-1630-2FC](#) [CM42](#) [FLUKE-376 FC](#) [A193 \(800 MM\)](#) [F201](#) [F205](#) [F65](#) [DIGIFLEX 4000A 350MM](#)
[DIGIFLEX 400A 170MM](#) [DIGIFLEX 400A 250MM](#) [MN93A](#) [FLUKE I6000SFLEX-24](#) [KEW2010](#) [P1670](#) [FLK-A3004FC](#) [AMP-330-EUR](#)
[APPA SFLEX-18D](#) [UT200A](#) [UT201](#) [UT205](#) [UT205A](#) [UT206](#) [UT206A](#) [UT210A](#) [UT210B](#) [UT213A](#)