



## AX5801 | TwinSAFE drive option card

Drive-integrated safety functions:

– stop functions (STO, SS1)

Suitable for AX5000 Servo Drives from 1.5 A to 40 A:

- AX5x01-0000-0200 and -0202
- AX5x03-0000-0200 and -0202
- AX5x06-0000-0200 and -0202
- AX5112-0000-0200 and -0202
- AX5118-0000-0200 and -0202
- AX5125-0000-0200 and -0202
- AX5140-0000-0200 and -0202

Technical data	AX5801-0200
Operating voltage of the relays	24 V DC (-15 %/+20 %)
Operating voltage of the feedback contacts	24 V DC (-15 %/+20 %)
Max. switching current of the feedback contacts	0.35 A
Cross-section of the connections (use of ferrules is recommended)	0.2...1.5 mm <sup>2</sup>
Stripping length of the wires	10 mm
Current consumption (total for both relays)	50 mA
Protocol	–
Fault response time	–
Weight	approx. 85 g
Ambient temperature (operation)	see documentation
Storage temperature	-25...+70 °C
Permissible humidity	5...95 %, non-condensing
Further environmental and operating conditions	see AX5000
Approvals/markings	<a href="#">Overview of TwinSAFE Certifications (PDF)</a>
Realisation STO	hard-wired via safe inputs
Safe stop functions	Safe Torque Off (STO), Safe Operating Stop (SOS), Safe Stop 1 (SS1), Safe Stop 2 (SS2)
Safety standard	ISO 13849-1:2006 (Cat. 4, PL e) and IEC 61508 (ed.2) (SIL 3)

Ordering information	
AX5801-0200	TwinSAFE drive option card for AX5000 up to 40 A, HW 2.0: STO, SS1 (1)

Further components	
<b>AX51xx</b>	Digital Compact Servo Drives (1-channel)
<b>AX52xx</b>	Digital Compact Servo Drives (2-channel)
<b>EL6900</b>	TwinSAFE Logic
<b>KL6904</b>	TwinSAFE Logic Bus Terminal, 4 safe outputs
<b>EK1960</b>	TwinSAFE Compact Controller

## **X-ON Electronics**

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Development Tools](#) category:*

*Click to view products by [Beckhoff](#) manufacturer:*

Other Similar products are found below :

[ED430-0040-PA-K-000](#) [ENCCA-03-KH](#) [ENCCA-05-KH](#) [ENCE-03-KH](#) [ENCE-05-KH](#) [FD422-AA-000](#) [FD422S-LA-000](#) [MOT-005-05-KL](#)

[MOTE-005-03-KL](#) [MOTE-005-05-KL](#) [CX-DRIVE 2.9](#)