

CP6600-0001-0020 | 10.1-inch "Economy" Panel PC

Variants	Processor	available
CP6600-0001-0020	ARM Cortex™-A8, 1 GHz (TC3: 30)	yes

*The TwinCAT 3 performance class defines the exact ordering number for the respective TwinCAT 3 product. Please see [here](#) for an overview of the TC3 performance classes.

CP6600-0001-0020	
Housing	aluminium front with steel sheet rear cover
	all connectors at the bottom of the rear side
	1 slot for microSD flash card, accessible from the rear side
	lithium battery of the system clock, accessible from the rear side
	pull-out clamping levers for fast installation without loose parts
	protection class front side IP 54, rear side IP 20
	operating temperature 0...55 °C
Front panel	10.1-inch TFT display, resolution 1024 x 600 WSVGA
	touch screen
	without keys
Features	processor ARM Cortex™-A8, 1 GHz (TC3: 30)
	3½-inch motherboard
	1 GB DDR3 RAM
	graphic adapter integrated inside the processor
	1 on-board Ethernet adapter 10/100BASE-T with RJ45 connector
	1 on-board EtherCAT adapter with RJ45 connection
	512 MB microSD flash card
	1 serial RS232 ports and 2 USB 2.0 ports
	24 V DC power supply
	Microsoft Windows Embedded Compact 7, English

Options	10.1-inch "Economy" Panel PC with ARM Cortex™-A8
C9900-H800	2 GB microSD card, instead of 512 MB microSD card
C9900-H801	4 GB microSD card, instead of 512 MB microSD card
C9900-H806	8 GB microSD card, instead of 512 MB microSD card
C9900-U213	internal, capacitive 1-second UPS to ensure secure backup of persistent application data on the microSD flash card and 128 kbyte NOVRAM for fail-safe storage of TwinCAT process data, requires TwinCAT and Windows Embedded Compact 7
C9900-S706	TwinCAT 2 PLC runtime for Windows Embedded Compact 7
C9900-S707	TwinCAT 2 NC PTP runtime for Windows Embedded Compact 7
C9900-G072	Push-button extension for CP6x00 with landscape 10.1-inch display <ul style="list-style-type: none"> – push-button extension on the bottom side – 3 push-button keys with signal lamp, type RAFI RAFIX 22FS+, round, 30 mm – 1 emergency stop key, type RAFI RAFIX 22FS+ – Labels for push-button caps for individual marking of each push-button can be ordered as an option. – The emergency stop key is wired with two normally-closed contacts, the red push-button with one normally-closed contact and the remaining push-buttons each with one normally-open contact to a terminal row. – Additionally, all push-buttons are transmitted with a normally-open contact via USB. – The LEDs of the push-buttons are controlled via USB only.
C9900-G073	Push-button extension for CP6x00 with landscape 10.1-inch display <ul style="list-style-type: none"> – push-button extension on the bottom side – 3 push-button keys with signal lamp, type RAFI RAFIX 22FS+, round, 30 mm – 1 emergency stop key, type RAFI RAFIX 22FS+ – Labels for push-button caps for individual marking of each push-button can be ordered as an option. – The emergency stop key and the red push-button are wired each with two normally-closed contacts to a terminal row. The remaining push-buttons are wired each with two normally-open contacts to a terminal row. – The LEDs of the push-buttons are wired to a terminal row.

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Controllers](#) category:

Click to view products by [Beckhoff](#) manufacturer:

Other Similar products are found below :

[CS1WCN223](#) [CS1WCN713](#) [CS1WKS001E](#) [61F-11NH](#) [61FGPN8DAC120](#) [61F-GP-NT AC110](#) [61F-GPN-V50-AC110](#) [70177-1011](#) [F03-03](#)
[HAS B](#) [F03-03 HAS C](#) [F03-31](#) [81513201](#) [81513535](#) [81550401](#) [FT1A-C12RA-W](#) [88981106](#) [H2CAC24A](#) [R88A-CAGA005S](#) [R88A-](#)
[CRGB003CR-E](#) [R88ARR080100S](#) [R88A-TK01K](#) [DCN1-1](#) [DTB4896VRE](#) [DTB9696CVE](#) [DTB9696LVE](#) [MR-50LF+](#) [E53-AZ01](#) [E53E8C](#)
[E5CWLQ1TCAC100240](#) [B300LKL21](#) [NE1ASCPU02EIPVER11](#) [NE1SCPU01](#) [NE1SDRM21U](#) [NSCXDC1V3](#) [NSH5-232CW-3M](#)
[NT20SST122BV1](#) [NV3Q-SW41](#) [NV4W-ATT01](#) [NV-CN001](#) [OAS-160-N](#) [K31S6](#) [K33-L1B](#) [K3TX-AD31A](#) [L595020](#) [SRS2-1](#) [G32X-V2K](#)
[26546803](#) [26546805](#) [26546831](#) [CJ1W-OD204](#)