



EL2622 | 2-channel relay output terminal 230 V AC, 5 A, potential-free make contacts, no power contacts

The EL2622 output terminal has two relays each of which has a single contact and can be generally used for switching devices requiring mains power. The EtherCAT Terminal indicates its signal state by means of light emitting diodes. The EL2622 has potential-free contacts. The power contacts are not looped through.

Technical data	EL2622 ES2622
Connection technology	relay output
Number of outputs	2 x make contacts
Nominal voltage	230 V AC/30 V DC
Load type	ohmic, inductive, lamp load
Distributed clocks	–
Ohmic switching current	5 A AC/DC per channel
Inductive switching current	2 A AC/DC per channel
Minimum permitted load	10 mA at 5 V DC
Lamp test, electronic ballast	4 x 58 W
Current consumption E-bus	typ. 170 mA
Electrical isolation	500 V (E-bus/field potential)
Current consumption power contacts	–
Bit width in the process image	2 outputs
Operating cycles mech. (min.)	2 x 10 ⁷
Operating cycles electr. (min.)	1 x 10 ⁵ (5 A/30 V DC)
Configuration	no address or configuration setting
Special features	–
Weight	approx. 50 g
Operating/storage temperature	0...+55 °C/-25...+85 °C
Relative humidity	95 %, no condensation
Vibration/shock resistance	conforms to EN 60068-2-6/EN 60068-2-27
EMC immunity/emission	conforms to EN 61000-6-2/EN 61000-6-4
Protect. class/installation pos.	IP 20/variable
Pluggable wiring	for all ESxxxx terminals
Approvals	CE, UL

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Controllers](#) category:

Click to view products by [Beckhoff](#) manufacturer:

Other Similar products are found below :

[CS1WCN223](#) [CS1WCN713](#) [CS1WKS001E](#) [61F-11NH](#) [61FGPN8DAC120](#) [61F-GP-NT AC110](#) [61F-GPN-V50-AC110](#) [70177-1011](#) [F03-03](#)
[HAS B](#) [F03-03 HAS C](#) [F03-31](#) [81513201](#) [81513535](#) [81550401](#) [FT1A-C12RA-W](#) [88981106](#) [H2CAC24A](#) [R88A-CAGA005S](#) [R88A-](#)
[CRGB003CR-E](#) [R88ARR080100S](#) [R88A-TK01K](#) [DCN1-1](#) [DTB4896VRE](#) [DTB9696CVE](#) [DTB9696LVE](#) [MR-50LF+](#) [E53-AZ01](#) [E53E8C](#)
[E5CWLQ1TCAC100240](#) [B300LKL21](#) [NE1ASCPU02EIPVER11](#) [NE1SCPU01](#) [NE1SDRM21U](#) [NSCXDC1V3](#) [NSH5-232CW-3M](#)
[NT20SST122BV1](#) [NV3Q-SW41](#) [NV4W-ATT01](#) [NV-CN001](#) [OAS-160-N](#) [K31S6](#) [K33-L1B](#) [K3TX-AD31A](#) [L595020](#) [SRS2-1](#) [G32X-V2K](#)
[26546803](#) [26546805](#) [26546831](#) [CJ1W-OD204](#)