



EL4028 | 8-channel analog output terminal 4...20 mA, 12bit

The EL4028 analog output terminal generates signals in the range between 4 and 20 mA. The power is supplied to the process level with a resolution of 12 bits and is electrically isolated. Ground potential for the output channels of the EtherCAT Terminal is common with the 24 V DC supply. The output stages are powered by the 24 V supply. The EL4028 combines eight channels in one housing. The signal state of the EtherCAT Terminal is indicated by light emitting diodes.

| Technical data | EL4028 ES4028 |
|------------------------------------|---|
| Connection technology | 1-wire, single-ended |
| Number of outputs | 8 |
| Power supply | 24 V DC via power contacts |
| Signal current | 4...20 mA |
| Distributed clocks | yes |
| Distributed clock precision | << 1 μ s |
| Load | < 150 Ω |
| Output error | < 0.1 % (relative to end value) |
| Resolution | 12 bit |
| Electrical isolation | 500 V (E-bus/signal voltage) |
| Conversion time | ~ 400 μ s |
| Current consumption power contacts | typ. 60 mA |
| Current consumption E-bus | typ. 100 mA |
| Bit width in the process image | 8 x 16 bit AO output |
| Special features | Optional watchdog: user-specific output value with ramp; user synchronisation can be activated. |
| Weight | approx. 60 g |
| Operating/storage temperature | -25...+60 °C/-40...+85 °C |
| Relative humidity | 95 %, no condensation |
| Vibration/shock resistance | conforms to EN 60068-2-6/EN 60068-2-27 |
| EMC immunity/emission | conforms to EN 61000-6-2/EN 61000-6-4 |
| Protect. class/installation pos. | IP 20/variable |
| Pluggable wiring | for all ESxxx terminals |
| Approvals/markings | CE, UL, ATEX |
| Ex-Marking | II 3 G Ex nA IIC T4 Gc |

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Controllers](#) category:

Click to view products by [Beckhoff](#) manufacturer:

Other Similar products are found below :

[CS1WCN223](#) [CS1WCN713](#) [CS1WKS001E](#) [61F-11NH](#) [61FGPN8DAC120](#) [61F-GP-NT AC110](#) [61F-GPN-V50-AC110](#) [70177-1011](#) [F03-03](#)
[HAS B](#) [F03-03 HAS C](#) [F03-31](#) [81513201](#) [81513535](#) [81550401](#) [FT1A-C12RA-W](#) [88981106](#) [H2CAC24A](#) [R88A-CAGA005S](#) [R88A-](#)
[CRGB003CR-E](#) [R88ARR080100S](#) [R88A-TK01K](#) [DCN1-1](#) [DTB4896VRE](#) [DTB9696CVE](#) [DTB9696LVE](#) [MR-50LF+](#) [E53-AZ01](#) [E53E8C](#)
[E5CWLQ1TCAC100240](#) [B300LKL21](#) [NE1ASCPU02EIPVER11](#) [NE1SCPU01](#) [NE1SDRM21U](#) [NSCXDC1V3](#) [NSH5-232CW-3M](#)
[NT20SST122BV1](#) [NV3Q-SW41](#) [NV4W-ATT01](#) [NV-CN001](#) [OAS-160-N](#) [K31S6](#) [K33-L1B](#) [K3TX-AD31A](#) [L595020](#) [SRS2-1](#) [G32X-V2K](#)
[26546803](#) [26546805](#) [26546831](#) [CJ1W-OD204](#)