



## KL2634 | 4-channel relay output terminal 250 V AC/30 V DC

The KL2634 output terminal has four relays, each of which has a single contact. The relay contact is suitable for use at up to 250 V AC or 30 V DC. The Bus Terminal indicates its signal state by means of light emitting diodes. The KL2634 is equipped with potential-free contacts.

Technical data	KL2634   KS2634
Connection technology	relay output
Number of outputs	4 x make contacts
Nominal voltage	250 V AC/30 V DC
Load type	ohmic, inductive
Max. output current	4 A per channel
Switching current	4 A AC/DC (ohmic)/2 A AC/DC (inductive)
Ohmic switching current	4 A AC/DC per channel
Inductive switching current	2 A AC/DC per channel
Minimum permitted load	0.1 mA at 0.1 V DC (at 120 operations/min.)
Electrical isolation	500 V (K-bus/field potential)
Current consumption power contacts	–
Current consumption K-bus	typ. 120 mA
Bit width in the process image	4 outputs
Operating cycles mech. (min.)	2 x 10 <sup>7</sup> (at 18 x 10 <sup>3</sup> switching cycles per hour)
Operating cycles electr. (min.)	1 x 10 <sup>5</sup> (3 A/30 V DC ohmic load)
Configuration	no address or configuration setting
Weight	approx. 70 g
Operating/storage temperature	0...+55 °C/-25...+85 °C
Relative humidity	95 %, no condensation
Vibration/shock resistance	conforms to EN 60068-2-6/EN 60068-2-27
EMC immunity/emission	conforms to EN 61000-6-2/EN 61000-6-4
Pluggable wiring	for all KSxxxx Bus Terminals
Approvals/markings	CE

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Controllers](#) category:*

*Click to view products by [Beckhoff](#) manufacturer:*

Other Similar products are found below :

[CS1WCN223](#) [CS1WCN713](#) [CS1WKS001E](#) [61F-11NH](#) [61FGPN8DAC120](#) [61F-GP-NT AC110](#) [61F-GPN-V50-AC110](#) [70177-1011](#) [F03-03](#)  
[HAS B](#) [F03-03 HAS C](#) [F03-31](#) [81513201](#) [81513535](#) [81550401](#) [FT1A-C12RA-W](#) [88981106](#) [H2CAC24A](#) [R88A-CAGA005S](#) [R88A-](#)  
[CRGB003CR-E](#) [R88ARR080100S](#) [R88A-TK01K](#) [DCN1-1](#) [DTB4896VRE](#) [DTB9696CVE](#) [DTB9696LVE](#) [MR-50LF+](#) [E53-AZ01](#) [E53E8C](#)  
[E5CWLQ1TCAC100240](#) [B300LKL21](#) [NE1ASCPU02EIPVER11](#) [NE1SCPU01](#) [NE1SDRM21U](#) [NSCXDC1V3](#) [NSH5-232CW-3M](#)  
[NT20SST122BV1](#) [NV3Q-SW41](#) [NV4W-ATT01](#) [NV-CN001](#) [OAS-160-N](#) [K31S6](#) [K33-L1B](#) [K3TX-AD31A](#) [L595020](#) [SRS2-1](#) [G32X-V2K](#)  
[26546803](#) [26546805](#) [26546831](#) [CJ1W-OD204](#)