



KL6821 | DALI/DALI 2 multi-master and power supply terminal

The KL6821 enables the connection of up to 64 DALI/DALI 2 slaves and 64 DALI input devices. The KS2000 software enables simple configuration via a PC that is directly coupled with the Bus Coupler via an RS232 interface or via the fieldbus. The integrated power supply unit generates an electrically isolated 24 V DC output voltage. No further components are required for the operation of the DALI/DALI 2 devices. The KL6821 operates fieldbus-independent.

Technical data	KL6821
Technology	DALI/DALI 2
Number of channels	1
Slaves/groups	max. 64 DALI/DALI 2 slaves and 64 DALI input devices; max. 16 groups
Data transfer channels	1
Data transfer standard	DALI + DALI 2
Data transfer rates	1200 baud
Current consumption K-bus	typ. 55 mA
Short-circuit proof	yes
Electrical isolation	500 V (K-bus/DALI-bus)
Bit width in the process image	input/output: 4 x 8 bit user data, 1 x 8 bit control/status (up to 5 x 8 bit user data are possible)
Configuration	via the Bus Coupler or the controller
Nominal voltage	24 V DC (-15 %/+20 %)
Input voltage	24 V DC (-15 %/+20 %)
Insulation voltage	DALI-bus/K-bus: 1,500 V DC, DALI-bus/power contacts: 1,500 V DC
DALI power supply	max. 250 mA
Surge voltage resistance	constant load 275 V AC _{rms}
Special features	2 digital inputs for simplified installation; TwinCAT library: TwinCAT PLC DALI
Weight	approx. 80 g
Operating/storage temperature	0...+55 °C/-25...+85 °C
Relative humidity	95 %, no condensation
Vibration/shock resistance	conforms to EN 60068-2-6/EN 60068-2-27
EMC immunity/emission	conforms to EN 61000-6-2/EN 61000-6-4
Protect. class/installation pos.	IP 20/variable
Approvals/markings	CE

System	
subsystem	For further subsystem products please see the system overview .

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Controllers](#) category:

Click to view products by [Beckhoff](#) manufacturer:

Other Similar products are found below :

[CS1WCN223](#) [CS1WCN713](#) [CS1WKS001E](#) [61F-11NH](#) [61FGPN8DAC120](#) [61F-GP-NT AC110](#) [61F-GPN-V50-AC110](#) [70177-1011](#) [F03-03](#)
[HAS B](#) [F03-03 HAS C](#) [F03-31](#) [81513201](#) [81513535](#) [81550401](#) [FT1A-C12RA-W](#) [88981106](#) [H2CAC24A](#) [R88A-CAGA005S](#) [R88A-](#)
[CRGB003CR-E](#) [R88ARR080100S](#) [R88A-TK01K](#) [DCN1-1](#) [DTB4896VRE](#) [DTB9696CVE](#) [DTB9696LVE](#) [MR-50LF+](#) [E53-AZ01](#) [E53E8C](#)
[E5CWLQ1TCAC100240](#) [B300LKL21](#) [NE1ASCPU02EIPVER11](#) [NE1SCPU01](#) [NE1SDRM21U](#) [NSCXDC1V3](#) [NSH5-232CW-3M](#)
[NT20SST122BV1](#) [NV3Q-SW41](#) [NV4W-ATT01](#) [NV-CN001](#) [OAS-160-N](#) [K31S6](#) [K33-L1B](#) [K3TX-AD31A](#) [L595020](#) [SRS2-1](#) [G32X-V2K](#)
[26546803](#) [26546805](#) [26546831](#) [CJ1W-OD204](#)