

Mid-Plane RJ45 Connectors

Stewart Connector's Mid-Plane RJ45 connectors are designed to have a reliable RJ45 connector with a lowered profile. These jacks optimize the real estate available on the board. Stewart's Mid-Plane RJ45 connectors are available in both single port and four port options. The single port Mid-Plane connectors are available with both yellow/green and bi-color LEDs.

Features & Benefits

- Both single and four port connectors available
- Cat5e - supports 1G and 2.5G data rates and 100 MHz transmission frequencies
- All configurations are right angle with a tab up design
- Four port design features 30 micro inches of gold plating on the contacts
- Single port designs feature 50 micro inches of gold plating on the contacts
- All available options are shielded
- Operating temperatures -40°C to 85°C
- LED options available
- RoHS compliant

Applications

- IoT applications
- Servers and switches
- Video game systems
- Portable storage devices
- Home and office equipment

Part Numbers

Part Number	Ports	LEDs	Recommended PCB Thickness		Tail Length	
			in	mm	in	mm
SS-74800-142	Single	Bi-Color	0.062in	1.57mm	0.085in	2.159mm
SS-74800-139	Single	Yellow/Green	0.062in	1.57mm	0.085in	2.159mm
SS-74800-125	Four (1x4)	Green	0.093in	2.36mm	0.125in	3.175mm
SS-74800-143	Single	None	0.062in	1.57mm	0.085in	2.159mm
SS-74800-144	Single	Yellow/Green	0.093in	2.36mm	0.125in	3.175mm
SS-74800-145	Single	None	0.093in	2.36mm	0.125in	3.175mm
SS-74800-146	Single	Bi-Color	0.093in	2.36mm	0.125in	3.175mm



Stewart Connector
11118 Susquehanna Trail South
Glen Rock, PA 17327-9199

+1 717.235.7512
techhelp@belf.com
belfuse.com/stewart-connector

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Modular Connectors / Ethernet Connectors](#) category:

Click to view products by [Bel Fuse](#) manufacturer:

Other Similar products are found below :

[8949-H88/06BLKA/SN](#) [74441-0010/BKN](#) [MP1010RX-1000](#) [MP44RX-1000](#) [PHJ-4P4C-1-V-4](#) [PHP-6P6C-5](#) [GAX-3-66](#) [GAX-8-62](#) [GDCX-PA-66-50](#) [GDCX-PN-64](#) [GDCX-PN-66](#) [GDCX-PN-66-50](#) [GDLX-A-66](#) [GDLX-N-66](#) [GDLX-S-66](#) [GDLX-S-88K](#) [GDLX-SMT-S-88](#) [GDTX-S-88-50](#) [GDX-PA-1010](#) [GLX-N-1010M-BLK](#) [GLX-S-88M-BLK](#) [GMX-N-1010](#) [GMX-S-1010](#) [GMX-S-66](#) [GMX-SMT4-N-88](#) [GPX-2-64](#) [GSGX-N-2-88](#) [GSGX-N-4-88](#) [GSX-NS2-88-3.05](#) [GSX-NS2-88-3.05-50](#) [GSX-NS-88-3.05-50](#) [PT-108A-8C-UL](#) [PT-J951-8C](#) [PTS-J531-8CS-50UL](#) [1-1775629-2](#) [A-2014-0-4](#) [GWLX-S-88-GR](#) [GWLX-S9-88-YG](#) [DC-1021-8-WH-6](#) [1300530003](#) [1324640-4](#) [RJ11FTVC2G](#) [RJ11FTVC2N](#) [RJFTVX2SA1G](#) [132764-001](#) [1413235](#) [MP88X-1000](#) [MPS88RX-5000](#) [E5288-S000K3-L](#) [E5908-15A242-L](#)