



pkg.	wt.	part no.
500	0.5 g	46.112.1001.50

ENEC Rating	9A / 320V
URus Rating:	9A / 300V
cUR Rating:	3A / 300V

**SMD Push through terminal block - 2 pole**  
**For wiring below the PCB / metal work**  
 Solder fixing

Housing: PPA  
 Contacts: Cu alloy

Approval: additional cURus

- No tools required! Wires can be released by twisting and pulling the wire simultaneously.
- Terminal block and ballast on same working level
- Note 1: Maximum thickness of PCB and heatsink should not exceed 3.6 mm
- Note 2: Recommendation for opening in heatsink is shown with minimum diameter. For other shaped pockets in heatsink the minimum creepage and clearance distances and manufacturing tolerances have to be considered.
- Note 3: Recommended dimension for opening in PCB
- Note 4: Recommended dimension for solder mask
- Note 5: For metal core PCBs the minimum creepage distance has to be guaranteed
- Note 6: Recommended pick & place area #1
- Note 7: Recommended pick & place area #2 inside of the connector. Max. diameter of nozzle is 2.5 mm.
- Note 8: Distance from center of mass to pick and place area #1 and #2
- General note: It is recommended to make an electrical connection between both poles of each polarity on the solder mask

LED-LINE	U <sub>imp</sub> 2,5 kV			
			0.20-0.75 mm <sup>2</sup>	0.20-0.75 mm <sup>2</sup>

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [LED Lighting Mounting Accessories](#) category:*

*Click to view products by [BJB](#) manufacturer:*

Other Similar products are found below :

[C16142\\_HEKLA-SOCKET-K](#) [3SU1401-1BG20-1AA0](#) [3SU1900-0BC31-0NB0](#) [ES16-RT](#) [1SFA616921R2042](#) [1SFA616921R2131](#)  
[1SFA616921R2133](#) [1SFA616921R2143](#) [1SFA611621R1093](#) [90100002](#) [B8910020](#) [D3980022](#) [E3990022](#) [E3990040](#) [V4840019](#) [V4850019](#)  
[CABI12 E BK 1M SET PRM](#) [FLAT8 H/U BK 1M SET PRM](#) [BEGTIN12 J/S BK 1M SET PRM](#) [1-2213678-6](#) [C16791\\_CLAMP-Z45-A](#)  
[F17250\\_SOLDER-CLIP-A](#) [CM22-4-20MA](#) [CM22-R10K-MT](#) [CM22-R1K](#) [CM22-R50K](#) [CM22-R5K-MT](#) [CM22-SLR](#) [10465](#) [M22-A](#) [M22-](#)  
[CK11](#) [M22-CK20](#) [M22-K01](#) [M22-LCH-W](#) [M22-LC-R](#) [M22-LED230-R](#) [M22-LED230-W](#) [M22-LEDC230-G](#) [M22-LEDC-G](#) [M22-LEDC-W](#)  
[M22-LED-G](#) [M22-LED-W](#) [M22-L-G](#) [M22-LH-G](#) [M22-LH-R](#) [M22-LH-W](#) [M22-L-R](#) [M22-L-W](#) [M22-L-X](#) [M22-MS](#)