

Data Sheet

Digital Milli-Ohm Meter Model 310

The model 310 Digital Milli-Ohm Meter is used to ensure continuity and integrity of a wire, cable, conduit or any electrical connection. The 310 has a display resolution of 100 micro-ohms and has a professional four wire Kelvin test lead set included to ensure accurate readings. The heavy duty case has a rubber seal to make the unit water resistant and a convenient shoulder strap.


Features & Benefits

- Four wire Kelvin lead measurements
- Over-voltage and over-temperature protection
- 5 ranges with 100 $\mu\Omega$ max. resolution
- Water resistant case with shoulder strap
- Auto Power Off
- IEC/EN 61010-1 / CE
- Included: 4-wire Kelvin leads, carrying case with shoulder strap and batteries



Specifications	310
Electrical	
Measuring ranges	0-200.0 m Ω in steps of 100 $\mu\Omega$ 0-2000 m Ω in steps of 1 m Ω 0-20.00 Ω in steps of 10 m Ω 0-200.0 Ω in steps of 100 m Ω 0-2000 Ω in steps of 1 Ω
Accuracy	$\pm 0.5\%$ of reading ± 2 digits over the operating temperature range -15 $^{\circ}$ C to +55 $^{\circ}$ C, with the supplied test leads.
Test current	1 mA => 2000 Ω range 10 mA => 200 / 20 Ω ranges 100 mA => 2000 m / 200 m Ω ranges.
Test current accuracy	$\pm 0.3\%$
Protection fuses	Supply: 1.5 A, HBC, 5 x 20 mm, DIN Current: 1 A, HBC, 5 x 20 mm, DIN Voltage: 0.5 A, HBC, 5 x 20 mm, DIN
Safety	LVD BS EN 61010-1 EMC BS EN 50081-1, BS EN 50082-1
Mechanical	
Bump test	IEC68-2-29
Vibration test	IEC1010, clause 8.3
Drop test	IEC1010, clause 8.4
Impact test	IEC1010, Clause 8.2
Rated environmental conditions	Indoor use Pollution degree 2 Altitude up to 2000 meter Relative humidity 80% max. Ambient temperature 0 $^{\circ}$ C~40 $^{\circ}$ C
One Year Warranty	
Weight	3.4 lbs (1.542 kg)
Dimensions (WxHxD)	9.82" x 4.33" x 7.48" (250 x 110 x 190 mm)

Simplified Measurement



Applications

The model 310 Digital milli-ohm meter, with its measuring range of 100 $\mu\Omega$ to 2000 Ω , is suitable for a wide range of applications such as:

- Measuring the winding resistance of electric motors, generators and transformers
- Bond testing in mines, aircraft, railways, ships, domestic and industrial wiring installations
- Measuring the ring main continuity testing in industrial and domestic wiring installations
- Measuring resistance in electronic equipment such as shunts, pcb tracks, switch and relay resistance
- Checking compression joints on overhead lines
- Testing and maintenance of switchboard /sub-station equipment on such items as fuses, joints, contacts and bonds

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Digital Multimeters](#) category:

Click to view products by [B&K Precision](#) manufacturer:

Other Similar products are found below :

[6111-517](#) [FS881](#) [40705X](#) [C.A 6133 LAUNCH KIT](#) [P 1070](#) [P 3315](#) [P 3340](#) [KEWMATE 2000A](#) [P 3725](#) [SEFRAM7202](#) [SEFRAM7303](#)
[AMP-220-EUR KIT2](#) [BS K-CLIP](#) [HD110C](#) [P 2005 A](#) [IBT6K](#) [AX-573](#) [1000-219](#) [1001-613](#) [1006-969](#) [1008-221](#) [30XR](#) [34XR](#) [35XP](#)
[TESTO 745](#) [0590 7450](#) [TESTO 760-2](#) [0590 7602](#) [TESTO 760-3](#) [0590 7603](#) [440012](#) [AX-155](#) [AX-174](#) [AX-178](#) [AX-18B](#) [AX-190A](#) [AX-503](#)
[AX-507B](#) [AX-594](#) [AX-LCR42A](#) [AX-MS8250](#) [AX-PDM01](#) [AX-T520](#) [AX-T901](#) [AX-T903](#) [BAT-250-EUR](#) [BM525S](#) [BM805S](#) [BM807S](#)
[BM817S](#) [BM827S](#) [BM829S](#) [BM857S](#)