

Data Sheet

Triple Output DC Power Supplies Models 1670A and 1671A

These triple output DC power supplies are ideal for general electronic servicing, school electronics labs, and powering up hobbyist's projects.

Model	1670A	1671A
Output Parameters		
Number of Outputs	Three (1 variable, 2 fixed)	
Range	0-30 V / 0-3 A (variable) 12 V \pm 5% / 500 mA (fixed) 5 V \pm 5% / 500 mA (fixed)	0-30 V / 0-5 A (variable) 12 V \pm 5% / 500 mA (fixed) 5 V \pm 5% / 500 mA (fixed)
Constant Voltage Operation		
Line Regulation	\leq 0.05% + 10 mV (main) \leq 1% (fixed output)	
Load Regulation	\leq 0.05% + 10 mV (main) \leq 1% (fixed output)	
Ripple & Noise	\leq 5 mV rms	
Constant Current Operation		
Adjustable Current Range	5% to 100% (Main)	
Line Regulation	\leq 0.4% + 10 mA	
Load Regulation	\leq 0.4% + 10 mA	
Ripple & Noise	\leq 10 mA rms	
Metering		
Display	3-digit LCDs	
Voltmeter Resolution	0.1 V	
Voltmeter Accuracy	\pm (1% reading + 2 digits)	
Ammeter Resolution	0.01 A	
Ammeter Accuracy	\pm (1% reading + 2 digits)	
General		
Overload Protection	Current limiting, Reverse polarity, Overvoltage, Short circuit	
AC Input	115/230 VAC, 50/60 Hz	
Power Consumption	165 W	265 W
Operating Temperature	0° to 40°C < 10-80% R.H.	
Storage Temperature	-15° to 70°C < 85% R.H.	
Dimensions (H x W x D)	4.9" x 8.5" x 9.5" (124 x 216 x 242 mm)	4.9" x 8.5" x 11.5" (124 x 216 x 292 mm)
Weight	10 lbs (4.5 kg)	14.3 lbs (6.5 kg)
One-Year Warranty		
Included Accessories	Instruction manual and spare fuse	



Model 1671A

- One variable 0 - 30 VDC,
0 - 3 A variable section (1670A)
0 - 5 A variable section (1671A)
- One 12 VDC fixed section
- One 5 VDC fixed section
- Constant voltage (CV) and constant current (CC) operation modes
- Short circuit and reverse polarity protection

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Benchtop Power Supplies](#) category:

Click to view products by [B&K Precision](#) manufacturer:

Other Similar products are found below :

[PR20](#) [ZUPNC402](#) [PSW 800-1.44](#) [2306](#) [UDP6730](#) [UDP6731](#) [UDP6720](#) [NGA142](#) [UDP3305S-E](#) [GRA-454](#) [UDP3305C](#) [UDP6721](#)
[MX103QP S2](#) [MX100Q S2](#) [UDP3305S](#) [MX100QP S2](#) [MX103Q S2](#) [GPP-3610H-GPIB](#) [GPP-7250-GPIB](#) [GRA-422](#) [CPX200DP](#) [AX-3003P](#)
[AX-6003P](#) [AX-8450A](#) [TPM-3003](#) [HMC8012](#) [HMP2020](#) [HMP4040](#) [UT804](#) [1405](#) [1410](#) [XLNRC](#) [Z-NL200](#) [Z-U](#) [1513](#) [1550](#) [EA-PS](#)
[805-12-12-80](#) [TRIPLE](#) [1652](#) [1665](#) [1666](#) [1673](#) [1694](#) [1698](#) [MX100TP](#) [1739](#) [TPM-3005](#) [1902B](#) [9174B](#) [GDM-8245](#) [GDM-8255A](#)