

BR1 - Solderable PC BreadBoard



Transfer your circuit to this permanent circuit board from a plug-in breadboard to create a rugged long-lasting prototype.

Features

- Transfer your circuit and wires without recutting wires or changing your layout.

The BR1 Solderable BreadBoard has the same pattern and spacing as a standard 830 connection point solderless breadboard.

- Soldered joints provide a more reliable longterm connection than solderless contacts.
- Standard 5-hole strip for each IC pin, just like solderless breadboards.
- Four power rails like solderless breadboards plus two bonus rails for power or signals.
- Bonus two-hole pads along the centerline allow DIL (dual in-line) headers to be used.
- **Lead free** etched copper PCB with an anti-tarnish coating for easy soldering.
- 0.1" hole spacing for DIP integrated circuits and headers.
- Four PCB mounting holes provided.

Specifications


- High-quality etched FR4 glass-epoxy circuit board.

- Single sided, 1oz/ft² copper with an anti-tarnish coating for easy soldering.
- Holes are drilled on 0.1" (2.54mm) centers.
- 0.042" (1.07mm) holes sized for ICs or square post headers.
- 1226 holes.
- 1.85" wide, 7.05" long, 1/16" thick (47 x 179 x 1.6mm).


Order Part# BR1

Related Parts: **BB830** and **BB830T** breadboards have the same layout in a solderless plug-in breadboard.

Note: The **SB830** Solderable PC BreadBoard is similar to BR1, and it has a silkscreen on the top side.



Board Layout (actual size)



X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for PCBs & Breadboards category:

Click to view products by [BusBoard Prototype manufacturer](#):

Other Similar products are found below :

[8004](#) [8007](#) [8016](#) [8017](#) [8028](#) [8029](#) [1268-12](#) [1268-10](#) [1320833-1](#) [923252-R](#) [3410](#) [3396](#) [8006](#) [8015](#) [8018](#) [8019](#) [8020](#) [1268-19](#) [1268-20](#)
[8026](#) [1239-19](#) [SBBTH1520-1](#) [SBBTH1506-1](#) [SBBTH4080-1](#) [SBBTH3030-1](#) [SBBTH1512-1](#) [SBBTH1508-1](#) [SBBSM2120-1](#) [SBB2808-1](#)
[SBB2805-1](#) [SBB1605-1](#) [SBB1602-1](#) [SBB1005-1](#) [SBB1002-1](#) [3426](#) [32P15WE](#) [ZAS1X206203XRPU160](#) [SBBTH3040-1](#) [SBB0004-1](#)
[SBB830-QTY10](#) [7115](#) [923749-I](#) [RE013-LF](#) [RE014-LF](#) [RE015-LF](#) [RE1210-LF](#) [RE200-C3](#) [RE210-S1](#) [RE317-HP](#) [RE438-LF](#)